

By the same Author.

FRAGMENTS OF SCIENCE:

A SERIES OF DETACHED ESSAYS, ADDRESSES, AND REVIEWS.

New Edition, being the Fifth, revised throughout, with Additions
and a NEW INTRODUCTION.

Crown 8vo. price 10s. 6d.

The Optical Condition of the
Atmosphere, in its Bear-
ings on Putrefaction and
Infection.

PART I.

- I. The Constitution of Na-
ture. 1865.
- II. Radiation. 1865.
- III. On Radiant Heat in Re-
lation to the Colour
and Chemical Consti-
tution of Bodies. 1866.
- IV. New Chemical Reactions
produced by Light.
- V. On Dust and Disease.
1870.
- VI. Voyage to Algeria to
Observe the Eclipse.
1870.
- VII. Niagara. 1872.
- VIII. Life and Letters of Fara-
day. 1870.
- IX. The Copley Medalist of
1870.
- X. The Copley Medalist of
1871.
- XI. Elementary Magnetism.
- XII. Death by Lightning.
- XIII. Science and the 'Spirits.

PART II.

NEW INTRODUCTION, em-
bracing Reflections on
Materialism.

- I. Reflections on Prayer and
Natural Law.
- II. Miracles and Special Pro-
vidences. 1867.
- III. Scientific Materialism.
1868.
- IV. Scientific use of the Im-
agination. 1870.
- V. Vitality. 1865.
- VI. On Prayer as a Form
of Physical Energy.
1872.
- VII. The Belfast Address.
1874.
Apology for the Belfast
Address.
- VIII. Crystals and Molecular
Force. 1874.
- Letter from the 'Times'
of November 9, 1874.

London, LONGMAN & CO.

Works by the same Author.

SOUND.

Third Edition, revised and augmented, including Recent Researches on Fog-Signalling; with Portrait and 190 Woodcuts and Diagrams. Crown 8vo. 10s. 6d.

HEAT a MODE of MOTION.

New Edition, being the Fifth; with a Plate and 110 Woodcuts and Diagrams. Crown 8vo. price 10s. 6d.

LECTURES on LIGHT DELIVERED in the UNITED STATES of AMERICA in 1872 and 1873. Second Edition, with Portrait, Lithographic Plate and 59 Diagrams. Crown 8vo. price 7s. 6d.

NOTES of a COURSE of NINE LECTURES on LIGHT, delivered at the Royal Institution of Great Britain, A.D. 1869. Crown 8vo. price 1s. sewed, or 1s. 6d. cloth.

NOTES of a COURSE of SEVEN LECTURES on ELECTRICAL PHENOMENA and THEORIES, delivered at the Royal Institution of Great Britain, A.D. 1870. Crown 8vo. price 1s. sewed, or 1s. 6d. cloth.

RESEARCHES on DIAMAGNETISM, and MAGNE-CRYSTALLIC ACTION; including the Question of Diamagnetic Polarity. With Six Copperplates and numerous Woodcut Illustrations. 8vo. price 14s.

CONTRIBUTIONS to MOLECULAR PHYSICS in the DOMAIN of RADIANT HEAT. With Two Plates and Thirty-one Woodcuts. 8vo. price 16s.

FARADAY as a DISCOVERER.

New and Cheaper Edition, with Two Portraits. Fcp. 8vo. price 3s. 6d.

London, LONGMANS & CO.

ELECTRICITY

LONDON : PRINTED BY
SPOTTISWOODE AND CO., NEW-STREET SQUARE
AND PARLIAMENT STREET

LESSONS
IN
ELECTRICITY

AT THE ROYAL INSTITUTION

1875-6

BY

JOHN TYNDALL, D.C.L., LL.D., F.R.S.

PROFESSOR OF NATURAL PHILOSOPHY
IN THE ROYAL INSTITUTION OF GREAT BRITAIN

LONDON
LONGMANS, GREEN, AND CO.
1876

All rights reserved

I wish to inscribe this book to Five Young Friends, whose names, in the approximate order of their ages, are here set down :—*

HUGH SPOTTISWOODE,

HENRY HUXLEY,

ROLFE LUBBOCK,

JOHN CLAUSIUS,

REGINALD HOOKER.

J. T.

* I write in Switzerland, and have to rely upon my memory, hence my uncertainty.

NOTE.—*A Price List of the Apparatus suitable for the experiments described in these Lessons will be found at the end of the volume. The prices are very reasonable, but the teacher or learner may materially reduce the cost by becoming his own instrument-maker.*

PREFACE.

MORE than fifty years ago the Board of Managers of the Royal Institution resolved to extend its usefulness, as a centre of scientific instruction, by giving, during the Christmas and Easter holidays of each year, two courses of Lectures suited to the intelligence of boys and girls.

On December 12, 1825, a Committee appointed by the Managers reported 'that they had consulted Mr. Faraday on the subject of engaging him to take a part in the juvenile lectures proposed to be given during the Christmas and Easter recesses, and they found his occupations were such that it would be exceedingly inconvenient for him to engage in such lectures.'

Faraday's holding aloof was, however, but temporary, for at Christmas 1827 we find him giving a 'Course of Six Elementary Lectures on Chemistry, adapted to a Juvenile Auditory.'

The Easter lectures were soon abandoned, but from the date mentioned to the present time the Christmas

lectures have been a marked feature of the Royal Institution.¹

Last Christmas it fell to my lot to give one of these courses. I had heard doubts expressed as to the value of Science-teaching in schools, and I had heard objections urged on the score of the expensiveness of apparatus. Both doubts and objections would, I considered, be most practically met by showing what could be done, in the way of discipline and instruction, by experimental lessons involving the use of apparatus so simple and inexpensive as to be within everybody's reach.

With some amplification, the substance of our Christmas Lessons is given in the present little volume.

¹ These brief historic references have already appeared in the Preface to the 'Forms of Water.'

CONTENTS.



SECT.	PAGE
1. INTRODUCTION	1
2. HISTORIC NOTES	1
3. THE ART OF EXPERIMENT	4
4. MATERIALS FOR EXPERIMENT	5
5. ELECTRIC ATTRACTIONS	8
6. DISCOVERY OF CONDUCTION AND INSULATION	13
7. THE ELECTROSCOPE. FURTHER ENQUIRIES ON CONDUCTION AND INSULATION	15
8. • ELECTRICS AND NON-ELECTRICS	19
9. ELECTRIC REPULSIONS. DISCOVERY OF TWO ELECTRICITIES	22
10. FUNDAMENTAL LAW OF ELECTRIC ACTION	23
11. ELECTRICITY OF THE RUBBER. DOUBLE OR 'POLAR' CHARACTER OF THE ELECTRIC FORCE	29
12. WHAT IS ELECTRICITY?	33
13. ELECTRIC INDUCTION. DEFINITION OF THE TERM	36
14. EXPERIMENTAL RESEARCHES ON ELECTRIC INDUCTION	38

SECT.	PAGE
15. THE ELECTROPHORUS	48
16. ACTION OF POINTS AND FLAMES	51
17. THE ELECTRICAL MACHINE	55
18. FURTHER EXPERIMENTS ON THE ACTION OF POINTS. THE ELECTRIC MILL. THE GOLDEN FISH. LIGHT- NING CONDUCTORS	58
19. HISTORY OF THE LEYDEN JAR. THE LEYDEN BATTERY	64
20. EXPLANATION OF THE LEYDEN JAR	69
21. FRANKLIN'S CASCADE BATTERY	73
22. NOVEL LEYDEN JARS OF THE SIMPLEST FORM	73
23. SEAT OF CHARGE IN THE LEYDEN JAR	77
24. IGNITION BY THE ELECTRIC SPARK. COTTRELL'S RUBBER. THE TUBE-MACHINE	80
25. DURATION OF THE ELECTRIC SPARK	85
26. ELECTRIC LIGHT IN VACUO	88
27. LICHTENBERG'S FIGURES	94
28. SURFACE COMPARED WITH MASS. DISTRIBUTION OF ELECTRICITY IN HOLLOW CONDUCTORS	95
29. PHYSIOLOGICAL EFFECTS OF THE ELECTRIC DISCHARGE	97
30. ATMOSPHERIC ELECTRICITY	99
31. THE RETURNING STROKE	102
32. THE LEYDEN BATTERY, ITS CURRENTS, AND SOME OF THEIR EFFECTS	108
CONCLUSION	111

LESSONS IN ELECTRICITY.



§ 1. *Introduction.*

MANY centuries before Christ, it had been observed that yellow amber (*elektron*), when rubbed, possessed the power of attracting light bodies.

Thales, the founder of the Ionic philosophy (B.C. 580), imagined the amber to be endowed with a kind of life.

This is the germ out of which has grown the science of *electricity*, a name derived from the substance in which this power of attraction was first observed.

It will be my aim, during six hours of these Christmas holidays, to make you, to some extent, acquainted with the history, facts, and principles, of this science, and to teach you how to work at it.

The science has two great divisions; the one called 'Frictional Electricity,' the other 'Voltaic Electricity.' For the present, our studies will be confined to the first, or older portion of the science, which is called 'Frictional Electricity,' because in it the electrical power is obtained from the rubbing of bodies together.

§ 2. *Historic Notes.*

The attraction of light bodies by rubbed amber was the sum of the world's knowledge of electricity

for more than 2,000 years. In 1600 Dr. Gilbert, physician to Queen Elizabeth, whose attention had been previously directed with great success to magnetism, vastly expanded the domain of electricity. He showed that not only amber, but various spars, gems, fossils, stones, glasses and resins, exhibited, when rubbed, the same power as amber.

Robert Boyle (1675) proved that a suspended piece of rubbed amber, which attracted other bodies to itself, was in turn attracted by a body brought near it. He also observed the *light* of electricity, a diamond, with which he experimented, being found to emit light when rubbed in the dark.

Boyle imagined that the electrified body threw out an invisible, glutinous substance, which laid hold of light bodies and, returning to the source from which it emanated, carried them along with it.

Otto von Guericke, Burgomaster of Magdeburg, contemporary of Boyle, and inventor of the air-pump, intensified the electric power previously obtained. He devised what may be called the first electrical machine, which was a ball of sulphur, about the size of a child's head. Turned by a handle, and rubbed by the dry hand, the sulphur sphere emitted light in the dark.

Von Guericke also noticed, and this is important, that a feather, having been first attracted to his sulphur globe, was afterwards repelled, and kept at a distance from it, until, having touched another body, it was again attracted. He heard the hissing of the 'electric fire,' and also observed that an un-electrified body, when brought near his excited sphere, became electrical and capable of being attracted.

The members of the Academy del Cimento examined

various substances electrically. They proved smoke to be attracted, but not flame, which, they found, deprived an electrified body of its power.

• They also proved liquids to be sensible to the electric attraction, showing that when rubbed amber was held over the surface of a liquid, a little eminence was formed, from which the liquid was finally discharged against the amber.

Sir Isaac Newton, by rubbing a flat glass, caused light bodies to jump between it and a table. He also noticed the influence of the rubber in electric excitation. His gown, for example, was found to be much more effective than a napkin.

Newton imagined that the excited body emitted an elastic fluid which penetrated glass.

In the efforts of Thales, Boyle, and Newton to form a mental picture of electricity we have an illustration of the tendency of the human mind, not to rest satisfied with the facts of observation, but to pass beyond the facts to their invisible causes.

Dr. Wall (1708) experimented with large, elongated pieces of amber. He found wool to be the best rubber of amber. 'A prodigious number of little cracklings' was produced by the friction, every one of them being accompanied by a flash of light. 'This light and crackling,' says Dr. Wall, 'seem in some degree to represent thunder and lightning.'¹ This is the first published allusion to thunder and lightning in connection with electricity.

Stephen Gray (1729) also observed the electric brush, snappings, and sparks. He made the prophetic

¹ 'Phil. Trans.' 1708, p. 69.

remark that 'though these effects are at present only minute, it is probable that in time there may be found out a way to collect a greater quantity of the electric fire, and, consequently, to increase the force of that power which by several of those experiments, if we are permitted to compare great things with small, seems to be of the same nature with that of thunder and lightning.'¹ This, you will observe, is far more definite than the remark of Dr. Wall.

§ 3. *The Art of Experiment.*

We have thus broken ground with a few historic notes, intended to show the gradual growth of electrical science. Our next step must be to get some knowledge of the facts referred to, and to learn how they may be produced and extended. The art of producing and extending such facts, and of enquiring into them by proper instruments, is the *art of experiment*. It is an art of extreme importance, for by its means we can, as it were, converse with Nature, asking her questions and receiving from her replies.

It was the neglect of experiment, and of the reasoning based upon it, which kept the knowledge of the ancient world confined to the single fact of attraction by amber for more than 2,000 years.

Skill in the art of experimenting does not come of itself; it is only to be acquired by labour. When you first take a billiard cue in your hand, your strokes are awkward and ill-directed. When you learn to dance, your first movements are neither graceful nor pleasant. By *practice* alone, you learn to dance and to play.

¹ 'Phil. Trans.' Vol. 39, p. 24.

This also is the only way of learning the art of experiment. You must not, therefore, be daunted by your clumsiness at first; you must overcome it, and acquire skill in the art *by repetition*.

In this way you will come into direct contact with natural truth—you will think and reason not on what has been said to you in books, but on what has been said to you by Nature. Thought springing from this source has a vitality not derivable from mere book-knowledge.

§ 4. *Materials for Experiment.*

At this stage of our labours we are to provide ourselves with the following materials:—

a. Some sticks of sealing-wax;

b. Two pieces of gutta-percha tubing, about 18 inches long and $\frac{3}{4}$ of an inch outside diameter;


c. Two or three glass tubes, about 18 inches long and $\frac{3}{4}$ of an inch wide, closed at one end, and not too thin, lest they should break in your hand and cut it;

d. Two or three pieces of clean flannel, capable of being folded into pads of two or three layers, about eight or ten inches square;

e. A couple of pads, composed of three or four layers of silk, about eight or ten inches square;

f. A board about 18 inches square, and a piece of india-rubber;


FIG. 1.



g. Some very narrow silk ribbon, *r*, and a wire loop, *w*, like that shown in fig. 1, in which sticks of sealing-wax, tubes of gutta-percha, rods of glass, or a walking-stick, may be suspended. I choose a narrow ribbon because it is convenient to have a suspending cord that will neither twist nor untwist of itself.

(I usually employ a loop with the two ends, which are here shown free, soldered together. The loop would thus be unbroken. But you may not be skilled in the art of soldering, and I therefore choose the free loop, which is very easily constructed. For the purpose of suspension an arrangement resembling a towel-horse, with a single horizontal rail, will be found convenient.)


FIG. 2.



h. A straw, *i i'*, fig. 2, delicately supported on the point of a sewing needle *N*. This is inserted in a stick of sealing-wax *A*, attached below to a little circular plate of tin, the whole forming a stand. In fig. 3 the straw is shown on a larger scale, and separate

from its needle. The short bit of straw in the middle, which serves as a cap, is stuck on by sealing-wax.

FIG. 3.



i. The name 'amalgam' is given to a mixture of mercury with other metals. Experience has shown that the efficacy of a silk rubber is vastly increased when it is smeared over with an amalgam formed of 1 part by weight of tin, 2 of zinc, and 6 of mercury. A little lard is to be first smeared on the silk, and the amalgam is to be applied to the lard. The amalgam, if hard, must be pounded or bruised with a pestle or a hammer until it is soft. You can purchase sixpennyworth of it at a philosophical instrument maker's. It is to be added to your materials.

k. I should like to make these pages suitable for boys without much pocket-money, and, therefore, aim at economy in my list of materials. But provide by all means, if you can, a fox's brush, such as those usually employed in dusting furniture.

§ 5. *Electric Attractions.*

Place your sealing-wax, gutta-percha tubing, and flannel and silk rubbers before a fire, to ensure their dryness. Be specially careful to make your glass tubes and silk rubbers not only warm, but hot. Pass the dried flannel briskly once or twice over a stick of sealing-wax or over a gutta-percha tube. A very small amount of friction will excite the power of attracting the suspended straw, as shown in *fig. 2*. Repeat the experiment several times and cause the straw to follow the attracting body round and round. Do the same with a glass tube rubbed with silk.

I lay particular stress on the heating of the glass tube, because glass has the power, which it exercises, of condensing upon its surface into a liquid film, the aqueous vapour of the surrounding air. This film must be removed.


I would also insist on practice, in order to render you expert. You will therefore attract bran, scraps of paper, gold leaf, soap bubbles, and other light bodies by rubbed glass, sealing-wax, and gutta-percha. Faraday was fond of making empty egg-shells, hoops of paper, and other light objects roll after his excited tubes.

It is only when the electric power is very weak, that you require your delicately suspended straw. With the sticks of wax, tubes, and rubbers here mentioned, even heavy bodies, when properly suspended, may be attracted. Place, for instance, a common walking-stick in the wire loop attached to the narrow ribbon, *fig. 1*, and let it swing horizontally. The glass, rubbed with

its silk, or the sealing-wax, or gutta-percha, rubbed with its flannel, will pull the stick quite round.

Abandon the wire loop; place an egg in an egg-cup, and balance a long lath upon the egg, as shown in fig. 4. The lath, though it may be almost a plank, will obe-

FIG. 4.



diently follow the rubbed glass, gutta-percha or sealing-wax.

Nothing can be simpler than this lath and egg arrangement, and hardly anything could be more impressive. The more you work with it, the better you will like it.

Pass an ebonite comb through the hair. In dry weather it produces a crackling noise; but its action upon the lath may be made plain in any weather. It is rendered electrical by friction against the hair, and with it you can pull the lath quite round.

If you moisten the hair with oil, the comb will still be excited and exert attraction; but if you moisten it with water, the excitement ceases; a comb passed through wetted hair, has no power over the lath. You will understand the meaning of this subsequently.

After its passage through dry or oiled hair, balance the comb itself upon the egg: it is attracted by the lath. You thus prove the attraction to be *mutual*: the comb attracts the lath, and the lath attracts the comb. Suspend your rubbed glass, rubbed gutta-percha, and rubbed sealing-wax in your wire loop. They are all just as much attracted by the lath as the lath was attracted by them. This is an extension of Boyle's experiment with the suspended amber (§ 2).

How it is that any unelectrified body attracts, and is attracted by the excited glass, sealing-wax and gutta-percha, we shall learn by and by.

A very striking illustration of electric attraction may be obtained with the board and india-rubber mentioned in our list of materials (§ 4). Place the board before the fire and make it *hot*; heat also a sheet of foolscap paper and place it on the board. There is no attraction between them. Pass the india-rubber briskly over the paper. It now clings firmly to the board. Tear it away, and hold it at arm's length, for it will move to your body if it can. Bring it near a door or wall, it will cling tenaciously to either. The electrified paper also powerfully attracts the balanced lath from a great distance.

The friction of the hand, of a cambric handkerchief, or of wash-leather fails to electrify the paper in any high degree. It requires friction by a special substance to make the excitement strong. This we learn by experience. It is also experience that has taught us that resinous bodies are best excited by flannel, and vitreous bodies by silk.

Take nothing for granted in this enquiry, and neglect no effort to render your knowledge complete

and sure. Try various rubbers, and satisfy yourself that differences like that first observed by Newton exist between them.

Vary also the body rubbed. Excite by friction paraffin and composite candles, resin, sulphur, bees'-wax, ebonite, and shellac. Also rock-crystal, and other vitreous substances, and attract with all of them the balanced lath. A film of collodion, a sheet of vulcanised india-rubber, or brown paper heated before the fire, rubbed briskly with the dry hand, attracts and is attracted by the lath.


Lay bare also the true influence of heat in the case of our rubbed paper. Spread a cold sheet of foolscap on a cold board—on a table, for example. If the air be not very dry, rubbing, even with the india-rubber, will not make them cling together. But is it because they were *hot* that they attracted each other in the first instance? No, for you may heat your board by plunging it into boiling water, and your paper by holding it in a cloud of steam. Thus heated they cannot be made to cling together. The heat really acts by expelling the moisture. Cold weather, if it be only dry, is highly favourable to electric excitation. During frost, the whisking of the hand over silk or flannel, or over a cat's back, renders it electrical.

The experiment of the Florentine academicians, whereby they proved the electric attraction of a liquid, is pretty, and worthy of repetition. Fill a very small watch-glass with oil, until the liquid forms a round curved surface, rising a little over the rim of the glass. A strongly excited glass tube, held over the oil, raises not one eminence only, but several, each of which finally discharges a shower of drops against the attract-

ing glass. The effect is shown in fig. 5, where G is the watch-glass on the stand T, and R the excited glass tube.¹

Cause the excited glass tube to pass close by your face, without touching it. You feel, like Hauksbee, as if

FIG. 5.



a cobweb were drawn over the face. You also sometimes smell a peculiar odour, due to a substance developed by the electricity, and called ozone.

Long ere this, while rubbing your tubes, you will have heard the 'hissing' and 'crackling' so often referred to by the earlier electricians; and if you have rubbed your glass tube briskly in the dark, you will have seen what they called the 'electric fire.' Using, instead of a tube, a tall glass jar, rendered hot, a good warm rubber, and vigorous friction, the streams of electric fire are very surprising in the dark.

¹ As a practical measure the watch-glass ought to rest upon a small stand, and not upon a surface of large area. The experiment is particularly well suited for projection on a screen.


§ 6. *Discovery of Conduction and Insulation.*

Here I must again refer to that most meritorious philosopher Stephen Gray. In 1729, he experimented with a glass tube stopped by a cork. When the tube was rubbed, the cork attracted light bodies. Gray states that he was 'much surprised' at this, and he 'concluded that there was certainly an attractive virtue communicated to the cork.' This was the starting point of our knowledge of electric Conduction.

A fir stick 4 inches long, stuck into the cork, was also found by Gray to attract light bodies. He made his sticks longer, but still found a power of attraction at their ends. He then passed on to packthread and wire. Hanging a thread s, fig. 6, from the top window of a house, so that the lower end nearly touched the ground, and twisting the upper end of the thread round his glass tube r, on briskly rubbing the tube, light bodies were attracted by the lower end n of the thread.

But Gray's most remarkable experiment was this:—He suspended a long hempen line horizontally by loops of packthread, but failed to transmit through it the electric power. He then suspended it by loops of silk and succeeded in sending the 'attractive virtue' through 765 feet of thread. He at first

FIG. 6.



thought the silk was effectual because it was thin; but on replacing a broken silk loop by a still thinner wire, he obtained no action. Finally, he came to the conclusion that his loops were effectual, not because they were thin but because they were *silk*. This was the starting point of our knowledge of Insulation.

It is interesting to notice the devotion of some men of science to their work. Dr. Wells, who wrote a beautiful essay, wherein he explained the origin of dew, finished it when he was on the brink of the grave. Stephen Gray was so near dying when his last experiments were made, that he was unable to write out an account of them. On his death-bed, and indeed the very day before his death, his description of them was taken from his lips by Dr. Mortimer, Secretary of the Royal Society, and afterwards printed in the 'Philosophical Transactions.'

One word of definition will be useful here. Some substances, as proved by Stephen Gray, possess in a very high degree the power of permitting electricity to pass through them; other substances stop the passage of the electricity. Bodies of the first class are called *conductors*; bodies of the second class are called *insulators*.

You cannot do better than repeat here the experiments of Gray. Push a cork into the open end of your glass tube; rub the tube, carrying the friction up to the end holding the cork. The cork will attract the balanced lath, shown in fig. 4, with which you have already worked so much.


But the excited glass is here so near the end of the cork that you may not feel certain that the observed attraction is that of the cork. You can, however, prove

that the cork attracts by its action upon light bodies which cling to it. Stick a pen-holder into the cork, and rub the glass tube as before. The free end of the holder will attract the lath. Stick a deal rod three or four feet long into the cork; its free end will attract the lath when the glass tube is excited. In this way, you prove to demonstration that the electric power is conveyed along the rod.

§ 7. *The Electroscope. Further Enquiries on Conduction and Insulation.*

A little addition to our apparatus will now be desirable. You can buy a book of 'Dutch metal' for fourpence; and a globular flask like that shown in fig. 7,

FIG. 7.



for sixpence, or at the most a shilling. Find a cork, c, which fits the flask; pass a wire, w, through the cork and bend it near one end at a right angle. Attach

by means of wax to the bent arm, which ought to be about three quarters of an inch long, two strips, L, of the Dutch metal, about three inches long and from half an inch to three-quarters of an inch wide. The strips will hang down face to face, in contact with each other. Stick by sealing-wax upon the other end of the wire a little plate of tin or sheet-zinc, T, about two inches in diameter. In all cases you must be careful so to use your wax as not to interrupt the metallic connection of the various parts of your apparatus, which we will name an *electroscope*. Gold leaf, instead of Dutch metal, is usually employed for electroscopes. I recommend the 'metal' because it is cheaper, and will stand rougher usage.

See that your globular flask is dry and free from dust. Bring your rubbed sealing-wax, R, or your rubbed glass, *near* the little plate of tin, the leaves of Dutch metal open out; withdraw the excited body, the leaves fall together. We shall enquire into the cause of this action immediately. Practise the approach and withdrawal for a little time. Now draw your rubbed sealing-wax or glass along the edge of the tin plate, T. The leaves diverge, and after the sealing-wax or glass is withdrawn they remain divergent. In the first experiment you communicated no electricity to the electroscope; in the second experiment you did. At present I will only ask you to take the opening out of the leaves as a proof that electricity has been communicated to them.

And now we are ready for Gray's experiments in a form different from his. Connect the end of a long wire with the tin plate of the electroscope; coil the other end round your glass tube. Rub the tube briskly, carrying the friction close to the coiled wire. A single

stroke of your rubber, if skilfully given, will cause the leaves to diverge. The electricity has obviously passed through the wire to the electroscope.

Substitute for the wire a string of common twine, rub briskly and you will cause the leaves to diverge; but there is a notable difference as regards the promptness of the divergence. You soon satisfy yourself that the electricity passes with greater facility through the wire than through the string. Substitute for the twine a string of silk. No matter how vigorously you rub you can now produce no divergence. The electricity cannot get through the silk at all.


This is the place to demonstrate in a manner never to be forgotten the influence of moisture. Wet your dry silk string throughout, and squeeze it a little so that the water from it may not trickle over your glass tube. Coil it round the tube as before, and excite the tube. The leaves of the electroscope immediately diverge. The *water* is here the conductor. The influence of moisture was first demonstrated by Du Fay (1733 to 1737), who succeeded in sending electricity through 1,256 feet of moist packthread.

It is hardly necessary to point out the meaning of Gray's experiment where he found that, with loops of wire or of packthread, he could not send the electricity from end to end of his suspended string. Obviously the electricity escaped in each of these cases through the conducting support to the earth.

My assistant, Mr. Cottrell, who has been working very hard for you and me, has devised an electroscope which we shall frequently employ in our lessons. *M*, fig. 8, is a little plate of metal, or of wood covered with tin-foil, supported on a rod of glass or of sealing-wax. *N* is

another plate of Dutch metal paper, separated about an inch from *m*, and attached by sealing-wax to the long

FIG. 8.



straw *I I'* (broken off in the figure); *A A'* is a horizontal pivot formed by a sewing needle, and supported on a bent strip of metal, as shown in the figure. By weighting the straw with a little wire near *I'*, you so balance it that the plate *N* shall be just lifted away from *M*. The wire *w*, which may be 100 feet long, proceeds from *M* to your glass tube, round which it is coiled. A single vigorous stroke of the tube by the rubber sends electricity along *w* to *M*; *N* is attracted downwards, the other end of the long straw being lifted through a considerable distance. In subsequent figures you will see the complete straw-index, and its modes of application.

A few experiments with either of these instruments will enable you to classify bodies as conductors, semi-conductors, and insulators. Here is a list of a few of each, which, however, differ much among themselves.

Conductors.

The common metals
Well-burned charcoal
Concentrated acids
Solutions of salts

Rain water
Linen
Living vegetables and animals.

Semi-conductors.

Alcohol and ether	Paper
Dry wood	Straw.
Marble	

Insulators.

Fatty oils	Silk
Chalk	Glass
India-rubber	Wax
Dry paper	Sulphur
Hair	Shellac.

A little reflection will enable you to vary these experiments indefinitely. Rub your excited sealing-wax or glass against the tin plate of your electroscope, and cause the leaves to diverge. Touch the plate with any one of the conductors mentioned in the list; the electroscope is immediately discharged. Touch it with a semi-conductor; the leaves fall as before, but less promptly. Touch the plate finally with an insulator, the electricity cannot pass, and the leaves remain unchanged.

§ 8. *Electrics and Non-Electrics.*

For a long period, bodies were divided into *electrics* and *non-electrics*, the former deemed capable of being electrified, the latter not. Thus the amber of the ancients, and the spars, gems, fossils, stones, glasses, and resins, operated on by Dr. Gilbert, were called *electrics*,

while all the metals were called non-electrics. We must now determine the true meaning of this distinction.

Take in succession a piece of brass, of wood coated with tin-foil, a lead bullet, apples, pears, turnips, carrots, cucumbers—uncoated wood not very dry will also answer—in the hand, and strike them briskly with flannel, or the fox's brush; none of them will attract the balanced lath, fig. 4, or show any other symptom of electric excitement. All of them therefore would have been once called non-electrics.

But suspend them in succession by a string of silk held in the hand, and strike them again; every one of them will now attract the lath.

Reflect upon the meaning of this experiment. We have introduced an insulator—the silk string—between the hand and the body struck, and we find that by its introduction the non-electric has been converted into an electric.

The meaning is obvious. When held in the hand, though electricity was developed in each case by the friction, it passed immediately through the hand and body to the earth. This transfer being prevented by the silk, the electricity, once excited, is retained, and the attraction of the lath is the consequence.

In like manner, a brass tube, held in the hand and struck with a fox's brush, shows no attractive power; but when a stick of sealing-wax, ebonite, or gutta-percha is thrust into the tube as a handle, the striking of the tube at once develops the power of attraction.

And now you see more clearly than you did at first the meaning of the experiment with the heated foolscap and india-rubber. Paper and wood always imbibe a certain amount of moisture from the air.

When the rubber was passed over the cold paper electricity was excited, but the paper, being rendered a conductor by its moisture, allowed the electricity to pass away.

Prove all things. Lay your cold foolscap on a cold board supported by dry tumblers; pass your india-rubber over the paper; lift it by a loop of silk, which has been previously attached to it, for if you touch it it will discharge itself. You will find it electric; and with it you can charge your electroscope, or attract from a distance your balanced lath.

The human body was ranked among the non-electrics. Make plain to yourself the reason. Stand upon the floor and permit a friend to strike you briskly with the fox's brush. Present your knuckle to the balanced lath, you will find no attraction. Here, however, you stand upon the earth, so that even if electricity had been developed, there is nothing to hinder it from passing away.

But, place upon the ground four warm glass tumblers, and upon the tumblers a board.¹ Stand upon the board, and present your knuckle to the lath. A single stroke of the fox's fur, if skilfully given, will produce attraction. If you stand upon a cake of resin, of ebonite, or upon a sheet of good india-rubber, the effect will be the same. You can also charge your electroscope with this electricity.

Throw a mackintosh over your shoulders and let a friend strike it with the fox's brush, the attractive force is greatly augmented.

¹ Some caution is necessary here. A large class of cheap glass tumblers conduct so freely that they are unfit for this and similar experiments. See § 19.

After brisk striking, present your knuckle to the knuckle of your friend. A spark will pass between you.

This experiment with the mackintosh further illustrates what you have already frequently observed, namely, that it is not friction alone, but the friction of special substances against each other, that produces electricity.

Thus we prove that non-electrics, like electrics, can be excited, the condition of success being, that an insulator shall be interposed between the non-electric and the earth. It is obvious that the old division into electrics and non-electrics, really meant a division into insulators and conductors.

§ 9. *Electric Repulsions. Discovery of two Electricities.*

We have hitherto dealt almost exclusively with electric attractions, but in an experiment already referred to (§ 2), Otto von Guericke observed the *repulsion* of a feather by his sulphur globe. I also anticipated matters in the use of our Dutch metal electroscope (§ 7), where the repulsion of the leaves informed us of the arrival of the electricity.

Du Fay, who was the real discoverer here, found a gold-leaf floating in the air to be first attracted and then repelled by the same excited body. He afterwards proved that when the floating leaf was repelled by rubbed glass, it was attracted by rubbed resin,—and that when it was repelled by rubbed resin, it was attracted by rubbed glass. Hence the important announcement, by Du Fay, that there are two kinds of electricity.

The electricity excited on glass was for a time called *vitreous* electricity,—while that excited on sealing-wax was called *resinous* electricity. These

terms are however improper ; because, by changing the rubber, we can obtain the electricity of sealing-wax upon glass, and the electricity of glass upon sealing-wax.

Roughen, for example, the surface of your glass tube with a grindstone, and rub it with flannel, the electricity of sealing-wax will be found upon the vitreous surface. Rub your sealing-wax with vulcanised india-rubber, the electricity of glass will be found upon the resinous surface. You will be able to prove this immediately.

We now use the term *positive* or *plus* electricity to denote that developed on glass by the friction of silk ; and *negative* or *minus* electricity to denote that developed on sealing-wax by the friction of flannel. These terms are adopted purely for the sake of convenience. There is no reason in nature why the resinous electricity should not be called positive, and the vitreous electricity negative. Once agreed, however, to apply the terms as here fixed, we must adhere to this agreement throughout.

• § 10. *Fundamental Law of Electric Action.*

In all the experiments which we have hitherto made, one of the substances operated on has been electrified by friction, and the other not. But once engaged in enquiries of this description, questions incessantly occur to the mind, the answering of which extends our knowledge, and suggests other questions. Suppose, instead of exciting only one of the bodies presented to each other, we were to excite both of them, what would occur ? This is the question which was asked and answered by Du Fay, and which we must now answer for ourselves.

Here your wire loop, fig. 1, comes again into play.

Place an un-rubbed gutta-percha tube, or a stick of sealing-wax, in the loop, and be sure that it is un-rubbed—that no electricity adheres to it from former experiments. If it fail to attract light bodies, it is unexcited; if it attract them, pass your hand over it several times, or, better, still, pass it over or through the flame of a spirit lamp. This will remove every trace of electricity. Satisfy yourself that the un-rubbed gutta-percha tube is attracted by a rubbed one.

Remove the un-rubbed tube from the loop, and excite it with its flannel rubber. One end of the tube is held in your hand and is therefore unexcited. Return the tube to the loop, keeping your eye upon the excited end. Bring a second rubbed tube near the excited end of the suspended one: strong repulsion is the consequence. Drive the suspended tube round and round by this force of repulsion.

Bring a rubbed glass tube near the excited end of the gutta-percha tube: strong attraction is the result.

Repeat this experiment step by step with two glass tubes. Prove that the rubbed glass tube attracts the un-rubbed one. Remove the un-rubbed tube from the loop, excite it by its rubber, return it to the loop, and establish the repulsion of glass by glass. Bring rubbed gutta-percha or sealing-wax near the rubbed glass: strong attraction is the consequence.

These experiments lead you directly to the fundamental law of electric action, which is this:—*Bodies charged with the same electricity repel each other, while bodies charged with opposite electricities attract each other. Positive repels positive, and attracts negative. Negative repels negative, and attracts positive.*


Devise experiments which shall still further illus-

trate this law. Repeat, for example, Otto von Guericke's experiment. Hang a feather by a silk thread and bring your rubbed glass tube near it: the feather is attracted, touches the tube, charges itself with the electricity of the tube, and is then repelled. Cause it to retreat from the tube in various directions. Du Fay's experiment with the gold-leaf will be repeated and explained further on. See § 18.

Hang your feather by a common thread: if no insulating substance intervenes between the feather and the earth, you can get no repulsion. Why? Obviously because the charge of positive electricity communicated by the rod, is not retained by the feather, but passes away to the earth. Hence, you have not positive acting against positive at all. Why the neutral body is attracted by the electrified one, will, as already stated, appear by and by.

Attract your straw needle by your rubbed glass tube. Let the straw strike the tube, so that the one

FIG. 9.




shall rub against the other. The straw accepts the

electricity of the tube and repulsion immediately follows attraction, as shown in fig. 9.

Mr. Cottrell has devised the simple electroscope represented in fig. 10 to show repulsion. *A* is a stem of sealing-wax with a small circle of tin *t* at the top. *w* is a bent wire proceeding from *t*, with a small disk attached to it by wax. *I I'* is a little straw index, supported by the needle *N*, as shown in fig. 10. The stem *A'*, also of sealing-wax, is not quite vertical, the object being to cause the bit of paper *I'*, to rest close

FIG. 10.




to *w* when the apparatus is not electrified. When electricity is imparted to *t*, it flows through the wires *w* and *w*, over both disk and index: immediate repulsion of the straw is the consequence.

No better experiment can be made to illustrate the self-repulsive character of electricity than the following one. Heat your square board (§ 5), and warm, as before, your sheet of foolscap. Spread the paper

upon the board, and excite it by the friction of india-rubber. Cut from the sheet two long strips with your penknife. Hold the strips together at one end. Separate them from the board, and lift them into the air: they forcibly drive each other apart, producing a wide divergence.

Cut several strips, so as to form a kind of tassel. Hold them together at one end. Separate them from

FIG. 11.




the board, and lift them into the air: they are driven asunder by the self-repellent electricity, presenting an appearance which may remind you of the hair of Medusa. The effect is represented in fig. 11.¹

¹ In one of my earliest lectures at the Royal Institution, having rubbed a sheet of foolscap, I was about to lift it bodily from the hot board, and to place it against the wall, when the thought of cutting it into strips, and allowing them to act upon each other, occurred to me. The result, of course, was that above described. Simple and obvious as it was, it gave Faraday, who was present at the time, the most lively pleasure. The simplest experiment, if only suited to its object, delighted him.

Another very beautiful experiment fits in here. Let fine silver sand, *s*, fig. 12, issue in a stream from a glass funnel, through an aperture one-eighth of an inch in diameter. Connect the sand in the funnel by a fine wire *w*, fig. 13, with your warm glass tube. Unelectrified,

FIG. 12.

FIG. 13.



the sand particles descend as a continuous stream, *s s'*, fig. 12, but at every stroke of the rubber they fly asunder, as in fig. 13, through self-repulsion.¹

Or let three or four fine fillets of water issue from three or four pin-holes in the bottom of a vessel close

¹ For these, and also for experiments with the electroscope, the teacher of a large class will find the lime-light shadows upon a white screen (or better still, those of the electric light) exceedingly useful. The effects are thus rendered visible to all at once.

to each other. Connect the water of the vessel with your glass tube, and rub as before. The liquid veins are scattered into spray by every stroke of the rubber.

These experiments are best made with 'Cottrell's rubber,' described in § 24.

And now you must learn to determine with certainty the quality of the electricity with which any body presented to you may be charged. You see immediately that attraction is no sure test, because un-electrified bodies are attracted. Further on (§ 14) you will be able to grapple with another possible source of error in the employment of attraction.

In determining quality, you must ascertain, by trial, the kind of electricity by which the charged body is repelled; if, for example, any electrified body repel, or is repelled by, sealing-wax rubbed with flannel, the electricity of the body is negative; if it repel, or is repelled by, glass, rubbed with silk, its electricity is positive. Du Fay had the sagacity to propose this mode of testing quality.

Apply this test to the strips of foolscap paper excited by the india-rubber. Bring a rubbed gutta-percha tube near the electrified strips, you have strong attraction. Bring a rubbed glass tube between the strips, you have strong repulsion and augmented divergence. Hence, the electricity, being repelled by the positive glass, is itself positive.

§ 11. *Electricity of the Rubber. Double or 'Polar' Character of the Electric Force.*

We have examined the action of each kind of electricity upon itself, and upon the other kind; but hitherto

we have kept the rubber out of view. One of the questions which inevitably occur to the enquiring scientific mind would be: how is the rubber affected by the act of friction? Here, as elsewhere, you must examine the subject for yourself, and base your conclusions on the facts you establish.

Test your rubber then, by your balanced lath. The lath is attracted by the flannel which has rubbed against gutta-percha; and it is attracted by the silk, which has rubbed against glass.

Regarding the quality of the electricity of the flannel or of the silk rubber, the attraction of the lath teaches you nothing. But, suspend your rubbed glass tube, and bring the flannel rubber near it: repulsion follows. The silk rubber, on the contrary, attracts the glass tube. Suspend your rubbed gutta-percha tube, and bring the silk rubber near it: repulsion follows. The flannel, on the contrary, attracts the tube.

The conclusion is obvious: the electricity of the flannel is positive, that of the silk is negative.

But the flannel is the rubber of the gutta-percha, whose electricity is negative; and the silk is the rubber of the glass, whose electricity is positive. Consequently, we have not only proved the rubber to be electrified by the friction, but also proved the electricity of the rubber to be opposite in quality to that of the body rubbed.

All your subsequent experience will verify the statement that the two electricities always go together; that you cannot excite one of them without at the same time exciting the other, and that the electricity of the rubber, though opposite in quality, is in all cases precisely equal in quantity to that of the body rubbed.

And now we will test these principles by a new experiment. In § 5 we learned that an ebonite comb is electrified by its passage through dry hair. You can readily prove the electricity of the comb to be negative. But the hair is here the rubber, and, in accordance with the principle just laid down, an equal quantity of positive electricity has been excited in the hair. If you stand on the ground uninsulated, the electricity of the hair passes freely through your body to the earth.

But stand upon an insulating stool¹—on your board, for example, supported by four warm tumblers—while I, standing on the ground, pass the comb briskly through your hair. I pass it ten, twenty, thirty times, and then ask you to attract your balanced lath. You present your knuckle, but there is no attraction.

Here the comb and the hair soon reach their maximum excitement, beyond which no further development of electricity occurs. Now, though the comb, as shown in § 5, is competent to attract the lath, while your body is here incompetent to do so, this may be because the small quantity of electricity existing in a concentrated form upon the comb becomes, when diffused over the body, too feeble to produce attraction.

Can we not exalt the electricity of your body? Guided by the principles laid down, let us try to do so. First I pass the unelectrified comb through your hair; it comes away electrified. After discharging the comb by passing my hand closely over it, I pass it again through the hair. As before, it quits the hair electrified, and I

¹ A stool with glass legs which, to protect them from the moisture of the air, are usually coated with a solution of shellac. Regarding the attraction of glass for atmospheric humidity, you will call to mind what has been said in § 5.

again discharge it. I do this ten or twenty times, always depriving the comb of its electricity after it has quitted the hair. Now present your knuckle to the balanced lath. It is powerfully attracted.

Here, as I have said, the unelectrified comb carried in each case electricity away with it; but, in accordance with the foregoing principles, it left an equal quantity of the opposite electricity behind it. And though the amount of electricity corresponding to a single charge of the comb, when diffused over the body, proved insensible to our tests, that amount ten or twenty times multiplied became not only sensible, but strong. Indeed, by discharging the comb, and passing it in each case unelectrified through the hair, the insulated human body can be rendered highly electrical.

Near the beginning of this section I said, in rather an off-hand way, that rubbed flannel repels rubbed glass, while rubbed silk repels rubbed gutta-percha. Now, while it is generally easy to obtain the repulsion by the flannel, it is by no means always easy to obtain the repulsion by the silk. Over and over again I have been foiled in my attempts to show this repulsion. I wish you, therefore, to be aware of an infallible method of obtaining it.

Stand on your insulating stool, and rub your glass tube briskly with the amalgamated silk; hand me the tube. I pass my hand closely over its surface, removing from that surface nearly the whole of its electricity. I hand you the tube again, and you again excite it. You hand it to me, and I again discharge it. In each case, therefore, you excite an unelectrified glass tube, and in each case the tube leaves behind upon the rubber an amount of negative electricity equal in quantity to the

positive carried away. By thus adding charge to charge, the rubber is rendered highly electrical; and, even should its insulating power be impaired by the amalgam, it can now afford to yield a portion of its electricity to your hand and body, and still powerfully repel rubbed gutta-percha. The principle, which might be further illustrated, is obviously the same as that applied in the case of the comb.

§ 12. *What is Electricity?*

Thus far we have proceeded from fact to fact, acquiring knowledge of a very valuable kind. But facts alone cannot satisfy us. We seek a knowledge of the *principles* which lie behind the facts, and which are to be discerned by the mind alone. Thus, having spoken as we have done, of electricity passing hither and thither, and of its being prevented from passing; hardly any thoughtful boy or girl can avoid asking what is it that thus passes?—what *is* electricity? Boyle and Newton betrayed their need of an answer to this question when the one imagined his unctuous threads issuing from and returning to the electrified body; and when the other imagined that an elastic fluid existed which penetrated his rubbed glass.

When I say 'imagined' I do not intend to represent the notions of these great men as vain fancies. Without imagination we can do nothing here. By imagination I mean the power of picturing mentally things which, though they have an existence as real as that of the world around us, cannot be touched directly by the organs of sense. I mean the purified scientific imagination, without the exercise of which we cannot

take a single step into the region of causes and principles.

It was by the exercise of the scientific imagination that Franklin devised the theory of a single electric fluid to explain electrical phenomena. This fluid he supposed to be self-repulsive, and diffused in definite quantities through all bodies. He supposed that when a body has more than its proper share it is positively, when less than its proper share it is negatively electrified. It was by the exercise of the same faculty that Symmer devised the theory of two electric fluids, each self-repulsive, but both mutually attractive.

At first sight Franklin's theory seems by far the simpler of the two. But its simplicity is only apparent. For though Franklin assumed only one fluid, he was obliged to assume three distinct actions. Firstly, he had the self-repulsion of the electric particles. Secondly, the mutual attraction of the electric particles and the ponderable particles of the body through which the electricity was diffused. Thirdly, these two assumptions when strictly followed out lead to the unavoidable conclusion that the material particles also mutually repel each other. Thus the theory is by no means so simple as it appears.

The theory of Symmer, though at first sight the most complicated, is in reality by far the simpler of the two. According to it electrical actions are produced by two fluids, each self-repulsive, but both mutually attractive. These fluids cling to the atoms of matter, and carry the matter to which they cling along with them. Every body, in its natural condition, possesses both fluids in equal quantities. As long as the fluids are mixed together they neutralise each other,

the body in which they are thus mixed being in its natural or unelectrical condition.

By friction (and by various other means) these two fluids may be torn asunder, the one clinging by preference to the rubber, the other to the body rubbed.

According to this theory there must always be attraction between the rubber and the body rubbed, because, as we have proved, they are oppositely electrified. This is in fact the case. And mark what I now say. Over and above the common friction, this electrical attraction has to be overcome whenever we rub glass with silk, or sealing-wax with flannel.

You are too young to fully grasp this subject yet; and indeed it would lead us too far away to enter fully into it. But I will throw out for future reflection the remark, that the overcoming of the ordinary friction produces heat then and there upon the surfaces rubbed, while the force expended in overcoming the electric attraction may be converted into heat which shall appear a thousand miles away from the place where it was generated.

Theoretic conceptions are incessantly checked and corrected by the advance of knowledge, and this theory of electric fluids is doubted by many eminent scientific men. It will, at all events, have to be translated into a form which shall connect it with heat and light, before it can be accepted as complete. Nevertheless, keeping ourselves unpledged to the theory, we shall find it of exceeding service both in unravelling and in connecting together electrical phenomena.

§ 13. *Electric Induction. Definition of the Term.*

We have now to apply the theory of electric fluids to the important subject of electric *induction*.

It was noticed by early observers that *contact* was not necessary to electrical excitement. Otto von Guericke, as we have already seen (§ 2), found that a body brought near his sulphur globe became electrical. By bringing his excited glass tube near one end of a conductor, Stephen Gray attracted light bodies at the other end. He also obtained attraction through the human body. From the human body also Du Fay, to his astonishment, obtained a spark. Canton, in 1753, suspended pith-balls by thread, and holding an excited glass tube, at a considerable distance from them, caused them to diverge. On removing the tube the balls fell together, no permanent charge being imparted to them. Such phenomena were further studied and developed by Wilcke and Æpinus, Coulomb and Poisson.

These and all similar results are embraced by the law, that when an electrified body is brought near an unelectrified conductor, the neutral fluid of the latter is decomposed; one of its constituents being attracted, the other repelled. When the electrified body is withdrawn, the separated electricities flow again together and render the conductor unelectric.

This decomposition of the neutral fluid by the mere presence of an electrified body is called *induction*. It is also called electrification by *influence*.


If, while it is under the influence of the electrified body, the body influenced be touched, the free electri-

city (which is always of the same kind as that of the influencing body) passes away, the opposite electricity being held captive.

On removing the electrified body the captive electricity is set free, the conductor being charged with electricity opposite in kind to that of the body which electrified it.

You cannot do better here than repeat Stephen Gray's experiment. Support a small plank or lath, $L L'$, fig. 14, upon a warm tumbler, G , and bring under one of

FIG. 14.



its ends, L , and within four or five inches of that end, scraps of light paper or of gold leaf. Excite your glass tube, R , vigorously, and bring it over the other end of the plank, without touching it. The ends may be six or eight feet apart; the light bodies will be attracted. The experiment is easily made, and you are not to rest satisfied till you can make it with ease and certainty.

This is a fit place to repeat that you must keep a close eye upon the tumblers you employ for insulation.

Some of them, made of common glass, are hardly to be accounted insulators at all.

§ 14. *Experimental Researches on Electric Induction.*

Our mastery over this subject of induction must be completé; for it underlies all our subsequent enquiries. Without reference to it nothing is to be explained; possessed of it you will enjoy not only a wonderful power of explanation, but of prediction. We will attack it, therefore, with the determination to exhaust it.

And here a slight addition must be made to our apparatus. We must be in a condition to take samples

FIG. 15.




of electricity, and to convey them, with the view of testing them, from place to place. For this purpose the little 'carrier,' shown in fig. 15, will be found convenient. *T* is a bit of tin-foil, two or three inches square. A straw stem is stuck on to it by sealing-wax, the lower end of the stem being covered by sealing-wax. To make the insulation sure, the part between *R* and *S'* is wholly of sealing-wax. You can have stems of ebonite, which are stronger, for a few pence; but you can have this one for a fraction of a penny. The end *R'* is to be held in the hand; the electrified body is to be touched by *T*, and the electricity conveyed to an electroscope to be tested.

Touch your rubbed glass rod with *T*, and then touch your electroscope: the leaves diverge with positive electricity. Touch your rubbed gutta-percha or seal-

ing-wax with τ , and then touch your electroscope: the leaves diverge with negative electricity. If the electricity of any body augment the divergence produced by the glass, the electricity of that body is positive. If it augment the divergence produced by the gutta-percha, the electricity is negative. And now we are ready for further work.

Place an egg, E , fig. 16, on its side upon a dry wine-

FIG. 16.



glass; bring your excited glass tube, G , within an inch or so of the end of the egg. What is the condition of the egg? Its electricity is decomposed; the negative fluid covering the end a adjacent to the glass, the positive covering the other end b . Remove the glass tube: what occurs? The two electricities flow together and neutrality is restored. Prove this neutrality. Neither a carrier touching the egg, nor the egg itself, has any power to affect your electroscope, or to attract your balanced lath.

Again, bring the excited tube near the egg. Touch its distant part b with your carrier. The carrier now

attracts the straw (fig. 2) or the balanced lath (fig. 4). It also causes the leaves of your electroscope to diverge. What is the *quality* of the electricity? It repels and is repelled by rubbed glass; the electricity at *b* is therefore positive. Discharge the carrier by touching it, and bring it into contact with the end *a* of the egg nearest to the glass tube. The electricity you take away repels and is repelled by gutta-percha. It is therefore negative. Test the quality also by the electroscope.

While the tube *a* is near the egg touch the end *b* with your finger; now try to charge the carrier by touching *b*: you cannot do so—the positive electricity has disappeared. Has the negative disappeared also? No. Remove the glass tube, and once more touch the egg at *b* by the carrier. It is charged, not with positive, but with negative electricity. Clearly understand this experiment. The neutral electricity of the egg is first decomposed into negative and positive; the former attracted, the latter repelled by the excited glass. The repelled electricity is free to escape, and it has escaped on your touching the egg with your finger. But the attracted electricity cannot escape as long as the influencing tube is held near. On removing the tube which holds the negative fluid in bondage, that fluid immediately diffuses itself over the whole egg. An apple, or a turnip, will answer for these experiments at least as well as an egg.

Discharge the egg by touching it. Re-excite the glass tube and bring it again near. Touch the egg with a wire or with your finger at *a*. Is it the negative at *a*, into which you plunge your finger, that escapes? No such thing. The free positive fluid passes through the negative, and through your finger to the earth. Prove

this by removing, first, your finger, and then the glass tube. The egg is charged negatively.

Again ; place two eggs, *EE*, fig. 17, lengthwise on two dry wine-glasses, *gg*, and cause two of their ends to

FIG. 17.




touch each other, as at *c*. Bring your rubbed glass rod near the end *a*, and while it is there separate the eggs by moving one glass away from the other. Withdraw the rod and test both eggs. *a* repels rubbed sealing-wax, and *b* repels rubbed glass ; *a* is therefore negative, *b* is positive. The two charges, moreover, exactly neutralise each other in the electroscope. Again bring the eggs together and restore the rubbed tube to its place near *a*. Touch *a* and then separate the eggs. Remove the glass rod and test the eggs. *a* is negative, *b* is neutral. Its electricity has escaped through the finger, though placed at *a*.

Equally good, if not indeed more handy, for these experiments are two apples *AA*, fig. 18, supported on stems of sealing-wax. A needle is heated and sunk in each case into the stick of wax at the top, and on to the needle the apple is pushed. The sealing-wax stems are


stuck on by melting to little foot-boards. By arrangements of this kind you make experiments which are

FIG. 18.



more instructive than those usually made with instruments twenty times more expensive.

FIG. 19.



Push your researches still farther, and instead of bringing the eggs or apples together, place them six feet

or so apart, and let a light chain, *c*, fig. 19, or a wire, stretch from one to the other. Two brass balls, or wooden balls covered with tin-foil, supported by tall drinking glasses, *g* & *g'*, will be better than the eggs for this experiment, for they will bear better the strain of the chain; but you can make the experiment with the eggs, or very readily with the two apples or two turnips. For the present we will suppose the straw-index *i i'* not to be there. Rub your glass tube *n*, and bring it near one of the balls; test both: the near one, *t'*, is negative, the distant one, *t*, positive. Touch the near one, the positive electricity, which had been driven along the chain to the remotest part of the system, returns along the chain, passes through the negative, which is held captive by the tube, and escapes to the earth. When the tube *n* is removed, negative electricity overspreads both chain and balls.


In fig. 8 you made the acquaintance of the plate *n*, and the straw-index *i i'*, shown on a smaller scale in fig. 19. By their means you immediately see both the effect of the first induction, and the consequence of touching any part of the system with the finger. The plate *n* rests over the ball or turnip *t*, the position of the straw-index being that shown by the dots. Bring the rubbed tube near *t'*: the end *n* of the index immediately descends and the other end rises along the graduated scale. Remove the glass rod; the index *i i'* immediately falls. Practise this approach and withdrawal, and observe how promptly the index declares the separation and recomposition of the fluids. .

While the tube is near *t'*, and the end *n* of the index is attracted, let *t'* be touched by the finger. The end *n* is immediately liberated, for the electricity which pulled

it down escapes along the chain and through the finger to the earth. Now remove your excited tube. The captive negative electricity diffuses itself over both balls, and the index is again attracted.

Instead of the chain you may interpose between the balls 100 feet of wire supported by silk loops. This is done in fig. 20, which shows the wire *w* supported by

FIG. 20.




the silk strings *s s s*. For the ball or turnip *r'*, fig. 19, the cylinder *c*, on a glass support *G*, is substituted, the little table *M* taking the place of the ball *r*. Every approach and withdrawal of the rubbed glass tube *R* is followed obediently by the attraction and liberation of *N*, and the corresponding motion of the index *N I*.

Repeat here an experiment, first made by a great electrician named *Æpinus*. I wish you to make these historic experiments. Insulate an elongated metal conductor, *c c'*, fig. 21, or one formed of wood coated with tin-foil—even a carrot, cucumber, or parsnip, so that

it be insulated, will answer. Let a small weight, *w*, suspended from a silk string, *s*, rest on one end of the conductor, and hold your rubbed glass tube, *R*, over the

FIG. 21.



other end. You can predict beforehand what will occur when you remove the weight. It carries away with it electricity, which repels rubbed glass, and attracts your balanced lath.

Stand on an insulating stool ; or make one by placing a board on four warm tumblers. Present the knuckles of your right hand, to the end of the balanced lath, and stretch forth your left arm. There


is no attraction. But let a friend or an assistant bring the rubbed glass tube over the left arm; the lath immediately follows the right hand.

Touch the lath, or any other uninsulated body; the 'attractive virtue,' as it was called by Gray, disappears. After this, as long as the excited tube is held over the arm there is no attraction. But when the tube is removed the attractive power of the hand is restored. Here the first attraction was by positive electricity driven to the right hand from the left, and the second attraction by negative electricity, liberated by the removal of the glass rod. Experiment proves the logic of theory to be without a flaw.

Stand on an insulating stool, and place your right hand on the electroscope: there is no action. Stretch forth the left arm and permit an assistant alternately to bring near, and to withdraw, an excited glass tube. The gold leaves open and collapse in similar alternation. At every approach, positive electricity is driven over the gold leaves; at every withdrawal, the equilibrium is restored.

We are now in a condition to repeat, with ease, the

FIG. 22.



experiment of Du Fay mentioned in § 13. A board is supported by four silk ropes, and on the board is

stretched a boy. Bring his forehead, or better still his nose, under the end of your straw index $11'$, fig. 22. Then bring down over his legs your rubbed glass tube; instantly the end $1'$ is attracted and the end 1 rises along the graduated scale. Before the end $1'$ comes into contact with the nose or forehead a spark passes between it and the boy.

I will now ask you to charge your Dutch metal electroscope (fig. 7) positively by rubbed gutta-percha, and to charge it negatively by rubbed glass. A moment's reflection will enable you to do it. You bring your excited body near: the same electricity as that of the excited body is driven over the leaves, and they diverge by repulsion. Touch the electroscope, the leaves collapse. Withdraw your finger, and withdraw afterwards the excited body: the leaves then diverge with the opposite electricity.

The simplest way of testing the quality of electricity is to charge the electroscope with electricity of a known kind. If, on the *approach* of the body to be tested, the leaves diverge still wider, the leaves and the body are similarly electrified. The reason is obvious.

Omitting the last experiment, the wealth of knowledge which these researches involve might be placed within any intelligent boy's reach by the wise expenditure of half-a-crown.

Once firmly possessed of the principle of induction and versed in its application, the difficulties of our subject will melt away before us. In fact our subsequent work will consist mainly in unravelling phenomena by the aid of this principle.

Without a knowledge of this principle we could

render no account of the attraction of neutral bodies by our excited tubes. In reality the attracted bodies are *not* neutral: they are first electrified by influence, and it is because they are thus electrified that they are attracted.

This is the place to refer more fully to a point already alluded to. Neutral bodies, as just stated, are attracted, because they are really converted into electrified bodies by induction. Suppose a body to be feebly electrified positively, and that you bring your rubbed glass tube to bear upon the body. You clearly see that the induced negative electricity may be strong enough to mask and overcome the weak positive charge possessed by the body. We should thus have two bodies electrified alike, attracting each other. This is the danger against which I promised to warn you in § 10, where the test of attraction was rejected.

We will now apply the principle of induction to explain a very beautiful invention, made known by the celebrated Volta in 1775.


§ 15. *The Electrophorus.*

Cut a circle, T, fig. 23, 6 inches in diameter out of sheet zinc, or out of common tin. Heat it at its centre by the flame of a spirit-lamp or of a candle. Attach to it there a stick of sealing-wax, H, which, when the metal cools, is to serve as an insulating handle.—You have now the *lid* of the electrophorus. A resinous surface, or what is simpler a sheet of vulcanised india-rubber, R, or even of hot brown paper, will answer for the *plate* of the electrophorus.

Rub your 'plate' with flannel, or whisk it briskly

with a fox's brush. It is thereby negatively electrified. Place the 'lid' of your electrophorus on the excited

FIG. 23.



surface: it touches it at a few points only. For the most part lid and plate are separated by a film of air.

The excited surface acts by induction across this film upon the lid, attracting its positive and repelling its negative electricity. You have in fact in the lid two layers of electricity, the lower one, which is 'bound,' positive; the upper one, which is 'free,' negative. Lift the lid: the electricities flow again together; neutrality is restored, and your lid fails to attract your balanced lath.

Once more place the lid upon the excited surface: touch it with th^e finger. What occurs? You ought to know. The free electricity, which is negative, will escape through your body to the earth, leaving the chained positive behind.

Now lift the lid by the handle: what is its condition? Again I say you ought to know. It is covered

with free positive electricity. If it be presented to the lath it will strongly attract it: if it be presented to the knuckle it will yield a spark.

A smooth half-crown, or a penny, will answer for this experiment. Stick to the coin an inch of sealing-wax as an insulating handle: bring it down upon the excited india-rubber: touch it, lift it, and present it to your lath. The lath may be six or eight feet long, three inches wide and half an inch thick; the little electrophorus lid, formed by the half crown, will pull it round and round. The experiment is a very impressive one.

Scrutinise your instrument still further. Let the end of a thin wire rest upon the lid of your electrophorus, under a little weight if necessary; and connect the other end of the wire with the electroscope. As you lower the lid down towards the excited plate of the electrophorus, what must occur? The power of prevision now belongs to you and you must exercise it. The repelled electricity will flow over the leaves of the electroscope, causing them to diverge. Lift the lid, they collapse. Lower and raise the lid several times, and observe the corresponding rhythmic action of the electroscope leaves.

A little knob of sealing-wax, B, coated with tin-foil, or indeed any knob with a conducting surface, stuck to the lid of the electrophorus, will enable you to obtain a better spark. The reason of this will immediately appear.

More than half the value of your present labour consists in arranging each experiment in thought before it is realised in fact; and more than half the delight of your work will consist in observing the verification of what you have foreseen and predicted.

§ 16. *Action of Points and Flames.*

The course of exposition proceeds naturally from the electrophorus to the electrical machine. But before we take up the machine we must make our minds clear regarding the manner in which electricity diffuses itself over conductors, and more especially over elongated and pointed conductors.


Rub your glass tube and draw it over an insulated sphere of metal—of wood covered with tin-foil, or indeed any other insulated spherical conductor. Repeat the process several times, so as to impart a good charge to the sphere. Touch the charged sphere with your carrier, and transfer the charge to the electroscope. Note the divergence of the leaves. Discharge the electroscope, and repeat the experiment, touching, however, some other point of the sphere. The electroscope shows sensibly the same amount of divergence. Even when the greatest exactness of the most practised experimenter is brought into play, the spherical conductor is found to be equally charged at all points of its surface. You may figure the electric fluid as a little ocean encompassing the sphere, and of the same depth everywhere.

But supposing the conductor, instead of being a sphere, to be a cube, an elongated cylinder, a cone, or a disk. The depth, or as it is sometimes called the *density* of the electricity, will not be everywhere the same. The corners of the cube will impart a stronger charge to your carrier than the sides. The end of the cylinder will impart a stronger charge than its middle. The edge of the disk will impart a stronger charge than

its flat surface. The apex or point of the cone will impart a stronger charge than its curved surface or its base.

You can satisfy yourself of the truth of all this in a rough, but certain way, by charging, after the sphere, a turnip cut into the form of a cube; or a cigar-box coated with tin-foil; a metal cylinder, or a wooden one coated with tin-foil; a disk of tin or of sheet zinc; a carrot or parsnip with its natural shape improved so as to make it a sharp cone. You will find the charge imparted to the carrier by the sharp corners and points of such bodies, when electrified, to be greater than that communicated by the gently rounded or flat surfaces. The difference may not be great, but it will be distinct. Indeed an egg laid on its side, as we have

FIG. 24.




already used it in our experiments on induction (fig. 16), yields a stronger charge from its ends than from its middle.

Let me place before you an example of this distribution, taken from the excellent work on 'Frictional Electricity' by Professor Riess of Berlin. Two cones, fig. 24, are placed together base to base. Calling the strength of the charge along the circular edge where the two bases join each other 100, the charge at the apex of the blunter cone is 133; and at the apex of the sharper one

202. The other numbers give the charges taken from the points where they are placed. Fig. 25, moreover,

FIG. 25.



represents a cube with a cone placed upon it. The charge on the face of the cube being 1, the charges at the corners of the cube and at the apex of the cone are given by the other numbers; they are all far in excess of the electricity on the flat surface.

Riess found that he could deduce with great accuracy the *sharpness* of a point, from the charge which it imparted. He compared in this way the sharpness of various thorns, with that of a fine English sewing needle. The following is the result:—Euphorbia thorn was sharper than the needle; gooseberry thorn of the same sharpness as the needle; while cactus, blackthorn, and rose, fell more and more behind the needle in sharpness. Calling, for example, the charge obtained from euphorbia 90; that obtained from the needle was 80, and from the rose only 53.

Considering that each electricity is self-repulsive, and that it heaps itself up upon a point in the manner here shown, you will have little difficulty in conceiving that

when the charge of a conductor carrying a point is sufficiently strong, the electricity will finally disperse itself by streaming from the point.

The following experiments are theoretically important:—Attach a stick of sealing-wax to a small plate of tin or of wood, so that the stick may stand upright. Heat a needle and insert it into the top of the stick of wax; on this needle mount horizontally a carrot. You have thus an insulated conductor. Stick into your carrot at one of its ends a sewing needle; and hold for an instant your rubbed glass tube in front of this needle without touching it. What occurs? The negative electricity of the carrot is immediately discharged from the point against the glass tube. Remove the tube, test the carrot: it is positively electrified.

And now for another experiment, not so easily made, but still certain to succeed if you are careful. Excite your glass rod, turn your needle away from it, and bring the rod near the other end of the carrot. What occurs? The positive electricity is now repelled to the point, from which it will stream into the air. Remove the rod and test the carrot: it is negatively electrified.


Again turn the point towards you, and place in front of it a plate of dry glass, wax, resin, shellac, paraffin, gutta-percha, or any other insulator. Pass your rubbed glass tube once downwards or upwards, the insulating plate being between the excited tube and the point. The point will discharge its electricity against the insulating plate, which on trial will be found negatively electrified.

§ 17. *The Electrical Machine.*

An electrical machine consists of two principal parts; the insulator which is excited by friction, and the 'prime conductor.'

The sulphur sphere of Otto von Guericke was, as already stated, the first electrical machine. The hand was the rubber, and indeed it long continued to be so. For the sulphur sphere, Hauksbee and Winckler substituted globes of glass. Boze of Wittenberg (1741) added the prime conductor, which was at first a tin tube supported by resin, or suspended by silk. Soon afterwards Gordon substituted a glass cylinder for the globe. It was sometimes mounted vertically, sometimes horizontally. Gordon so intensified his discharges as to be able to kill small birds with them. In 1760 Planta introduced the plate machine now commonly in use.

FIG. 26.




Mr. Cottrell has constructed for these Lessons the small cylinder machine shown in fig. 26. The glass

cylinder is about 7 inches long and 4 inches in diameter: its cost is eighteen pence. Through the cylinder passes tightly, as an axis, a piece of lath, rendered secure by sealing-wax where it enters and where it quits the cylinder. *g* is a glass rod supporting the conductor *c*, which is a piece of lath coated with tin-foil. Into the lath is driven the series of pin points, *p, p*. The rubber *r*, is seen at the further side of the cylinder, supported by the upright lath *r'*, and caused to press against the glass. *s'* is a flap of silk attached to the rubber. When the handle is turned sparks may be taken, or a Leyden jar¹ charged at the knob *c*.

A plate machine is shown in fig. 27. *p* is the plate, which turns on an axis passing through its centre;

FIG. 27.



r and *r'* are two rubbers which clasp the plate, with the flaps of silk *s s'* attached to them. *a* and *a'* are rows of

¹ To be subsequently explained.

points forming part of the prime conductor, c. G G' is an insulating rod of glass, which cuts off the connection between the conductor and the handle of the machine.

The prime conductor is charged in the following manner. When the glass plate is turned, as it passes each rubber it is positively electrified. Facing the electrified glass is the row of points, placed midway between the two rubbers. On these points the glass acts by induction, attracting the negative and repelling the positive. In accordance with the principles already explained in § 16, the negative electricity streams from the points against the excited glass, which then passes on neutralised to the next rubber, where it is again excited.


Thus the prime conductor is charged, not by the direct communication to it of positive electricity, but by depriving it of its negative.

If when the conductor is charged you bring the knuckle near it, the electricity passes from the conductor to the knuckle in the form of a spark.

Take this spark with the blunt knuckle while the machine is being turned; and then try the effect of presenting the finger ends, instead of the knuckle, to the conductor. The spark falls exceedingly in brilliancy. Substitute for the finger ends a needle point: you fail to get a spark at all. To obtain a good spark the electricity upon the prime conductor must reach a sufficient density (or tension as it is sometimes called); and to secure this no points from which the electricity can stream out must exist on the conductor, or be presented to it. All parts of the conductor are therefore carefully rounded off, sharp points and edges being avoided.

It is usual to attach to the conductor an electroscope consisting of an upright metal stem, A C, fig.

FIG. 28.



28, to which a straw with a pith ball, B, at its free end, is attached. The straw turns loosely upon a pivot at C. The electricity passing from the conductor is diffused over the whole electroscope, and the straw and stem being both positively electrified, repel each other. The straw, being the movable body, flies away. The amount of the divergence is

measured upon a graduated arc.

§ 18. *Further Experiments on the Action of Points.*
The Electric Mill. The Golden Fish. Lightning Conductors.

If no point exist on the conductor, a single turn of the handle of the machine usually suffices to cause the straw to stand out at a large angle to the stem. If, on the contrary, a point be attached to the conductor, you cannot produce a large divergence, because the electricity, as fast as it is generated, is dispersed by the point. The same effect is observed when you present a point to the conductor. The conductor acts by induction upon the point, causing the negative electricity to stream from it against the conductor, which is thus neutralised almost as fast as it is charged. Flames and glowing embers act like points; they also rapidly discharge electricity.

The electricity escaping from a point or flame into the air renders the air self-repulsive. The consequence

is that when the hand is placed over a point mounted on the prime conductor of a machine in good action, a cold blast is distinctly felt. Dr. Watson noticed this blast from a flame placed on an electrified conductor; while Wilson noticed the blast from a point. Jallabert and the Abbé Nollet also observed and described the influence of points and flames. The blast is called the 'electric wind.' Wilson moved bodies by its action: Faraday caused it to depress the surface of a liquid: Hamilton employed the *reaction* of the electric wind to make pointed wires rotate. The 'wind' was also found to promote evaporation.

Hamilton's apparatus is called the 'electric mill.' Make one for yourself thus: Place two straws ss , $s's'$,

FIG. 29.




fig. 29, about eight inches long, across each other at a right angle. Stick them together at their centres by a bit of sealing-wax. Pass a fine wire through each straw and bend it where it issues from the straw, so as to

form a little pointed arm perpendicular to the straw, and from half an inch to three-quarters of an inch long. It is easy, by means of a bit of cork or sealing-wax, to fix the wire so that the little bent arms shall point not upwards or downwards, but sideways, when the cross is horizontal. The points of sewing needles may also be employed for the bent arms. A little bit of straw stuck into the cross at the centre, forms a cap. This slips over a sewing needle, *N*, supported by a stick of sealing-wax, *A*. Connect the sewing needle with the electric machine, and turn. A wind of a certain force is discharged from every point, and the cross is urged round with the same force in the opposite direction.


You might easily, of course, so arrange the points that the wind from some of them would neutralise the wind from others. But the little pointed arms are to be so bent that the reaction in every case shall not oppose but add itself to the others.

The following experiments will yield you important information regarding the action of points. Stand, as you have so often done before, upon a board supported by four warm tumblers. Hold a small sewing needle, with its point defended by the fore finger of your right hand, towards your Dutch metal electroscope. Place your left hand on the prime conductor of your machine. Let the handle be turned by a friend or an assistant: the leaves of the electroscope open out a little. Uncover the needle point by the removal of your finger; the leaves at once fly violently apart.

Mount a stout wire upright on the conductor, *c*, fig. 30, of your machine; or support the wire by sealing-wax, gutta-percha or glass, at a distance from the

conductor, and connect both by a fine wire. Bend your stout wire into a hook, and hang from it a tassel, T,

FIG. 30.



composed of many strips of light tissue paper. Work the machine. Electricity from the conductor flows over the tassel, and the strips diverge.¹ Hold your closed fist towards the tassel, the strips of paper stretch towards it. Hold the needle, defended by the finger, towards the tassel: attraction also ensues. Uncover the needle without moving the hand; the strips retreat as if blown away by a wind. Holding the needle N, fig. 31, upright underneath the tassel, its strips discharge themselves and collapse utterly.

And now repeat Du Fay's experiment which led to

¹ This is always the case in London. Still even here some days are so dry as to render it difficult to electrify the tassel.





FIG. 31.

the discovery of two electricities. Excite your glass tube, and hold it in readiness while a friend, or an

FIG. 32.




assistant, liberates a real gold or silver leaf in the air. Bring the tube near the leaf: it plunges towards the tube, stops suddenly, and then flies away. You may chase it round the room for hours without permitting it to reach the ground. The leaf is first acted upon inductively by the tube. It is powerfully attracted for a moment, and rushes towards the tube. But from its thin

edges and corners the negative electricity streams forth, leaving the leaf positively electrified. Repulsion then sets in, because tube and leaf are electrified alike, as shown in fig. 32. The retreat of the tassel in the last experiment is due to a similar cause.

There is also a discharge of positive electricity into the air from the more distant portions of the

FIG. 33.



gold-leaf, to which that electricity is repelled. Both discharges are accompanied by an electric wind. It is possible to give the gold-leaf a shape which shall enable it to float securely in the air, by the reaction of the two winds issuing from its opposite ends. This is Franklin's experiment of the Golden Fish. It was first made with the charged conductor of an electrical machine. M.

Srztsczek revived it in a more convenient form, using instead of the conductor the knob of a charged Leyden jar. You may walk round a room with the jar in your hand; the 'fish' will obediently follow in the air an inch or two, or even three inches, from the knob. See A B, fig. 33. Even a hasty motion of the jar will not shake it away.


Well-pointed lightning conductors, when acted on by a thunder cloud, discharge their induced electricity against the cloud. Franklin saw this with great clearness, and illustrated it with great ingenuity. The under side of a thunder cloud, when viewed horizontally, he observed to be ragged, composed, in fact, of fragments one below the other, sometimes reaching near the earth. These he regarded as so many stepping-stones which assist in conducting the stroke of the cloud. To represent these by experiment he took two or three locks of fine loose cotton, tied them in a row, and hung them from his prime conductor. When this was excited the locks stretched downwards towards the earth; but by presenting a sharp point erect under the lowest bunch of cotton, it shrunk upwards to that above it, nor did the shrinking cease till all the locks had retreated to the prime conductor itself. 'May not,' says Franklin, 'the small electrified clouds, whose equilibrium with the earth is so soon restored by the point, rise up to the main body, and by that means occasion so large a vacancy, that the grand cloud cannot strike in that place?'

§ 19. *History of the Leyden Jar. The Leyden Battery.*

The next discovery which we have to master throws all former ones into the shade. It was first announced in

a letter addressed on the 4th of November, 1745, to Dr. Lieberkühn, of Berlin, by Kleist, a clergyman of Cammin, in Pomerania. By means of a cork, c, fig. 34,

FIG. 34.



he fixed a nail, n, in a phial, g, into which he had poured a little mercury, spirits, or water, w. On electrifying the nail he was able to pass from one room into another with the phial in his hand and to ignite spirits of wine with it. 'If,' said he, 'while it is electrifying I put my finger, or a piece of gold which I hold in my hand, to the nail, I receive a shock which stuns my arms and shoulders.'

In the following year Cunæus of Leyden made substantially the same discovery. It caused great wonder and dread, which arose chiefly from the excited imagination. Musschenbroek felt the shock, and declared in a letter to a friend that he would not take a second one for the crown of France. Bleeding at the nose, ardent fever, a heaviness of head which endured for days, were all ascribed to the shock. Boze wished that he might die of it, so that he might enjoy the honour of having his death chronicled in the Paris Academy

of Sciences.' Kleist missed the explanation of the phenomenon; while the Leyden philosophers correctly stated the conditions necessary to the success of the experiment. Hence the phial received the name of the Leyden phial, or Leyden jar.

The discovery of Kleist and Cunæus excited the most profound interest, and the subject was explored in all directions. Wilson in 1746 filled a phial partially with water, and plunged it into water, so as to bring the water surfaces, within and without the phial, to the same level. On charging such a phial the strength of the shock was found greater than had been observed before.

Two years subsequently Dr. Watson and Dr. Bevis noticed how the charge grew stronger as the area of the conductor in contact with the outer surface of the phial increased. They substituted shot for water inside the jar, and obtained substantially the same effect. Dr. Bevis then coated a plate of glass on both sides with silver foil, to within about an inch of the edge, and obtained from it discharges as strong as those obtained from a phial containing half a pint of water. Finally Dr. Watson coated his phial inside and out with silver foil. By these steps the Leyden jar reached the form which it possesses to-day.

It is easy to repeat the experiment of Dr. Bevis. Procure a glass plate nine inches square; cover it on both sides, as he did, with tin-foil seven inches square, leaving the rim uncovered. Connect one side with the earth and the other with the machine. Charge and discharge: you obtain a brilliant spark.

In our experiment with the Golden Fish (fig. 33), we employed a common form of the Leyden jar, only with

the difference that to get to a sufficient distance from the glass, so as to avoid the attraction of the fish by the jar itself, the knob was placed higher than usual. But with a good flint-glass tumbler, a piece of tin-foil, and a bit of stout wire, you can make a jar for yourself. Bad glass, remember, is not rare.¹ In fig. 35 you have

FIG. 35.



such a jar. τ is the outer, τ' the inner coating, reaching to within an inch of the edge of the tumbler G . w is the wire fastened below by wax, and surmounted by a knob, which may be of metal, or of wax or wood, coated with tin-foil. In charging the jar you connect the outer coating with the earth—say with a gas-pipe or a water-pipe—and present the knob to the conductor of your machine. A few turns will charge the jar. It is discharged by laying one knob of a 'discharger' against the outer coating, and causing the other knob to approach the knob of the jar. Before

¹ In preparing these Lessons we have made several jars which refused to be charged, through the badness of their glass, and which showed their imperfect insulation by discharging our electroscope.

contact, the electricity flies from knob to knob in the form of a spark.





FIG. 36.

A 'discharger' suited to our means and purposes is shown in fig. 36. *H* is a stick of sealing-wax, or, better still, of ebonite: *W W* a stout wire bent as in the figure, and ending in the knobs *B B'*. These may be of wax coated with tin-foil. Any other light conducting knobs would of course answer. The insulating handle *H* protects you effectually from the shock.

You must render yourself expert in the use of the discharger. The mode of using it is shown in fig. 37.


FIG. 37.



By augmenting the size of a Leyden jar we render

it capable of accepting a larger charge of electricity. But there is a limit to the size of a jar. When, therefore, larger charges are required than a single jar can furnish, we make use of a number of jars. In fig. 38

FIG. 38.



nine of them are shown. All their interior coatings are united together by brass rods, while all the outer coatings rest upon a metal surface in free communication with the earth.

This combination of Leyden jars constitutes the *Leyden Battery*, the effect of which is equal to that of a single jar of nine times the size of one of the jars.

§ 20. *Explanation of the Leyden Jar.*

The principles of electrical induction with which you are now so familiar will enable you to thoroughly

analyse and understand the action of the Leyden jar. In charging the jar the outer coating is connected with the earth, and the inner coating with the electrical machine. Let the machine, as usual, be of glass yielding positive electricity. When it is worked the electricity poured into the jar acts inductively across the glass upon the outer coating; attracting its negative and repelling its positive to the earth. Two mutually attractive electric layers are thus in presence of each other, being separated merely by the glass. When the machine is in good order and the glass of the jar is thin, the attraction may be rendered strong enough to perforate the jar. By means of the discharger the opposite electricities are enabled to unite in the form of a spark.

Franklin saw and announced with clearness the escape of the electricity from the outer coating of the jar. His statement is that whatever be the quantity of the 'electric fire' thrown into the jar, an equal quantity was dislodged from the outside. We have now to prove by actual experiment that this explanation is correct.

Place your Leyden jar upon a table, and connect the outer coating with your electroscope. There is no divergence of the leaves when electricity is poured into the jar.


But here the outer coating is connected through the table with the earth. Let us cut off this communication by an insulator. Place the jar upon a board supported by warm tumblers, or upon a piece of vulcanised india-rubber cloth, and again connect the outer coating with the electroscope. The moment electricity is communicated to the knob of the jar the leaves of Dutch metal diverge. Detach the wire by your discharger

and test the quality of the electricity—it is positive, as theory declares it must be.

Consider now the experiment of Kleist and Cunæus (fig. 34). You will, I doubt not, penetrate its meaning. You will see that in their case the *hand* formed the outer coating of the jar. When electricity was communicated through the nail to the water within, that electricity acted across the glass inductively upon the hand, attracting the one fluid and repelling the other to the earth.

Again I say, prove all things; and what is here affirmed may be proved by the following beautiful and

FIG. 39.



conclusive experiment:—Stand on your board, 11', fig. 39,

insulated by its four tumblers; or upon a sheet of gutta-percha, or vulcanised india-rubber. Seize the old Leyden phial, J, with your left hand, and present the knuckle of your right hand to your balanced lath, L' L. When electricity is communicated to the nail, the lath is immediately attracted by the knuckle. Or touch your electroscope with your right hand: when the phial is charged the leaves immediately diverge, by the electricity driven from your left hand to the electroscope.

Here the nail may be electrified either by connecting it with the prime conductor of the machine, or by rubbing it with an excited glass rod. Indeed I should prefer your resorting to the simplest and cheapest means in making these experiments.


§ 21. *Franklin's Cascade Battery.*

As a thoughtful and reflective boy or girl you cannot, I think, help wondering at the power which your thorough mastery of the principles of induction gives you over these wonderful and complicated phenomena. By those principles the various facts of our science are bound together into an organic whole. But we have not yet exhausted the fruitfulness of this principle.

Consider the following problem. Usually we allow the electricity of the outer coating to escape to the earth. Suppose we try to utilise it. Place, then, your jar A B, fig. 40, upon vulcanised india-rubber, and connect by a wire B C its outer coating with the knob or inner coating of a second jar C D. What will occur when the first jar is charged? Why, the second one will be charged also by the electricity which has escaped from the outer coating of the first. And suppose you connect the outer coat-

ing of the second insulated jar with the inner coating of a third, EF; what occurs? The third jar will obviously be charged with the electricity repelled from the outer coating of the second. Of course we need not stop here. We may have a long series of insulated jars, the outer coating of each being connected with the inner coating of the next succeeding one. Connect the outer coating of the last jar IK by a wire *e* with the earth, and charge the first jar. You charge thereby the entire series of jars. In this simple way you master practi-

FIG. 40.



cally, and grasp the theory of Franklin's celebrated 'cascade battery.'

You must see that before making this important experiment you could really have predicted what would occur. This power of prevision is one of the most striking characteristics of science.

§ 22. Novel Leyden Jars of the Simplest Form.

Possessed of its principles, we can reduce the Leyden jar to far simpler forms than any hitherto

dealt with. Spread a sheet of tin-foil smoothly upon a table, and lay upon the foil a pane of glass. Remember that the glass, as usual, must be dry. Stick on to the glass by sealing-wax two loops of narrow silk ribbon, by which the pane may be lifted; and then lay smoothly upon the glass a second sheet of tin-foil, less than the pane in size, leaving a rim of uncovered glass all round. Carry a fine wire from the upper sheet of tin-foil to your electroscope. A little weight will keep the end of the wire attached to the tin-foil.

Rub this weight with your excited glass tube, two or three times if necessary, until you see a slight divergence of the Dutch metal leaves. Or connecting the weight with the conductor of your machine, turn very carefully until the slight divergence is observed. What is the condition of things here? You have poured, say positive electricity on to the upper sheet of metal. It acts inductively across the glass upon the under sheet, the positive fluid of which escapes to the earth, leaving the negative behind. You see before your mind's eye two layers holding each other in bondage. Now take hold of your loops and lift the glass plate, so as to separate the upper tin-foil from the lower. What would you expect to occur? Freed from the grasp of the lower layer, the electricity of the upper one will diffuse itself over the electroscope so promptly and powerfully, that if you are not careful you will destroy the instrument by the mutual repulsion of its leaves.

Practise this experiment, which is a very old one of mine, by lowering and lifting the glass plate, and observing the corresponding rhythmic action of the leaves of the electroscope.

Common tin-plate may be used in this experiment


instead of tin-foil, and a sheet of vulcanised india-rubber instead of the pane of glass. Or simpler still, for the tin-foil a sheet of common unwarmed foolscap may be employed. Satisfy yourself of this. Spread a *sheet* of foolscap on a table; lay the plate of glass upon it, and spread a *leaf* of foolscap, less than the glass in size, on the plate of glass. Connect the leaf with the electroscope, and charge it, exactly as you charged the tin-foil. On lifting the glass with its leaf of foolscap, the leaves of the electroscope instantly fly apart; on lowering the glass they again fall together. Abandon the under sheet altogether, and make the table the outer coating; if it be not of very dry wood, or covered by an insulating varnish, you will obtain with it the results obtained with the tin-foil, tin, and foolscap. Thus by the simplest means we illustrate great principles.

The withdrawal of the electricity from the electroscope, by lowering the plate of glass, so as to bring the electricity of the upper coating within the grasp of the lower one, is sometimes called 'condensation.' The electricity on one plate or sheet was figured as squeezed together, or condensed, by the attraction of the other. A special instrument called a *condenser* is constructed by instrument makers to illustrate the action here explained.

You may readily make a condenser for yourself. Take two circles, P P' , fig. 41, of tin or of sheet zinc, and support the one, P' , by a stick of sealing-wax or glass, G ; the other, P , by a metal stem, connected with the earth. The insulated plate, P' , is called the collecting plate; the uninsulated one, P , the condensing plate. Connect the collecting plate with your electro-


scope by the wire *w*, and bring the condensing plate near it, leaving, however, a thin space of air between

FIG. 41.



them. Charge the collector, *P'*, or the wire, *w*, with your glass rod, until the leaves of the electroscope *begin* to diverge. Withdraw the condensing plate, the leaves fly asunder; bring the condensing plate near, the leaves again collapse.

FIG. 42.



Or vary your construction, and make your con-

denser thus. Employing the table, or a sheet of foolscap if the table be an insulator, as one plate of the condenser, spread upon it the sheet of india-rubber, *p*, fig. 42, and lay upon the rubber the sheet of block-tin *A B*. Connect the tin by the wire, *w*, with the electroscope, *T*. Impart electricity to the little weight, *A*, till the leaves, *L*, begin to diverge; then lift the tin-plate by its two silk loops; the leaves at once fly asunder.

Finally show your complete knowledge of the Leyden jar, and your freedom from the routine of the instrument makers, by making a 'jar' in the following novel way. Stand upon a board supported by warm tumblers. Hold in your right hand a sheet of vulcanised india-rubber, and clasp, with it between you, the left hand of a friend in connection with the earth. Place your left hand on the conductor of the machine, and let it be worked. You and your friend soon feel a crackling and a tickling of the hands, due to the heightening attraction of the opposite electricities across the india-rubber. The 'hand-jar' is then charged. To discharge it you have only to bring your other hands together: the shock of the Leyden jar is then felt and its spark seen and heard.

By the discharge of the hand-jar you can fire gunpowder. But this will be referred to more particularly further on. (See § 25.)

§ 23. *Seat of Charge in the Leyden Jar.*

Franklin sought to determine how the charge was hidden in the Leyden jar. He charged with electricity a bottle half-filled with water and coated on the outside with tin-foil: dipping the finger of one hand into the

water, and touching the outside coating with the other, he received a shock. He was thus led to inquire, is the electricity in the water? He poured the water into a second bottle, examined it, and found that it had carried no electricity along with it.

His conclusion was 'that the electric fire must either have been lost in the decanting, or must have remained in the bottle. The latter he found to be true; for, filling the charged bottle with fresh water, he obtained the shock, and was therefore satisfied that the power of giving it resided in the glass itself.'¹

(An account of Franklin's discoveries was given by him in a series of letters addressed to Peter Collinson, Esq., F.R.S., from 1747 to 1754.)

So much for history; but you are to verify the history by repeating Franklin's experiments. Place water in a wide glass vessel; place a second glass vessel within the first, and fill it to the same height with water. Connect the outer water by a wire with the earth, and the inner water by a wire with the electric machine. One or two turns furnish a sufficient charge. Removing the inner wire, and dipping one finger into the outside and the other into the inside water, a smart shock is felt. This was Franklin's first experiment.

Pass on to the second. Coat a glass jar with tin-foil (not too high); fill it to the same height with water, and place it on india-rubber cloth. Charge it by connecting the outside coating with the earth, and the water inside (by means of a stem cemented to the bottom of the jar and ending above in a knob) with an electric

¹ Priestley's 'History of Electricity, 3rd edition, p. 149.

machine. You obtain a bright spark on discharging. This proves your apparatus to be in good order.

Re-charge. Take hold of the charged jar with the india-rubber, and pour the water into a second similar jar. No sensible charge is imparted to the latter. Pour fresh unelectrified water into the first jar, and discharge it. The retention of the charge is shown by a brilliant spark. Be careful in these experiments, or you will fail as I did at first. The edge of the jar out of which the water is poured has to be surrounded by a band of bibulous paper to catch the final drop, which, trickling down, would discharge the jar.

Experiments like those of Franklin are now made by rendering the coatings of the Leyden jar movable. Such a jar being charged, the interior coating may be lifted out and proved unelectric. The glass may then be removed from the outer coating and the latter proved unelectric. Restoring the jar and coatings, on connecting the two latter, the discharge passes in a brilliant spark.

Make a jar with movable coatings thus:—Roll cartridge paper round a good flint-glass tumbler, *g*, fig. 43, to within about an inch of the top. Paste down the lower edge of the paper, and put a paper bottom to it corresponding to the bottom of the glass. Coat the paper, *t*, inside and out with tin-foil. Make a similar coating, *t'*, for the inside of the tumbler, attaching to it an upright wire, *w*, ending in a hook. You have then to all intents and purposes a Leyden jar.

FIG. 43.



Put the pieces together and charge the jar. By means of a rod of glass, sealing-wax, or gutta-percha, lift out the interior coating. It will carry a little electricity away with it. Place it upon a table and discharge it wholly. Then by the hand lift the glass out of the outer coating. Neither of the coatings now shows the slightest symptom of electricity. Restore the tumbler to its outer coating, and, by means of the hook and insulating rod, restore the inner coating to its place. Discharge the jar: you obtain a brilliant spark. The electricity which produces this spark must have been resident in and on the glass.

Here, as in all other cases, you can charge your jar with a rubbed glass tube, though a machine in good working order will do it more rapidly. With 'Cottrell's rubber,' described in the next section, you may greatly exalt the performance of your glass tube.

§ 24. *Ignition by the Electric Spark. Cottrell's Rubber. The Tube-machine.*


Various attempts had been vainly made by Nollet and others to ignite inflammable substances by the electric spark. This was first effected by Ludolf, at the opening of the Academy of Sciences by Frederick the Great at Berlin, on the 23rd of January, 1744. With a spark from the sword of one of the court cavaliers present on the occasion, Ludolf ignited sulphuric ether.

Dr. Watson also made numerous experiments on the ignition of bodies by the electric spark. He fired gunpowder and discharged guns. Causing, moreover, a spoon containing ether to be held by an electrified person,

he ignited the ether by the finger of an unelectrified person. He also noticed that the spark varied in colour when the substances between which it passed varied.

These, and numerous other experiments may be made with a far simpler 'machine' than any hitherto described. It was devised for your benefit by Mr. Cottrell. In the electric machine, as we have learned, the prime conductor is flooded with positive electricity through the discharge of the negative from the points against the excited glass. Your glass tube and rubber may be similarly turned to account. A strip of sheet-brass or copper, *P*, fig. 44, is sewn on to the edge of

FIG. 44.




the silk pad, *R*, employed as a rubber. Through apertures in the strip about twenty pin-points are introduced, and soldered to the metal. When the tube is clasped by the rubber, the metal strip and points quite encircle the tube.

When a fine wire, *w*, connects the strip of metal with the knob of a Leyden jar, by every downward stroke of the rubber the glass tube is powerfully excited, and

hotly following the exciting rubber is the circle of points. From these, against the rod, negative electricity is discharged, the free positive electricity escaping along the wire to the jar, which is thus rapidly charged.

The ignition of gas is readily effected by Cottrell's rubber. Connecting the strip of metal, *r*, fig. 45, with an insulated metallic knob, *B*, placed within a quarter or an eighth of an inch of an uninsulated argand burner connected with the earth, at every downward stroke of the rubber a stream of sparks passes between the knob

FIG. 45.




and burner. If gas be turned on, it is immediately ignited by the stream of sparks. Blowing out the flame and repeating the experiment, every stroke of the rubber infallibly ignites the gas.

Sulphuric ether, in a spoon which has been previously warmed, is thus ignited: but the ether soon cools by evaporation; its vapour is diminished by the cold, and it is then less easy to ignite. Bisulphide of carbon may be substituted for the ether, with the certainty

that every stroke of the rubber will set it ablaze.¹ The spark thus obtained also fires a mixture of oxygen and hydrogen. The two gases unite with explosion to form water, when an electric spark is passed through them.

Mr. Cottrell has also mounted his glass tube so as to render friction in both directions available. The *tube-machine* is represented in fig. 46. A B is the glass

FIG. 46.



tube, clasped by the rubber, R. P P' are two strips of metal furnished with rows of points. From P P' wires proceed to the knob C, which is insulated by the horizontal stem, G. This insulating stem may be abolished with advantage, the wires from P and P' being rendered strong enough to support the ball C.

¹ I am indebted to Dr. Debus for the suggestion of the bisulphide as a substitute for the ether.

At c sparks may be taken, a Leyden jar charged, the electric mill turned, while wires carried from it may be employed in experiments on ignition. I however strongly recommend to your attention the more simple rubber shown in fig. 44.


‘Seldom,’ says Riess, ‘has an experiment done so much to develope the science to which it belongs as this of the ignition of bodies by the electric spark.’ It aroused universal interest; and was repeated in all Royal houses. Money was ready for the further prosecution of electrical research. The experiment afterwards spread among the people. Riess considers it probable that the general interest thus excited led to the discovery of the Leyden jar, which was made soon afterwards.

Klingenstierna astonished King Frederick of Sweden by igniting a spoon of alcohol with a piece of ice. With Cottrell’s rubber and bisulphide of carbon this striking experiment is easily made, and you ought to render your knowledge complete by repeating it. At every stroke of the rubber the spark from the end of a pointed rod of ice infallibly sets the bisulphide on fire.

Cadogan Morgan, in 1785, sought to produce the electric spark in the interior of solid bodies. He inserted two wires into wood, and caused the spark to pass between them: the wood was illuminated with blood-red light, or with yellow light, according as the depth at which the spark was produced was greater or less. The spark of the Leyden jar produced within an ivory ball, an orange, an apple, or under the thumb, illuminates these bodies throughout. A lemon is especially suited to this experiment; flashing forth at every spark as a spheroid of brilliant golden light. The

manner in which the lemon is mounted on the brass stem B is shown in fig. 47. The spark occurs at s, in the interval between the stems A and B. A row of

FIG. 47.



eggs in a glass cylinder is also brilliantly illuminated at the passage of every spark from a Leyden jar.


§ 25. Duration of the Electric Spark.

The duration of the electric spark is very brief: in a special case, Sir Charles Wheatstone found it to be $\frac{1}{24000}$ th of a second. This, however, was the maximum duration. In other cases it was less than the millionth of a second.

When a body is illuminated for an instant, the image of the body remains upon the retina of the eye for about one-fifth of a second. If, then, a body in swift motion be illuminated by an *instantaneous* flash, it will be seen to stand motionless for one-fifth of a second at the point where the flash falls upon it. A rifle bullet passing through the air, and illuminated by

an electric flash, would be seen thus motionless; a circle like DD' , fig. 48, divided into black and white sectors, and rotating so quickly as to cause the sectors

^c
FIG. 48.




to blend to a uniform grey, appears, when illuminated by the spark of a Leyden jar, perfectly motionless, with all its sectors revealed. A falling jet of water, which appears continuous, is resolved by the electric flash into its constituent drops. Lightning, as shown by Professor Dove, is similarly rapid in its discharge.

For a long time it was found almost impossible to ignite gunpowder by the electric spark. Its duration is so brief that the powder, when the discharge occurred in its midst, was simply scattered violently about. In 1787 Wolff introduced into the circuit through which the discharge passed a glass tube wetted on the inside. He thereby rendered the ignition certain. This was owing to the retardation of the spark by the imperfect conductor. Gun-cotton, phosphorus, and amadou, which are torn asunder by the unretarded spark, are ignited when the discharge is retarded by a tube of water. A wetted string is the usual means resorted to for retardation when gunpowder is to be discharged.

The instrument usually employed for the ignition of powder is the universal discharger. We make our own discharger thus:— i and i' (fig. 49) are insulating

FIG. 49.




rods of glass or sealing-wax, supporting two metal arms, the ends of which can be brought down upon the little central table s . One of the metal arms of the discharger being connected by a wire e with the earth, the separated ends of the two arms are surrounded with powder at s . Sending through it the unretarded charge, the powder is scattered mechanically. Introducing the wet string w into the circuit, ignition infallibly occurs when the spark passes.

This is the place to fulfil our promise to ignite gunpowder by the 'hand-jar.' Fig. 50 explains the arrangement. h h' are the hands of the insulated person, r

the hand of the uninsulated friend, & the india-rubber between both hands. The lead ball *B* is suspended by a wet string *S*. On the little stand *P*, connected with

FIG. 50.



the earth, is placed the powder. The charging of the hand-jar is described in § 22. When charged, it is only necessary to bring the ball *B* down upon the powder to cause it to explode.

§ 26. *Electric Light in Vacuo.*


The electric light in vacuo was first observed by Picard in 1675. While carrying a barometer from the Observatory to the Porte St. Michel in Paris, he saw light in the upper portion of the tube. Sebastien and Cassini observed it afterwards in other barometers. John Bernouilli devised a 'mercurial phosphorus,' by shaking mercury in a tube which had been exhausted by an

air-pump. This was handed to the King of Prussia—Frederick I.—who awarded for it a medal of forty ducats value. The great mathematician wrote a poem in honour of the occasion.

Bernouilli failed to explain the effect. The explanation was reserved for Hauksbee, who in 1705 took up the subject and experimented upon it before the Royal Society. On the plate of an air-pump he placed two bell-jars, one over the other. The outer and larger jar was open at the top. Into the opening Hauksbee fixed, air-tight, a funnel, which he stopped with a plug of wood and filled with mercury. He exhausted the space between the two jars, withdrew the wooden plug and allowed the mercury to stream against the outer surface of the inner jar. He thus obtained a shower of fire. This is a truly beautiful experiment when witnessed by an observer close at hand.

A copy of Hauksbee's own figure illustrating this experiment is annexed, fig. 51. *M* is the funnel containing the mercury, *P* the plug of wood, *s* the outer and *s'* the inner bell-jar. Instead of the plug *P*, an india-rubber tube, held by a clip, may be employed with advantage to connect the funnel with the exhausted jar. By gradually relaxing the clip the mercury may be made to fall at a rate corresponding to the maximum luminous effect. The streams of light

FIG. 51.



produced are very beautiful, but they are more continuous than they are shown to be by Hauksbee.

In 1706 Hauksbee referred the phenomenon to its true cause, namely, the friction between mercury and glass in the highly rarefied air. John Bernouilli ridiculed Hauksbee's explanation. But truth outlives ridicule, and it is now universally admitted that Hauksbee was right.

Hauksbee also made the following experiment, which, as shown by Riess, is explained by reference to the principle of induction. A hollow glass globe was mounted so as to be capable of quick rotation. It was exhausted, and while it rotated the hand was placed against it in the dark. It was positively electrified by the hand. This positive electricity acted inductively on the glass itself, attracting its negative, but discharging its positive as a luminous glow through the rarefied air within. Hauksbee was able to read by the light thus produced.

By such experiments it was shown that rarefied air favoured the passage of electricity. Dry air is in fact an insulator, which must be broken through to produce the electric spark. Through an exhausted glass tube six feet long a discharge freely passes which would be incompetent to leap over the fiftieth part of this interval in air. But whereas the spark in air is dense and brilliant, the discharge in vacuo fills the exhausted tube with a diffuse light.

(It is here worthy of remark that at a very early period Grummert, a Pole, proposed the employment of this diffuse electric light to illuminate coal mines—a notion which has been revived in our day. The light

in this form is not competent to ignite the explosive gases which produce such terrible disasters in mines.)

Priestley, in his 'History of Electricity,' thus describes the light in vacuo. "Take a tall receiver, very dry, and in the top of it insert with cement a wire not very acutely pointed, then exhaust the receiver and present the knob of the wire to the conductor, and every spark will pass through the vacuum in a broad stream of light, visible through the whole length of the receiver, be it ever so tall. This stream often divides itself into a variety of beautiful rivulets, which are continually changing their course, uniting and dividing again in the most pleasing manner. If a jar be discharged through this vacuum, it gives the appearance of a very dense body of fire, darting directly through the centre of the vacuum without ever touching the sides.'

Cavendish employed a double barometer-tube, bent into the form of a horseshoe, with its curved portion empty, to show the passage of electricity through a vacuum. It is really not the vacuum which conducts the electricity, but the highly attenuated air and vapour which fill the space above the barometric columns. When the mercury employed is carefully purged of air and moisture by previous boiling, the space above the mercury, as proved by Walsh, De Luc, Morgan, and Davy, is wholly incapable of conducting electricity. Similar experiments have been made in the laboratory of Mr. Gassiot, to whom we are indebted for so many beautiful electrical experiments. Professor Dewar has also brought his experimental skill to bear with success upon this subject.

Electricity therefore does not pass through a true vacuum; it requires ponderable matter to carry it. If

a gold-leaf electroscope be kept at a distance from all conductors, it may be kept charged for an almost indefinite period in a good air-pump vacuum.

The matter rendered thus luminous by the electrical discharge is attracted and repelled like other electrified matter. 'A finger,' says Priestley, 'put on the outside of the glass will draw it [the luminous stream] wherever a person pleases. If the vessel be grasped with both hands, every spark is felt like the pulsation of a great artery, and all the fire makes towards the hands. This pulsation is felt at some distance from the receiver; and in the dark a light is seen betwixt the hands and glass.'

'All this,' continues the historian of Electricity, 'while the pointed wire is supposed to be electrified positively; if it be electrified negatively the appearance is remarkably different. Instead of streams of fire, nothing is seen but one uniform luminous appearance, like a white cloud, or the milky-way on a clear star-light night. It seldom reaches the whole length of the vessel, but is generally only like a lucid ball at the end of the wire.'


Of the two appearances here described the former is now known as the *electric brush*, and the latter as the *electric glow*. Both can be produced in unconfined air. The glow is sometimes seen on the masts of ships, and it is mentioned by the ancients as appearing on the points of lances. It is called St. Ermo's or St. Elmo's fire, after the sailor's saint, Erasmus, who suffered martyrdom at Gaeta at the beginning of the fourth century.

The purple colour of the diffused light in attenuated air was noticed by Hauksbee. The colour depends upon the residue of attenuated gas, or vapour, through which the discharge passes. If it be an oxygen-residue

the light is whitish, if it be a hydrogen-residue the light is red, if a nitrogen-residue the light is purple, exactly resembling that displayed at times by the aurora borealis—a colour doubtless due to the discharge of electricity through the attenuated nitrogen of the air.

Electric light in vacuo is readily produced by the friction of an amalgamated rubber against the outside

FIG. 52.



of an exhausted tube. The light also is produced by the friction of mercury within a barometric vacuum. The discharges through tubes many feet in length and

exhausted by an air-pump are very fine. The double barometer tube of Cavendish also yields a truly splendid bow of light, when a strong electric discharge is sent through it. For this experiment fig. 52 shows the best arrangement. P is the prime conductor of an electrical machine, I an insulated metal ball, connected by a wire with the mercury trough A. The trough B is connected by a wire with the earth. c and c' mark the height of the mercurial columns. When the machine is worked sparks pass from P to I, a vivid bow of light at each passage stretching from c to c'. By causing I to approach P, the discharges become more frequent, but more feeble; by augmenting the distance P I, the sparks become rarer, but more strong. When very strong, a bow of dazzling brilliancy accompanies every spark.¹

Small tubes for these experiments are best obtained from philosophical instrument makers.

§ 27. *Lichtenberg's Figures.*

Lichtenberg devised a means of revealing the condition of an electrified surface by dusting it with powder. Red lead, in passing through muslin, is positively electrified; flower of sulphur is negatively electrified. Whisking a fox's brush over a cake of resin, and drawing over the surface the knob of a Leyden jar, positively charged, the resin is rendered in part negative and in part positive. Dusting the mixed powder over the surface, the sulphur arranges itself over the positive places, and the red lead over the negative places, a very beautiful pattern being the result.

¹ It is well to have the interval P I at some distance from the bow, so that the light of the spark shall not impair the effect of the discharge upon the eye.

This experiment of Lichtenberg's constituted the germ of Chladni's important acoustical researches. 'Chladni's figures' were the direct offspring of 'Lichtenberg's figures.'

§ 28. *Surface Compared with Mass. Distribution of Electricity in Hollow Conductors.*

Monnier proved that the charge of a conductor depended upon its surface, and not upon its solid contents. An anvil weighing 200 lbs. gave a smaller spark than a speaking trumpet weighing 10 lbs. A solid ball of lead gave a spark only of the same force as that obtained from a piece of thin lead of the same superficies, bent into the form of a hoop. Finally Monnier obtained a strong spark from a long strip of sheet lead, but a very small one when it was rolled into a lump.

Le Roi and D'Arcy showed that a hollow sphere accepted the same charge when empty as when filled with mercury, which augmented its weight 60-fold. All this proves the influence of *surface* as distinguished from *mass*.


The distribution of electricity is well illustrated by the deportment of hollow bodies. Impart by your carrier (fig. 15) successive measures of electricity to the interior of an insulated ice-pail, or a pewter pot. On testing the interior of the vessel with the carrier and an electroscope no electricity is found there; but it is found on the external surface. A hat suspended by silk strings answers as well as the ice-pail.

This experiment with the hat is a very instructive one. The hat may be charged either with Cottrell's rubber or with your rubbed glass tube.

Notice, when testing, that you take your strongest charges from the edges and not from the round or flat surface of the hat. The strongest charge of all is communicated to the carrier by the leaf of the hat.

The successive charges may be communicated to the hat by a metal ball suspended by silk. The charged ball, on touching the interior surface, becomes completely unelectric.

FIG. 53.



Franklin placed a long chain in a silver teapot which he electrified. Connecting his teapot with a pith-ball electroscope he produced a divergence. Then lifting the chain by a silk string he found that over

the portion outside the teapot the electricity diffused itself, this withdrawal of the electricity from the electroscope being announced by the partial collapse of the divergent pith-balls.

The mode of repeating this experiment is shown in fig. 53, where τ is the teapot, supported on a good glass tumbler g , and connected by the wire w with the electroscope E . The effect is small, but distinct.

The greatest experiment with hollow conductors was made by Faraday, who placed himself in a cubical chamber built of laths and covered with paper and wire gauze. It was suspended by silk ropes. Within this chamber he could not detect the slightest sign of electricity, however delicate his electroscope, and however strongly the sides of the chamber might be electrified.

§ 29. *Physiological Effects of the Electric Discharge.*

The physiological effect of the electric shock has been studied in various ways. Graham caused a number of persons to lay hold of the same metal plate, which was connected with the outer coating of a charged Leyden jar, and also to lay hold of a rod by which the jar was discharged. The shock divided itself equally among them.

The Abbé Nollet formed a line of one hundred and eighty guardsmen, and sent the discharge through them all. He also killed sparrows and fishes by the shock. The analogy of these effects with those produced by thunder and lightning could not escape attention, nor fail to stimulate enquiry.

Indeed, as experimental knowledge increased, men's thoughts became more definite and exact as regards the relation of electrical effects to thunder and lightning.

The Abbé Nollet thus quaintly expresses himself: 'If any one should take upon him to prove, from a well-connected comparison of phenomena, that thunder is, in the hands of Nature, what electricity is in ours, and that the wonders which we now exhibit at our pleasure are little imitations of those great effects which frighten us; I avow that this idea, if it was well supported, would give me a great deal of pleasure.' He then points out the analogies between both, and continues thus: 'All those points of analogy, which I have been some time meditating, begin to make me believe that one might, by taking electricity as the model, form to one's self, in relation to thunder and lightning, more perfect and more probable ideas than what have been offered hitherto.'¹

These views were prevalent at the time now referred to, and out of them grew the experimental proof by the great physical philosopher, Franklin, of the substantial identity of the lightning flash and the electric spark.

Franklin was twice struck senseless by the electric shock. He afterwards sent the discharge of two large jars through six robust men; they fell to the ground and got up again without knowing what had happened; they neither heard nor felt the discharge. Priestley, who made many valuable contributions to electricity, received the charge of two jars, but did not find it painful.

This experience agrees with mine. Some time ago I stood in this room with a charged battery of fifteen large Leyden jars beside me. Through some awkwardness on my part I touched the wire leading from the battery, and the discharge went through me. For a

¹ Priestley's 'History of Electricity,' pp. 151-52.

sensible interval life was absolutely blotted out, but there was no trace of pain. After a little time consciousness returned ; I saw confusedly both the audience and the apparatus, and concluded from this, and from my own condition, that I had received the discharge. To prevent the audience from being alarmed, I made the remark that it had often been my desire to receive such a shock accidentally, and that my wish had at length been fulfilled. But though the *intellectual* consciousness of my position returned with exceeding rapidity, it was not so with the *optical* consciousness. For, while making the foregoing remark, my body presented to my eyes the appearance of a number of separate pieces. The arms, for example, were detached from the trunk and suspended in the air. In fact, memory, and the power of reasoning, appeared to be complete, long before the restoration of the optic nerve to healthy action.

This may be regarded as an experimental proof that people killed by lightning suffer no pain.

§ 30. *Atmospheric Electricity.*

The air at all times can be proved to be a reservoir of electricity, which undergoes periodic variation. We have seen that ingenious men began soon to suspect a common origin for the crackling and light of the electric spark, and thunder and lightning. The greatest investigator in this field is the celebrated Dr. Franklin. He made an exhaustive comparison of the effects of electricity and those of lightning. The lightning flash he saw was of the same shape as the elongated electric spark ; like electricity, lightning strikes pointed objects

in preference to others; lightning pursues the path of least resistance; it burns, dissolves metals, rends bodies asunder, and strikes men blind. Franklin imitated all these effects, striking a pigeon blind, and killing a hen

FIG. 54.



and turkey by the electrical discharge. I place before you in fig. 54, with a view to its comparison with a discharge of forked lightning, the long spark obtained from an effective ebonite machine, furnished with a conductor of a special construction, which favours length of spark.

Having completely satisfied his mind by this comparison of the identity of both agents, Franklin proposed to draw electricity from the clouds by a pointed rod erected on a high tower. But before the tower could be built he succeeded in his object by means of a kite with a pointed wire attached to it. The electricity descended by the hempen string which held the kite, to a key at the end of it, the key being separated from the observer by a silken string held in the hand. Franklin thus obtained sparks, and charged a Leyden^{*} phial with atmospheric electricity.

But, spurred by Franklin's researches, an observer in France had previously proved the electrical character of lightning. A translation of Franklin's writings on

the subject fell into the hands of the naturalist Buffon, who requested his friend D'Alibard to revise the translation. D'Alibard was thus induced to erect an iron rod 40 feet long, supported by silk strings, and ending in a sentry-box. It was watched by an old dragoon named Coiffier, who on the 10th of May, 1752, heard a clap of thunder, and immediately afterwards drew sparks from the end of the iron rod.

The danger of experiments with metal rods was soon illustrated. Professor Richmann of St. Petersburg had a rod raised three or four feet above the tiles of his house. It was connected by a chain with another rod in his room; the latter rod resting in a glass vessel, and being therefore insulated from the earth. On the 6th of August, 1753, a thunder cloud discharged itself against the external rod; the electricity passed downwards along the chain; on reaching the rod below, it was stopped by the glass vessel, darted to Richmann's head, which was about a foot distant, and killed him on the spot. Had a perfect communication existed between the lower rod and the earth, the lightning in this case would have expended itself harmlessly.

In 1749 Franklin proposed lightning conductors. He repeated his recommendation in 1753. He was opposed on two grounds. The Abbé Nollet, and those who thought with him, considered it as impious to ward off heaven's lightnings, as for a child to ward off the chastening rod of its father. Others thought that the conductors would 'invite' the lightning to break upon them. A long discussion was also carried on as to whether the conductors should be blunt or pointed. Wilson advocated blunt conductors against Franklin, Cavendish, and Watson. He so influenced George III.,

hinting that the points were a republican device to injure his Majesty, that the pointed conductors on Buckingham House were changed for others ending in balls. Experience of the most varied kind has justified the employment of pointed conductors. In 1769 St. Paul's Cathedral was first protected.

The most decisive evidence in favour of conductors was obtained from ships; and such evidence was needed, to overcome the obstinate prejudice of seamen. Case after case occurred in which ships unprotected by conductors were singled out from protected ships, and shattered or destroyed by lightning. The conductors were at first made movable, being hoisted on the approach of a thunderstorm; but these were finally abandoned for the fixed lightning conductors devised by the late Sir Snow Harris. The saving of property and life by this obvious outgrowth of electrical research is incalculable.

§ 31. *The Returning Stroke.*

In the year 1779 Charles, Viscount Mahon, afterwards Earl Stanhope, published his 'Principles of Electricity.' On the title-page of the book stands the following remark:—'This treatise comprehends an explanation of an electrical *returning stroke*, by which fatal effects may be produced even at a vast distance from the place where the lightning falls.'


Lord Mahon's experiments, which are models of scientific clearness and precision, will be readily understood by reference to the principles of electric induction, with which you are now so familiar. It need only be noted here that whenever he speaks of a body being

plunged in an 'electrical atmosphere,' he means that the body is exposed to the inductive action of a second electrified body, which latter he supposed to be surrounded by such an atmosphere.

A few extracts from his work will give a clear notion of the nature of his discovery :—

'I placed an insulated metallic cylinder, AB, fig. 55,

FIG. 55. :



within the electrical atmosphere of the prime conductor [PC] when charged, but beyond the striking distance. The distance between the near end A of the insulated metallic body and the side of the prime conductor was 20 inches. The body AB was of brass, of a cylindrical form, 18 inches long by 2 inches in diameter. I then placed another insulated brass body EF, 40 inches

long by about $3\frac{3}{4}$ inches in diameter, with its end E at the distance of about one-tenth of an inch from the end B of the other metallic body AB. I electrified the prime conductor. All the time that it was receiving its *plus* charge of electricity there passed a great number of weak (red or purple) sparks from the end B of the near body AB into the end E of the remote body EF.'

Make clear to your mind the origin of this stream of weak red or purple sparks. It is obviously due to the inductive action of the prime conductor PC upon the body AB. The positive electricity of AB being repelled by the prime conductor, passed as a stream of sparks to EF.

'When the prime conductor, having received its full charge, came suddenly to discharge, with an explosion, its superabundant electricity on a large brass ball L, which was made to communicate with the earth, it always happened that the electrical fluid, which had been gradually expelled from the body AB and driven into the body EF, did suddenly return from the body EF into the body AB, in a strong and bright spark, at the very instant that the explosion took place upon the ball L.


'This I call the electrical *returning stroke*.'

For the two conductors Lord Mahon then substituted his own body and that of another person, both of them standing upon insulating stools. He continues thus:—

'I placed myself upon an insulating stool E (fig. 56), so as to have my right arm A at the distance of about 20 inches from a large prime conductor; another person, standing upon another insulating stool K, brought his right hand B within one-quarter of an inch of my left hand B.

‘When the prime conductor began to receive its plus charge of electricity, we felt the electrical fluid running out of my hand B into his hand F.

FIG. 56.



‘When we separated our hands B and F a little, the electricity passed between us in small sparks, which sparks increased in sharpness the farther we removed our hands B and F asunder, until we had brought them quite out of a striking distance. The intervals of time between these *departing sparks* increased also the more the distance between our hands B and F was increased, as must necessarily be the case.

‘As soon as the prime conductor came suddenly to discharge its electricity upon the ball L, the superabundant electricity which the other person had received from my body did then return from him to me in a sharp spark, which issued from his hand F at the very instant that the explosion of the prime conductor took place upon the ball L.

‘I still continued upon the insulating stool E, and I desired the other person to stand upon the floor. The returning stroke between us was *still stronger* than it had yet been. The reason of it was this:—the other person being no longer insulated, transmitted his superabundant electricity freely into the earth. I consequently became still more negative than before.

‘Now, when the returning stroke came to take place, not only the electricity which had passed from my body into the body of the other person, but also the electricity which had passed from my body into the earth (through the other person), did suddenly return upon me from his hand F to my hand B, at the same instant that the discharge of the prime conductor took place upon the ball L. This caused the returning stroke to be stronger than before.’

Lord Mahon fused metals, and produced strong physiological effects by the return stroke.


In nature disastrous effects may be produced by the return stroke. The earth’s surface, and animals or men upon it, may be powerfully influenced by one end of an electrified cloud. Discharge may occur at the other end, possibly miles away. The restoration of the electric equilibrium by the return shock may be so violent as to cause death.

This was clearly seen and illustrated by Lord Mahon. Fig. 57 is a reduced copy of his illustration. ABC is the electrified cloud, the two ends of which, A and C, come near the earth. The discharge occurs at c. A man at F is killed by the returning stroke, while the people at D, nearer to the place of discharge, but farther from the cloud, are uninjured.

With the view of still further testing your know-

ledge of induction, I have here copied a portion of this admirable essay; but the entire memoir of Lord Mahon

FIG. 57.



would constitute a most useful and interesting lesson in electricity.

For our own instruction we can illustrate the return shock, thus:—Connect one arm of your universal discharger, fig. 49, with a conductor like *c*, fig. 20, and the other arm with the earth. Bring *c* within a few inches of your prime conductor, but not within striking distance; on working the machine a stream of feeble sparks will pass from point to point of the discharger. Let the prime conductor be discharged from time to time by an assistant; at every discharge the returning stroke is announced by a flash between the points of the discharger at *s*. If gun-cotton with a little fulminating powder scattered on it, or a fine silver wire, be introduced between the points of the discharger, the one is exploded and the other deflagrated.

The stream of repelled sparks first seen may be entirely abolished by establishing an *imperfect* connexion between the conductor *c* and the earth: a chain resting upon the dry table on which the conductor stands will do. The chain permits the feebler sparks to pass through it in preference to crossing the space *s*; but the returning stroke is too strong and sudden to find a sufficiently open channel through the table and chain, and on the discharge of the prime conductor the spark is seen.

It was the action of the return shock upon a dead frog's limbs, observed in the laboratory of Professor Galvani, that led to Galvani's experiments on animal electricity; and led further to the discovery, by Volta, of the electricity which bears his name.

§ 32. *The Leyden Battery, its Currents, and some of their Effects.*


In the ordinary Leyden battery described in § 19 all the inner coatings are connected together, and all the outer coatings are also connected together. Such a battery acts as a single large jar of extraordinary dimensions.

Wires are warmed by a moderate electric discharge; by augmenting the charge they are caused to glow; with a strengthened charge the metal is torn to pieces; fusion follows; and by still stronger charges the wires are reduced to metallic dust and vapour.

• For such experiments the wire must be thin. Without resistance we can have no heat, and when the wire is thick we have little resistance. The mechanism of the discharge, as shown by the figures produced, is

different in different wires. The figure produced by the dust of a deflagrated silver wire on white paper is shown in fig. 58.

FIG. 58.



When the discharge of a powerful battery is sent through a long steel chain with the ends of its links unsoldered, the sparks between the unsoldered links carry the incandescent particles of the steel along with them. These are consumed in the air, a momentary blaze occurring along the entire chain. Chain cables have been fused by being made the channels of a flash of lightning.

Retaining our conception of an electric fluid, at this point we naturally add to it the conception of a *current*. It is the electric current which produces the effects just described. In many of our former experiments we had electricity at rest (static electricity), here we have electricity in motion (dynamic electricity).

Sending the current from a battery through a flat spiral (the primary) formed of fifty or sixty feet of copper wire, and placing within a little distance of it a second similar spiral (the secondary) with its ends connected; the passage of the current in the first spiral excites in the second a current, which is competent to deflagrate wires, and to produce all the other effects of the electrical discharge. Even when the spirals are

some feet asunder, the shock produced by the secondary current is still manifest.

The current from the secondary spiral may be carried round a third; and this third spiral may be allowed to act upon a fourth, exactly as the primary did upon the secondary. A tertiary current is thus evoked by the secondary in the fourth spiral.

Carrying this tertiary current round a fifth spiral, and causing it to act inductively upon a sixth, we obtain in the latter a current of the fourth order. In this way we generate a long progeny of currents, all of them having the current sent from the battery through the first spiral, for a common progenitor. To Prof. Henry of the United States, and to Prof. Riess of Berlin, we are indebted for the investigation of the laws of these currents. These researches, however, were subsequent to, and were indeed suggested by, experiments of a similar character previously made by Faraday with Voltaic electricity.

Besides the electricity of friction and induction we have the following sources and forms of this power.

The contact of dissimilar metals produces electricity.

The contact of metals with liquids produces electricity.

A mere variation of the character of the contact of two bodies produces electricity.

Chemical action produces a continuous flow of electricity (Voltaic electricity).

Heat, suitably applied to dissimilar metals, produces a continuous flow of electricity (thermo-electricity).

The heating and cooling of certain crystals produce electricity (pyro-electricity).

The motion of magnets, and of bodies carrying electric currents, produces electricity (magneto-electricity).

The friction of sand against a metal plate produces electricity.

The friction of condensed water-particles against a safety valve, or better still against a box-wood nozzle through which steam is driven, produces electricity (Armstrong's hydro-electric machine).

These are different manifestations of one and the same power; and they are all evoked by an equivalent expenditure of some other power.

Conclusion.

Our experimental researches end here. I would now bespeak your attention for five minutes longer. The expensiveness of apparatus is sometimes urged as an obstacle to the introduction of science into schools. I hope it has been shown that the obstacle is not a real one. Leaving out of account the few larger experiments, which have contributed but little to our knowledge, it is manifest that the wise expenditure of a couple of guineas would enable any competent teacher to place the leading facts and principles of frictional electricity completely at the command of his pupils; giving them thereby precious knowledge, and still more precious intellectual discipline—a discipline which invokes observation, reflection, prevision by the exercise of reason, and experimental verification.

And here, if I might venture to do so, I would urge upon the science teachers of our public and other schools that the immediate future of science as a factor in English education depends mainly upon them. I would respect-

fully submit to them whether it would not be a mistake to direct their attention at present to the collection of costly apparatus. Their principal function just now is to arouse a love for scientific study. This is best done by the exhibition of the needful facts and principles with the simplest possible appliances, and by bringing their pupils into contact with actual experimental work.

The very time and thought spent in devising such simple instruments will give the teacher himself a grasp and mastery of his subject which he could not otherwise obtain; but it ought to be known by the head masters of our schools that time is needed, not only for devising such instruments, but also for preparing the experiments to be made with them after they have been devised. No science teacher is fit to meet his class without this distinct and special preparation before every lesson. His experiments are part and parcel of his language, and they ought to be as strict in logic, and as free from stammering, as his spoken words. To make them so may imply an expenditure of time which few head masters now contemplate, but it is a necessary expenditure, and they will act wisely in making provision for it.

To them, moreover, in words of friendly warning, I would say, make room for science by your own healthy and spontaneous action, and do not wait until it is forced upon you by revolutionary pressure from without. The condition of things now existing cannot continue. Its simple statement suffices to call down upon it the condemnation of every thoughtful mind. With reference to the report of a Commission appointed last year to enquire into the scientific instruction of this country, Sir John Lubbock writes as follows:—‘The Commis-

sioners have published returns from more than a hundred and twenty of the larger endowed schools. In more than half of these no science whatever is taught; only thirteen have a laboratory, and only eighteen possess any scientific apparatus. Out of the whole number, less than twenty schools devote as much as four hours a week to science, and only thirteen attach any weight at all to scientific subjects in the examinations.' •

Well may the Commissioners pronounce such a state of things to be nothing less than a national calamity! If persisted in, it will assuredly be followed by a reaction which the truest friends of classical culture in England will have the greatest reason to deplore.

PRICE LIST OF APPARATUS.

	£	s.	d.
1. A horizontally supported rail, with wire cradle and silk ribbon for suspending excited rods and light bodies	0	3	0
2. A wooden balancing lath and support	0	1	0
3. A delicate straw index on an insulated balancing-point on stand	0	0	9
4. Two sticks of sealing-wax	0	0	8
5. Two sticks of gutta-percha	0	6	0
6. Two small glass tubes	0	2	6
7. One large tube	0	3	0
8. One rubber of flannel	0	0	6
9. One rubber of silk	0	2	0
10. Box of amalgam	0	0	6
11. Ebonite comb	0	1	0
12. Foolscap paper	0	0	1
13. Mahogany board	0	2	6
14. Piece of india-rubber	0	0	6
15. Watch-glass for Florentine experiment (with oil)	0	0	2
16. Roughened glass tube	0	4	0
17. Straw electroscope	0	2	3
18. Dutch metal electroscope	0	2	6

Apparatus for Conduction, Insulation, and Induction.

19. Long cylindrical conductor	0	2	6
20. Cork and rod for insertion into glass tube	0	0	2
21. Box containing fragments of paper for attraction	0	0	2
22. Book of Dutch metal for attraction	0	0	4
23. Long length of copper wire	0	0	3
24. Silk thread for suspending copper wire	0	0	3
25. Long straw index and stand	0	2	0
26. Metal table on insulating stand	0	1	3
27. A length of packthread	0	0	1
28. A fox's brush	0	2	6
29. A brass tube to fit over end of gutta-percha tube	0	0	9
30. Two metal balls and insulated supports	0	5	0
31. Electric Carrier	0	0	6
32. Length of Chain	0	0	6

The Electrophorus.

33. Circular metal plate, with ball and insulated handle attached; and sheet of vulcanised rubber	0	5	6
---	---	---	---

Illustration of the Action of Points.

34. An electric machine	1	1	0
35. A conical metal conductor	0	2	6

Price List of Apparatus.

	£	s	d.
36. Number of needles	0	0	2
37. Reel of fine wire for connecting conductor with machine	0	0	3
38. Point or wire fitting into pipe conductor of machine for the action of electric wind on candle-flame	0	0	6
39. Electric Mill	0	1	0
40. Paper tassel and wire	0	0	6
41. Book of silver leaf	0	1	6

The Leyden Jar.

42. First form of Leyden jar	0	0	9
43. An ordinary Leyden jar	0	4	0
44. Bevis's plate	0	1	0
45. Insulated discharger with metal knobs	0	0	8
46. Two sheets of tin with silk holders	0	1	0
47. Glass plate for ditto with silk holders	0	1	0
48. Leyden jar with moveable coatings	0	2	6

Ignition by Electric Spark, etc.

49. Cottrell's rubber	0	2	6
50. An insulated brass ball	0	1	0
51. An Argand burner and flexible tubing	0	3	0
52. An iron spoon for igniting bisulphide of carbon, ether, etc.	0	0	2

Duration of Electric Spark.

53. A rotating disc with black and white sectors	0	2	6
54. Spark apparatus for connection with Leyden jar	0	2	6
55. Vacuum tube (electric light in vacuo)	0	2	6

Lichtenberg's Figures.

56. A resin cake	0	1	6
57. Bottle containing a mixture of flowers of sulphur and red lead; muslin gauze for dusting powder on resin surface	0	0	6
58. Box and packing	0	8	0

This apparatus is supplied by MR. STANLEY, of 18 RAILWAY APPROACH, LONDON BRIDGE. The instruments may be had singly or collectively in a box; each box being guaranteed by the signature of MR. COTTRELL. Price of the whole collection, box included, 5l. 10s.

JULY 1876.

GENERAL LIST OF WORKS

PUBLISHED BY

MESSRS. LONGMANS, GREEN, AND CO.

PATERNOSTER ROW, LONDON.



History, Politics, Historical Memoirs, &c.

The HISTORY of ENGLAND from the Accession of James the Second.
By LORD MACAULAY.

STUDENT'S EDITION, 2 vols. crown 8vo. 12s.

PEOPLE'S EDITION, 4 vols. crown 8vo. 16s.

CABINET EDITION, 8 vols. post 8vo. 48s.

LIBRARY EDITION, 5 vols. 8vo. £4.

LORD MACAULAY'S WORKS. Complete and Uniform Library Edition. Edited by his Sister, Lady TREVELYAN. 8 vols. 8vo. with Portrait price £5. 5s. cloth, or £8. 8s. bound in tree-calf by Rivière.

The HISTORY of ENGLAND from the Fall of Wolsey to the Defeat of the Spanish Armada. By JAMES ANTHONY FROUDE, M.A. late Fellow of Exeter College, Oxford.

LIBRARY EDITION, Twelve Volumes, 8vo. price £8. 18s.

CABINET EDITION, Twelve Volumes, crown 8vo. price 72s.

The ENGLISH in IRELAND in the EIGHTEENTH CENTURY.
By JAMES ANTHONY FROUDE, M.A. late Fellow of Exeter College, Oxford. 3 vols. 8vo. price 48s.

JOURNAL of the REIGNS of KING GEORGE IV. and KING WILLIAM IV. By the late CHARLES C. F. GREVILLE, Esq. Edited by HENRY REEVE, Esq. Fifth Edition. 3 vols. 8vo. 36s.

RECOLLECTIONS and SUGGESTIONS, 1813-1873. By JOHN EARL RUSSELL, K.G. New Edition, revised and enlarged. 8vo. 16s.

On PARLIAMENTARY GOVERNMENT in ENGLAND; its Origin, Development, and Practical Operation. By ALPHEUS TODD, Librarian of the Legislative Assembly of Canada. 2 vols. 8vo. price £1. 17s.

The CONSTITUTIONAL HISTORY of ENGLAND, since the Accession of George III. 1760-1860. By SIR THOMAS ERSKINE MAY, K.C.B. D.C.L. The Fifth Edition, thoroughly revised. 8 vols. crown 8vo. price 18s.

DEMOCRACY in EUROPE; a History. By SIR THOMAS ERSKINE MAY, K.C.B. D.C.L. 2 vols. 8vo. *In the press.*

The NEW REFORMATION, a Narrative of the Old Catholic Movement, from 1870 to the Present Time; with an Historical Introduction. By THEODORUS. 8vo. price 12s.

The OXFORD REFORMERS—John Colet, Erasmus, and Thomas More; being a History of their Fellow-work. By FREDERIC SEEHOHM. Second Edition, enlarged. 8vo. 14s.

LECTURES on the HISTORY of ENGLAND, from the Earliest Times to the Death of King Edward II. By WILLIAM LONGMAN, F.S.A. With Maps and Illustrations. 8vo. 15s.

The HISTORY of the LIFE and TIMES of EDWARD the THIRD. By WILLIAM LONGMAN, F.S.A. With 9 Maps, 8 Plates, and 16 Woodcuts. 2 vols. 8vo. 28s.

INTRODUCTORY LECTURES on MODERN HISTORY. Delivered in Lent Term, 1842; with the Inaugural Lecture delivered in December 1841. By the Rev. THOMAS ARNOLD, D.D. 8vo. price 7s. 6d.

WATERLOO LECTURES; a Study of the Campaign of 1815. By Colonel CHARLES C. CHENEY, R.E. Third Edition. 8vo. with Map, 10s. 6d.

HISTORY of ENGLAND under the DUKE of BUCKINGHAM and CHARLES the FIRST, 1624-1628. By SAMUEL RAWSON GARDINER, late Student of Ch. Ch. 2 vols. 8vo. with two Maps, price 24s.

The SIXTH ORIENTAL MONARCHY; or, the Geography, History, and Antiquities of PARTHIA. By GEORGE RAWLINSON, M.A. Professor of Ancient History in the University of Oxford. Maps and Illustrations. 8vo. 16s.

The SEVENTH GREAT ORIENTAL MONARCHY; or, a History of the SASSANIANS; with Notices, Geographical and Antiquarian. By G. RAWLINSON, M.A. Map and numerous Illustrations. 8vo. price 28s.

A HISTORY of GREECE. By the Rev. GEORGE W. COX, M.A. late Scholar of Trinity College, Oxford. VOLS. I. & II. (to the Close of the Peloponnesian War). 8vo. with Maps and Plans, 36s.

GENERAL HISTORY of GREECE to the Death of Alexander the Great; with a Sketch of the Subsequent History to the Present Time. By the Rev. GEORGE W. COX, M.A. With 11 Maps. Crown 8vo. 7s. 6d.

The GREEKS and the PERSIANS. By the Rev. GEORGE W. COX, M.A. (*Epochs of Ancient History, I.*) With 4 Coloured Maps. Fcp. 8vo. price 2s. 6d.

The TALE of the GREAT PERSIAN WAR, from the Histories of Herodotus. By GEORGE W. COX, M.A. New Edition. Fcp. 3s. 6d.

The 'HISTORY of ROME. By WILLIAM IHNE. VOLS. I. and II. 8vo. price 30s. The Third Volume is in the press.

GENERAL HISTORY OF ROME from the Foundation of the City to the Fall of Augustulus, B.C. 753—A.D. 476. By the Very Rev. C. MERRIVALE, D.D. Dean of Ely. With Five Maps. Crown 8vo. 7s. 6d.

HISTORY of the ROMANS under the EMPIRE. By the Very Rev. C. MERRIVALE, D.D. Dean of Ely. 8 vols. post 8vo. 48s.

The FALL of the ROMAN REPUBLIC; a Short History of the Last Century of the Commonwealth. By the same Author. 12mo. 7s. 6d.

The STUDENT'S MANUAL of the HISTORY of INDIA, from the Earliest Period to the Present. By Colonel MEADOWS TAYLOR, M.R.A.S. M.R.I.A. Second Thousand. Crown 8vo. with Maps, 7s. 6d.

The HISTORY of INDIA, from the Earliest Period to the close of Lord Dalhousie's Administration. By J. C. MARSHMAN. 3 vols. crown 8vo. 22s. 6d.

THE NATIVE STATES OF INDIA IN SUBSIDIARY ALLIANCE with the **BRITISH GOVERNMENT**; an Historical Sketch. By Colonel G. B. MALLISON, C.S.I. With 6 Coloured Maps. 8vo. 15s.

INDIAN POLITY; a View of the System of Administration in India. By Lieutenant-Colonel GEORGE CHESNEY, Fellow of the University of Calcutta. New Edition, revised; with Map. 8vo. price 21s.

THE BRITISH ARMY in 1875; with Suggestions on its Administration and Organisation. By JOHN HOLMS, M.P. New and Enlarged Edition, with 4 Diagrams. Crown 8vo. price 4s. 6d.

THE HISTORY OF PRUSSIA, from the Earliest Times to the Present Day; tracing the Origin and Development of her Military Organisation. By Captain W. J. WYATT. Vols. I. and II. A.D. 900 to A.D. 1825. 8vo. 36s.

POPULAR HISTORY OF FRANCE, from the Earliest Times to the Death of Louis XIV. By ELIZABETH M. SEWELL, Author of 'Amy Herbert' &c. With Coloured Maps. Crown 8vo. 7s. 6d.

STUDIES from GENOESE HISTORY. By Colonel G. B. MALLISON, C.S.I. Guardian to His Highness the Maharaja of Mysore. Crown 8vo. 10s. 6d.

LORD MACAULAY'S CRITICAL and HISTORICAL ESSAYS. CHEAP EDITION, authorised and complete. Crown 8vo. 3s. 6d.

CABINET EDITION, 4 vols. post 8vo. 24s.

LIBRARY EDITION, 3 vols. 8vo. 36s.

PEOPLE'S EDITION, 2 vols. crown 8vo. 8s.

STUDENT'S EDITION, 1 vol. cr. 8vo. 6s.

HISTORY OF EUROPEAN MORALS, from Augustus to Charlemagne. By W. E. H. LECKY, M.A. Second Edition. 2 vols. 8vo. price 28s.

HISTORY of the RISE and INFLUENCE of the SPIRIT of RATIONALISM in EUROPE. By W. E. H. LECKY, M.A. Cabinet Edition, being the Fourth. 2 vols. crown 8vo. price 16s.

THE HISTORY of PHILOSOPHY, from Thales to Comte. By GEORGE HENRY LEWES. Fourth Edition. 2 vols. 8vo. 32s.

THE HISTORY of the PELOPONNESIAN WAR. By THUCYDIDES. Translated by R. CRAWLEY, Fellow of Worcester College, Oxford. 8vo. 10s. 6d.

THE MYTHOLOGY of the ARYAN NATIONS. By GEORGE W. COX, M.A. late Scholar of Trinity College, Oxford. 2 vols. 8vo. 28s.

TALES of ANCIENT GREECE. By GEORGE W. COX, M.A. late Scholar of Trin. Coll. Oxon. Crown 8vo. price 6s. 6d.

HISTORY of CIVILISATION in England and France, Spain and Scotland. By HENRY THOMAS BUCKLE. New Edition of the entire Work, with a complete INDEX. 3 vols. crown 8vo. 24s.

SKETCH of the HISTORY of the CHURCH of ENGLAND to the Revolution of 1688. By the Right Rev. T. V. SHORT, D.D. Lord Bishop of St. Asaph. Eighth Edition. Crown 8vo. 7s. 6d.

MAUNDER'S HISTORICAL TREASURY; General Introductory Outlines of Universal History, and a series of Separate Histories. Latest Edition, revised by the Rev. G. W. COX, M.A. Fcp. 8vo. 6s. cloth, or 16s. 6d. calf.

CATES' and WOODWARD'S ENCYCLOPEDIA of CHRONOLOGY, HISTORICAL and BIOGRAPHICAL. 8vo. price 42s.

THE ERA of the PROTESTANT REVOLUTION. By F. SEEBOHM. With 4 Coloured Maps and 12 Diagrams on Wood. Fcp. 8vo. 2s. 6d.

- The CRUSADES.** By the Rev. G. W. COX, M.A. late Scholar of Trinity College, Oxford. With Coloured Map. Fcp. 8vo. 2s. 6d.
- The THIRTY YEARS' WAR, 1618-1648.** By SAMUEL RAWSON GARDINER, late Student of Christ Church. With Coloured Map. Fcp. 8vo. 2s. 6d.
- The HOUSES of LANCASTER and YORK;** with the Conquest and Loss of France. By JAMES GAIRDNER, of the Public Record Office. With Five Coloured Maps. Fcp. 8vo. 2s. 6d.
- EDWARD the THIRD.** By the Rev. W. WARBURTON, M.A. late Fellow of All Souls College, Oxford. With 3 Coloured Maps and 8 Genealogical Tables. Fcp. 8vo. 2s. 6d.
- The AGE of ELIZABETH.** By the Rev. M. CREIGHTON, M.A. late Fellow and Tutor of Merton College, Oxford. With 5 Maps and 4 Genealogical Tables. Fcp. 8vo. 2s. 6d.
- The FALL of the STUARTS;** and Western Europe from 1678 to 1697. By the Rev. E. HALE, M.A. Assistant-Master, Eton. With 11 Maps and Plans. Fcp. 8vo. 2s. 6d.
- The FIRST TWO STUARTS and the PURITAN REVOLUTION, 1603-1660.** By SAMUEL RAWSON GARDINER, late Student of Christ Church. With 4 Coloured Maps. Fcp. 8vo. 2s. 6d.
- The WAR of AMERICAN INDEPENDENCE, 1775-1783.** By JOHN MALCOLM LUDLOW, Barrister-at-Law. With 4 Coloured Maps. Fcp. 8vo. 2s. 6d.
- REALITIES of IRISH LIFE.** By W. STEUART TRENCH, late Land Agent in Ireland to the Marquess of Lansdowne, the Marquess of Bath, and Lord Digby. Cheaper Edition. Crown 8vo. price 2s. 6d.

Biographical Works.

- The LIFE and LETTERS of LORD MACAULAY.** By his Nephew, G. OTTO TREVELYAN, M.P. 2 vols. 8vo. with Portrait, price 36s.
- The LIFE of SIR WILLIAM FAIRBAIRN, Bart. F.R.S.** Corresponding Member of the National Institute of France, &c. Partly written by himself; edited and completed by WILLIAM POLE, F.R.S. [*In the Press.*]
- ARTHUR SCHOPENHAUER, his LIFE and his PHILOSOPHY.** By HELEN ZIMMERN. Post 8vo. with Portrait, 7s. 6d.
- MÉMOIRES of BARON STOCKMAR.** By his SON, Baron E. VON STOCKMAR. Translated from the German by G. A. M. Edited by F. MAX MÜLLER, M.A. 2 vols. crown 8vo. 21s.
- AUTOBIOGRAPHY.** By JOHN STUART MILL. 8vo. price 7s. 6d.
- The LIFE of NAPOLEON III.** derived from State Records, Unpublished Family Correspondence, and Personal Testimony. By BLANCHARD JERROLD. 4 vols. 8vo. with numerous Portraits and Facsimiles. Vols. I. and II. price 18s. each. The Third Volume is in the press.
- LIFE and LETTERS of Sir GILBERT ELLIOT, First EARL of MINTO.** Edited by the COUNTESS of MINTO. 3 vols. 8vo. 31s. 6d.
- ESSAYS in MODERN MILITARY BIOGRAPHY.** By CHARLES CORNWALLIS CHESNEY, Lieutenant-Colonel in the Royal Engineers. 8vo. 12s. 6d.
- The MÉMOIRES of SIR JOHN RERESBY,** of Thrybergh, Bart. M.P. for York, &c. 1634-1689. Written by Himself. Edited from the Original Manuscript by JAMES J. CARTWRIGHT, M.A. 8vo. price 21s.

ISAAC CASAUBON, 1559-1614. By MARK PATTISON, Rector of Lincoln College, Oxford. 8vo. 18s.

LORD, GEORGE BENTINCK; a Political Biography. By the Right Hon. BENJAMIN DISRAELI, M.P. Crown 8vo. price 6s.

LEADERS of PUBLIC OPINION in IRELAND; Swift, Flood, Grattan, and O'Connell. By W. E. H. LECKY, M.A. New Edition, revised and enlarged. Crown 8vo. price 7s. 6d.

DICTIONARY of GENERAL BIOGRAPHY; containing Concise Memoirs and Notices of the most Eminent Persons of all Countries, from the Earliest Ages. By W. L. R. CATES. New Edition, extended in a Supplement to the Year 1875. Medium 8vo. price 25s.

LIFE of the DUKE of WELLINGTON. By the Rev. G. R. GLEIG, M.A. Popular Edition, carefully revised; with copious Additions. Crown 8vo. with Portrait, 5s.

MEMOIRS of SIR HENRY HAVELOCK, K.C.B. By JOHN CLARK MARSHMAN. Cabinet Edition, with Portrait. Crown 8vo. price 3s. 8d.

VICISSITUDES of FAMILIES. By Sir J. BERNARD BURKE, C.B. Ulster King of Arms. New Edition, enlarged. 2 vols. crown 8vo. 21s.

The RISE of GREAT FAMILIES, other Essays and Stories. By Sir J. BERNARD BURKE, C.B. Ulster King of Arms. Crown 8vo. price 12s. 6d.

ESSAYS in ECCLESIASTICAL BIOGRAPHY. By the Right Hon. Sir J. STEPHEN, LL.D. Cabinet Edition. Crown 8vo. 7s. 6d.

MAUNDER'S BIOGRAPHICAL TREASURY. Latest Edition, reconstructed, thoroughly revised, and in great part rewritten; with 1,000 additional Memoirs and Notices, by W. L. R. CATES. Fcp. 8vo. 6s. cloth; 10s. 6d. calf.

LETTERS and LIFE of FRANCIS BACON, including all his Occasional Works. Collected and edited, with a Commentary, by J. SPEDDING, Trin. Coll. Cantab. Complete in 7 vols. 8vo. £4. 4s.

The LIFE, WORKS, and OPINIONS of HEINRICH HEINE. By WILLIAM STIGAND. 2 vols. 8vo. with Portrait of Heine, price 28s.

BIOGRAPHICAL and CRITICAL ESSAYS, reprinted from Reviews, with Additions and Corrections. Second Edition of the Second Series. By A. HAYWARD, Q.C. 2 vols. 8vo. price 28s. THIRD SERIES, in 1 vol. 8vo. price 14s.

Criticism, Philosophy, Polity, &c.

The LAW of NATIONS considered as **INDEPENDENT POLITICAL COMMUNITIES;** the Rights and Duties of Nations in Time of War. By Sir TRAVERS TWISS, D.C.L., F.R.S. New Edition, revised; with an Introductory Juridical Review of the Results of Recent Wars, and an Appendix of Treaties and other Documents. 8vo. 21s.

CHURCH and STATE: their relations Historically Developed. By T. HEINRICH GEFFCKEN, Professor of International Law at the University of Strasburg. Translated from the German by E. FAIRFAX TAYLOR. *In the press.*

A SYSTEMATIC VIEW of the SCIENCE of JURISPRUDENCE. By SHELDON AMOS, M.A. Professor of Jurisprudence to the Inns of Court, London. 8vo. price 18s.

A PRIMER of the ENGLISH CONSTITUTION and GOVERNMENT.

By SHELDON AMOS, M.A. Professor of Jurisprudence to the Inns of Court.
Second Edition, revised. Crown 8vo. 6s.

OUTLINES of CIVIL PROCEDURE. Being a General View of the Supreme Court of Judicature and of the whole Practice in the Common Law and Chancery Divisions under all the Statutes now in force. By EDWARD STANLEY ROSCOE, Barrister-at-Law. 12mo. price 3s. 6d.**The INSTITUTES of JUSTINIAN;** with English Introduction, Translation and Notes. By T. C. SANDARS, M.A. Sixth Edition. 8vo. 18s.**SOCRATES and the SOCRATIC SCHOOLS.** Translated from the German of Dr. E. ZELLER, with the Author's approval, by the Rev. OSWALD J. REICHEL, M.A. Crown 8vo. 8s. 6d.**The STOICS, EPICUREANS, and SCEPTICS.** Translated from the German of Dr. E. ZELLER, with the Author's approval, by OSWALD J. REICHEL, M.A. Crown 8vo. price 14s.**PLATO and the OLDER ACADEMY.** Translated from the German of Dr. EDUARD ZELLER by S. FRANCES ADLEYNE and ALFRED GOODWIN, B.A. Fellow of Balliol College, Oxford. Crown 8vo. 18s.**The ETHICS of ARISTOTLE,** with Essays and Notes. By Sir A. GRANT, Bart. M.A. LL.D. Third Edition. 2 vols. 8vo. 32s.**The POLITICS of ARISTOTLE;** Greek Text, with English Notes. By RICHARD CONGREVE, M.A. New Edition, revised. 8vo. 18s.**The NICOMACHEAN ETHICS of ARISTOTLE** newly translated into English. By R. WILLIAMS, B.A. Fellow and late Lecturer of Merton College, and sometime Student of Christ Church, Oxford. New Edition. 8vo. 7s. 6d.**PICTURE LOGIC;** an Attempt to Popularise the Science of Reasoning by the combination of Humorous Pictures with Examples of Reasoning taken from Daily Life. By A. SWINBOURNE, B.A. With Woodcut Illustrations from Drawings by the Author. Second Edition. Fcp. 8vo. price 5s.**ELEMENTS of LOGIC.** By R. WHATLEY, D.D. late Archbishop of Dublin. New Edition. 8vo. 10s. 6d. crown 8vo. 4s. 6d.**Elements of Rhetoric.** By the same Author. New Edition. 8vo. 10s. 6d. crown 8vo. 4s. 6d.**English Synonyms.** By E. JANE WHATLEY. Edited by Archbishop WHATLEY. Fifth Edition. Fcp. 8vo. price 3s.**On the INFLUENCE of AUTHORITY in MATTERS of OPINION.** By the late Sir GEORGE CORNEWALL LEWIS, Bart. New Edition. 8vo. 14s.**COMTE'S SYSTEM of POSITIVE POLITY, or TREATISE upon SOCIOLOGY.** Translated from the Paris Edition of 1851-1854, and furnished with Analytical Tables of Contents. In Four Volumes, 8vo. each forming in some degree an independent Treatise:—

VOL. I. General View of Positivism and its Introductory Principles. Translated by J. H. BRIDGES, M.B. Price 21s.

VOL. II. Social Statics, or the Abstract Laws of Human Order. Translated by F. HARRISON, M.A. Price 14s.

VOL. III. Social Dynamics, or the General Laws of Human Progress (the Philosophy of History). Translated by Professor E. S. BEESLY, M.A. 8vo. 21s.

VOL. IV. Synthesis of the Future of Mankind. Translated by R. CONGREVE, M.D.; and an Appendix, containing the Author's Minor Treatises, translated by H. D. HUTTON, M.A. [In the press.]

DEMOCRACY in AMERICA. By ALEXIS DE TOCQUEVILLE. Translated by HENRY REEVE, Esq. New Edition. 2 vols. crown 8vo. 16s.

ORDER and PROGRESS: Part I. Thoughts on Government; Part II. Studies of Political Crises. By FREDERIC HARRISON, M.A. of Lincoln's Inn. 8vo. price 14s.

BACON'S ESSAYS with ANNOTATIONS. By R. WHATELY, D.D. late Archbishop of Dublin. New Edition, 8vo. price 10s. 6d.

LORD BACON'S WORKS, collected and edited by J. SPEDDING, M.A. R. L. ELLIS, M.A. and D. D. HEATH. 7 vols. 8vo. price £3. 13s. 6d.

On REPRESENTATIVE GOVERNMENT. By JOHN STUART MILL. Crown 8vo. price 2s.

On LIBERTY. By JOHN STUART MILL. New Edition. Post 8vo. 7s. 6d. Crown 8vo. price 1s. 4d.

PRINCIPLES of POLITICAL ECONOMY. By JOHN STUART MILL. Seventh Edition. 2 vols. 8vo. 30s. Or in 1 vol. crown 8vo. price 5s.

ESSAYS on SOME UNSETTLED QUESTIONS of POLITICAL ECONOMY. By JOHN STUART MILL. Second Edition. 8vo. 6s. 6d.

UTILITARIANISM. By JOHN STUART MILL. New Edition. 8vo. 5s.

DISSERTATIONS and DISCUSSIONS: Political, Philosophical, and Historical. By JOHN STUART MILL. New Editions. 4 vols. 8vo. price £2. 6s. 6d.

EXAMINATION of Sir. W. HAMILTON'S PHILOSOPHY, and of the Principal Philosophical Questions discussed in his Writings. By JOHN STUART MILL. Fourth Edition. 8vo. 16s.

An OUTLINE of the NECESSARY LAWS of THOUGHT; a Treatise on Pure and Applied Logic. By the Most Rev. W. THOMSON, Lord Archbishop of York, D.D. F.R.S. New Edition. Crown 8vo. price 6s.

PRINCIPLES of ECONOMICAL PHILOSOPHY. By HENRY DUNNING MACLEOD, M.A. Barrister-at-Law. Second Edition. In Two Volumes. VOL. I. 8vo. price 15s. VOL. II. PART I. price 12s. VOL. II. PART II. *just ready.*

A SYSTEM of LOGIC, RATIOCINATIVE and INDUCTIVE. By JOHN STUART MILL. Ninth Edition. Two vols. 8vo. 25s.

SPEECHES of the RIGHT HON. LORD MACAULAY, corrected by Himself. People's Edition, crown 8vo. 3s. 6d.

The ORATION of DEMOSTHENES on the CROWN. Translated by the Right Hon. Sir R. P. COLLIER. Crown 8vo. price 5s.

FAMILIES of SPEECH: Four Lectures delivered before the Royal Institution of Great Britain. By the Rev. F. W. FARRAR, D.D. F.R.S. New Edition. Crown 8vo. 3s. 6d.

CHAPTERS on LANGUAGE. By the Rev. F. W. FARRAR, D.D. F.R.S. New Edition. Crown 8vo. 5s.

HANDBOOK of the ENGLISH LANGUAGE. For the use of Students of the Universities and the Higher Classes in Schools. By R. G. LATHAM, M.A. M.D. The Ninth Edition. Crown 8vo. price 6s.

DICTIONARY of the ENGLISH LANGUAGE. By R. G. LATHAM, M.A. M.D. Abridged from Dr. Latham's Edition of Johnson's English Dictionary, and condensed into One Volume. Medium 8vo. price 2s.

A DICTIONARY of the ENGLISH LANGUAGE. By R. G. LATHAM, M.A. M.D. Founded on the Dictionary of Dr. SAMUEL JOHNSON, as edited by the Rev. H. J. TODD, with numerous Emendations and Additions. In Four Volumes, 4to. price £7.

THESAURUS of ENGLISH WORDS and PHRASES, classified and arranged so as to facilitate the Expression of Ideas, and assist in Literary Composition. By P. M. ROGER, M.D. New Edition. Crown 8vo. 10s. 6d.

LECTURES on the SCIENCE of LANGUAGE. By F. MAX MÜLLER, M.A. &c. The Eighth Edition. 2 vols. crown 8vo. 16s.

MANUAL of ENGLISH LITERATURE, Historical and Critical. By THOMAS ARNOLD, M.A. New Edition. Crown 8vo. 7s. 6d.

SOUTHEY'S DOCTOR, complete in One Volume. Edited by the Rev. J. W. WARTER, B.D. Square crown 8vo. 12s. 6d.

HISTORICAL and CRITICAL COMMENTARY on the OLD TESTAMENT; with a New Translation. By M. M. KALISCH, Ph.D. VOL. I. *Genesis*, 8vo. 18s. or adapted for the General Reader, 12s. VOL. II. *Ezodus*, 15s. or adapted for the General Reader, 12s. VOL. III. *Leviticus*, PART I. 15s. or adapted for the General Reader, 8s. VOL. IV. *Leviticus*, PART II. 15s. or adapted for the General Reader, 8s.

A DICTIONARY of ROMAN and GREEK ANTIQUITIES, with about Two Thousand Engravings on Wood from Ancient Originals, illustrative of the Industrial Arts and Social Life of the Greeks and Romans. By A. RICH, B.A. Third Edition, revised and improved. Crown 8vo. price 7s. 6d.

A LATIN-ENGLISH DICTIONARY. By JOHN T. WHITE, D.D. Oxon. and J. E. RIDDLE, M.A. Oxon. Fifth Edition. 1 vol. 4to. 28s.

WHITE'S COLLEGE LATIN-ENGLISH DICTIONARY (Intermediate Size), abridged for the use of University Students from the Parent Work (as above). Medium 8vo. Third Edition, 15s.

WHITE'S JUNIOR STUDENT'S COMPLETE LATIN-ENGLISH and ENGLISH-LATIN DICTIONARY. New Edition. Square 12mo. price 12s.

Separately { The ENGLISH-LATIN DICTIONARY, price 5s. 6d.
The LATIN-ENGLISH DICTIONARY, price 7s. 6d.

A LATIN-ENGLISH DICTIONARY, adapted for the Use of Middle-Class Schools. By JOHN T. WHITE, D.D. Oxon. Square fcp. 8vo. price 3s.

An ENGLISH-GREEK LEXICON, containing all the Greek Words used by Writers of good authority. By C. D. YONGE, M.A. 4to. price 21s.

Mr. YONGE'S NEW LEXICON, English and Greek, abridged from his larger work (as above). Revised Edition. Square 12mo. price 8s. 6d.

A GREEK-ENGLISH LEXICON. Compiled by H. G. LIDDELL, D.D. Dean of Christ Church, and R. SCOTT, D.D. Dean of Rochester. Sixth Edition. Crown 4to. price 36s.

A LEXICON, GREEK and ENGLISH, abridged from LIDDELL and SCOTT'S *Greek-English Lexicon*. Fourteenth Edition. Square 12mo. 7s. 6d.

A PRACTICAL DICTIONARY of the FRENCH and ENGLISH LANGUAGES. By L. CONTANSEAU. Revised Edition. Post 8vo. 7s. 6d.

CONTANSEAU'S POCKET DICTIONARY, French and English, abridged from the above by the Author. New Edition. Square 18mo. 3s. 6d.

A NEW POCKET DICTIONARY of the GERMAN and ENGLISH LANGUAGES. By F. W. LONGMAN, Balliol College, Oxford. 18mo. 5s.

NEW PRACTICAL DICTIONARY of the GERMAN LANGUAGE; German-English and English-German. By the Rev. W. L. BLACKLEY, M.A. and Dr. CARL MARTIN FRIEDLÄNDER. Post 8vo. 7s. 6d.

The MASTERY of LANGUAGES; or, the Art of Speaking Foreign Tongues Idiomatically. By THOMAS PRENDERGAST. 8vo. 6s.

Miscellaneous Works and Popular Metaphysics.

LECTURES delivered in AMERICA in 1874. By CHARLES KINGSLEY, F.L.S. F.G.S, late Rector of Eversley. Crown 8vo. price 5s.

GERMAN HOME LIFE. Reprinted, with Revision and Additions, from *Fraser's Magazine*. Crown 8vo. 6s.

THE MISCELLANEOUS WORKS of THOMAS ARNOLD, D.D. Late Head Master of Rugby School and Regius Professor of Modern History in the University of Oxford, collected and republished. 8vo. 7s. 6d.

MISCELLANEOUS and POSTHUMOUS WORKS of the Late HENRY THOMAS BUCKLE. Edited, with a Biographical Notice, by HELEN TAYLOR. 3 vols. 8vo. price 52s. 6d.

MISCELLANEOUS WRITINGS of JOHN CONINGTON, M.A. late Corps Professor of Latin in the University of Oxford. Edited by J. A. SYMONDS, M.A. With a Memoir by H. J. S. SMITH, M.A. 2 vols. 8vo. 28s.

ESSAYS, CRITICAL and BIOGRAPHICAL. Contributed to the *Edinburgh Review*. By HENRY ROGERS. New Edition, with Additions. 2 vols. crown 8vo. price 12s.

ESSAYS on some THEOLOGICAL CONTROVERSIES of the TIME. Contributed chiefly to the *Edinburgh Review*. By HENRY ROGERS. New Edition, with Additions. Crown 8vo. price 6s.

RECREATIONS of a COUNTRY PARSON. By A. K. H. B. FIRST and SECOND SERIES, crown 8vo. 3s. 6d. each.

The Common-place Philosopher in Town and Country. By A. K. H. B. Crown 8vo. price 3s. 6d.

Leisure Hours in Town; Essays Consolatory, Æsthetical, Moral, Social, and Domestic. By A. K. H. B. Crown 8vo. 3s. 6d.

The Autumn Holidays of a Country Parson; Essays contributed to *Fraser's Magazine*, &c. By A. K. H. B. Crown 8vo. 3s. 6d.

Seaside Musings on Sundays and Week-Days. By A. K. H. B. Crown 8vo. price 3s. 6d.

The Graver Thoughts of a Country Parson. By A. K. H. B. FIRST, SECOND, and THIRD SERIES, crown 8vo. 3s. 6d. each.

Critical Essays of a Country Parson, selected from Essays contributed to *Fraser's Magazine*. By A. K. H. B. Crown 8vo. 3s. 6d.

Sunday Afternoons at the Parish Church of a Scottish University City. By A. K. H. B. Crown 8vo. 3s. 6d.

Lessons of Middle Age; with some Account of various Cities and Men. By A. K. H. B. Crown 8vo. 3s. 6d.

Counsel and Comfort spoken from a City Pulpit. By A. K. H. B. Crown 8vo. price 3s. 6d.

Changed Aspects of Unchanged Truths; Memorials of St. Andrews Sundays. By A. K. H. B. Crown 8vo. 3s. 6d.

Present-day Thoughts; Memorials of St. Andrews Sundays. By A. K. H. B. Crown 8vo. 3s. 6d.

Landscapes, Churches, and Moralities. By A. K. H. B. Crown 8vo. price 3s. 6d.

SHORT STUDIES ON GREAT SUBJECTS. By JAMES ANTHONY FROUDE, M.A. late Fellow of Exeter Coll. Oxford. 2 vols. crown 8vo. price 12s. or 2 vols. demy 8vo. price 24s.

SELECTIONS from the WRITINGS of LORD MACAULAY. Edited, with Occasional Explanatory Notes, by GEORGE OTTO TREVELYAN, M.P. 1 vol. crown 8vo. *[In the press.]*

LORD MACAULAY'S MISCELLANEOUS WRITINGS:—

LIBRARY EDITION. 2 vols. 8vo. Portrait, 21s.

PEOPLE'S EDITION. 1 vol. crown 8vo. 4s. 6d.

LORD MACAULAY'S MISCELLANEOUS WRITINGS and SPEECHES.

STUDENT'S EDITION, in crown 8vo. price 6s.

The Rev. SYDNEY SMITH'S MISCELLANEOUS WORKS; including his Contributions to the *Edinburgh Review*. Crown 8vo. 6s.

The WIT and WISDOM of the Rev. SYDNEY SMITH; a Selection of the most memorable Passages in his Writings and Conversation. 16mo. 3s. 6d.

The ECLIPSE of FAITH; or, a Visit to a Religious Sceptic. By HENRY ROGERS. Latest Edition. Fcp. 8vo. price 5s.

Defence of the Eclipse of Faith, by its Author; a rejoinder to Dr. Newman's *Reply*. Latest Edition. Fcp. 8vo. price 3s. 6d.

CHIPS from a GERMAN WORKSHOP; Essays on the Science of Religion, on Mythology, Traditions, and Customs, and on the Science of Language. By F. MAX MÜLLER, M.A. &c. 4 vols. 8vo. £2. 18s.

ANALYSIS of the PHENOMENA of the HUMAN MIND. By JAMES MILL. A New Edition, with Notes, Illustrative and Critical, by ALEXANDER BAIN, ANDREW FINDLATER, and GEORGE GROTE. Edited, with additional Notes, by JOHN STUART MILL. 2 vols. 8vo. price 28s.

An INTRODUCTION to MENTAL PHILOSOPHY, on the Inductive Method. By J. D. MORELL, M.A. LL.D. 8vo. 12s.

PHILOSOPHY WITHOUT ASSUMPTIONS. By the Rev. T. P. KIRKMAN, F.R.S. Rector of Croft, near Warrington. 8vo. 10s. 6d.

The SENSES and the INTELLECT. By ALEXANDER BAIN, M.D. Professor of Logic in the University of Aberdeen. Third Edition. 8vo. 15s.

The EMOTIONS and the WILL. By ALEXANDER BAIN, LL.D. Professor of Logic in the University of Aberdeen. Third Edition, thoroughly revised, and in great part re-written. 8vo. price 15s.

MENTAL and MORAL SCIENCE: a Compendium of Psychology and Ethics. By the same Author. Third Edition. Crown 8vo. 10s. 6d. Or separately: PART I. *Mental Science*, 6s. 6d. PART II. *Moral Science*, 4s. 6d.

LOGIC, DEDUCTIVE and INDUCTIVE. By ALEXANDER BAIN, LL.D.
In TWO PARTS, crown 8vo. 10s. 6d. Each Part may be had separately :—
PART I. *Deduction*, 4s. PART II. *Induction*, 6s. 6d.

A BUDGET of PARADOXES. By AUGUSTUS DE MORGAN, F.R.A.S.
and C.P.S. 8vo. 15s.

APPARITIONS; a Narrative of Facts. By the Rev. B. W. SAVILE,
M.A. Author of 'The Truth of the Bible' &c. Crown 8vo. price 4s. 6d.

A TREATISE of HUMAN NATURE, being an Attempt to Introduce
the Experimental Method of Reasoning into Moral Subjects; followed by Dia-
logues concerning Natural Religion. By DAVID HUME. Edited, with Notes,
&c. by T. H. GREEN, Fellow and Tutor, Ball. Coll. and T. H. GROSE, Fellow
and Tutor, Queen's Coll. Oxford. 2 vols. 8vo. 28s.

ESSAYS MORAL, POLITICAL, and LITERARY. By DAVID HUME.
By the same Editors. 2 vols. 8vo. price 28s.

The PHILOSOPHY of NECESSITY; or, Natural Law as applicable to
Mental, Moral, and Social Science. By CHARLES BRAY. 8vo. 9s.

UEBERWEG'S SYSTEM of LOGIC and HISTORY of LOGICAL
DOCTRINES. Translated, with Notes and Appendices, by T. M. LINDSAY,
M.A. F.R.S.E. 8vo. price 16s.

FRAGMENTARY PAPERS on SCIENCE and other Subjects. By
the late Sir H. HOLLAND, Bart. Edited by his Son, the Rev. F. HOLLAND. 8vo.
price 14s.

Astronomy, Meteorology, Popular Geography, &c.

BRINKLEY'S ASTRONOMY. Revised and partly re-written, with
Additional Chapters, and an Appendix of Questions for Examination. By J. W.
BRUBBES, D.D. Fellow and Tutor of Trinity College, Dublin, and F. BRUNNOW,
Ph.D. Astronomer Royal of Ireland. Crown 8vo. price 6s.

OUTLINES of ASTRONOMY. By Sir J. F. W. HERSCHEL, Bart.
M.A. Latest Edition, with Plates and Diagrams. Square crown 8vo. 12s.

ESSAYS on ASTRONOMY, a Series of Papers on Planets and Meteors,
the Sun and Sun-surrounding Space, Stars and Star-Cloudlets; with a Dissertation
on the Transit of Venus. By R. A. PROCTOR, B.A. With Plates and Wood-
cuts. 8vo. 12s.

THE TRANSITS of VENUS; a Popular Account of Past and Coming
Transits, from the first observed by Horrocks A.D. 1639 to the Transit of
A.D. 2012. By R. A. PROCTOR, B.A. Second Edition, with 20 Plates (12 coloured)
and 38 Woodcuts. Crown 8vo. 8s. 6d.

The UNIVERSE and the COMING TRANSITS; Presenting Re-
searches into and New Views respecting the Constitution of the Heavens;
together with an Investigation of the Conditions of the Coming Transits of Venus.
By R. A. PROCTOR, B.A. With 22 Charts and 22 Woodcuts. 8vo. 16s.

The MOON; her Motions, Aspect, Scenery, and Physical Condition.
By R. A. PROCTOR, B.A. With Plates, Charts, Woodcuts, and Three Lunar
Photographs. Crown 8vo. 15s.

The SUN; RULER, LIGHT, FIRE, and LIFE of the PLANETARY
SYSTEM. By R. A. PROCTOR, B.A. Second Edition, with 10 Plates (7 co-
loured) and 107 Figures on Wood. Crown 8vo. 14s.

OTHER WORLDS THAN OURS; the Plurality of Worlds Studied under the Light of Recent Scientific Researches. By R. A. PROCTOR, B.A. Third Edition, with 14 Illustrations. Crown 8vo. 10s. 6d.

THE ORBS AROUND US; Familiar Essays on the Moon and Planets, Meteors and Comets, the Sun and Coloured Pairs of Stars. By R. A. PROCTOR, B.A. Second Edition, with Charts and 4 Diagrams. Crown 8vo. price 7s. 6d.

SATURN and its SYSTEM. By R. A. PROCTOR, B.A. 8vo. with 14 Plates, 14s. 4.

THE MOON, and the Condition and Configurations of its Surface. By EDMUND NEWIN, Fellow of the Royal Astronomical Society, &c. With 26 Maps and 5 Plates. Medium 8vo. 31s. 6d.

A NEW STAR ATLAS, for the Library, the School, and the Observatory, in Twelve Circular Maps (with Two Index Plates). Intended as a Companion to 'Webb's Celestial Objects for Common Telescopes.' With a Letterpress Introduction on the Study of the Stars, illustrated by 9 Diagrams. By R. A. PROCTOR, B.A. Crown 8vo. 5s.

SCHELLEN'S SPECTRUM ANALYSIS, in its application to Terrestrial Substances and the Physical Constitution of the Heavenly Bodies. Translated by JANE and C. LASSELL; edited, with Notes, by W. HUGGINS, LL.D. F.R.S. With 13 Plates (6 coloured) and 223 Woodcuts. 8vo. price 28s.

CELESTIAL OBJECTS for COMMON TELESCOPES. By the Rev. T. W. WEBB, M.A. F.R.A.S. Third Edition, revised and enlarged; with Maps, Plate, and Woodcuts. Crown 8vo. price 7s. 6d.

AIR and RAIN; the Beginnings of a Chemical Climatology. By ROBERT ANGUS SMITH, Ph.D. F.R.S. F.C.S. With 8 Illustrations. 8vo. 24s.

AIR and its RELATIONS to LIFE; being, with some Additions, the Substance of a Course of Lectures delivered at the Royal Institution of Great Britain. By W. N. HARTLEY, F.C.S. Demonstrator of Chemistry at King's College, London. Second Edition, with 66 Woodcuts. Small 8vo. 6s.

NAUTICAL SURVEYING, an INTRODUCTION to the PRACTICAL and THEORETICAL STUDY of. By J. K. LAUGHTON, M.A. Small 8vo. 6s.

DOVE'S LAW of STORMS, considered in connexion with the Ordinary Movements of the Atmosphere. Translated by R. H. SCOTT, M.A. 8vo. 10s. 6d.

KEITH JOHNSTON'S GENERAL DICTIONARY of GEOGRAPHY, Descriptive, Physical, Statistical, and Historical; forming a complete Gazetteer of the World. New Edition, revised and corrected. 1 vol. 8vo. [*Nearly ready.*]

THE PUBLIC SCHOOLS ATLAS of MODERN GEOGRAPHY. In 31 Coloured Maps, exhibiting clearly the more important Physical Features of the Countries delineated, and Noting all the Chief Places of Historical, Commercial, or Social Interest. Edited, with an Introduction, by the Rev. G. BUTLER, M.A. Imperial 8vo. or imperial 4to. 5s. cloth.

THE PUBLIC SCHOOLS MANUAL of MODERN GEOGRAPHY. By the Rev. GEORGE BUTLER, M.A. Principal of Liverpool College; Editor of 'The Public Schools Atlas of Modern Geography.' [*In preparation.*]

THE PUBLIC SCHOOLS ATLAS of ANCIENT GEOGRAPHY, in 25 Coloured Maps. Edited by the Rev. GEORGE BUTLER, M.A. Principal of Liverpool College. Imperial 8vo. or imperial 4to. 7s. 6d. cloth.

MAUNDER'S TREASURY of GEOGRAPHY, Physical, Historical, Descriptive, and Political. Edited by W. HUGHES, F.R.G.S. Revised Edition, with 7 Maps and 16 Plates. Fcp. 6s. cloth, or 10s. 6d. bound in calf.

Natural History and Popular Science.

TEXT-BOOKS of SCIENCE, MECHANICAL and PHYSICAL,
adapted for the use of Artisans and of Students in Public and Science Schools.

The following Text-Books in this Series may now be had:—

- ANDERSON'S Strength of Materials, small 8vo. 3s. 6d.
 ARMSTRONG'S Organic Chemistry, 9s. 6d.
 BARRY'S Railway Appliances, 3s. 6d.
 BLOXAM'S Metals, 3s. 6d.
 GOODEVE'S Elements of Mechanism, 3s. 6d.
 ——— Principles of Mechanics, 3s. 6d.
 GRIFFIN'S Algebra and Trigonometry, 3s. 6d. Notes, 3s. 6d.
 JENKIN'S Electricity and Magnetism, 3s. 6d.
 MAXWELL'S Theory of Heat, 3s. 6d.
 MERRIFIELD'S Technical Arithmetic and Mensuration, 3s. 6d. Key, 3s. 6d.
 MILLER'S Inorganic Chemistry, 3s. 6d.
 PREECE & SIVEWRIGHT'S Telegraphy, 3s. 6d.
 SHELLEY'S Workshop Appliances, 3s. 6d.
 THORPE'S Quantitative Chemical Analysis, 4s. 6d.
 THORPE & MUIR'S Qualitative Analysis, 3s. 6d.
 TILDEN'S Chemical Philosophy, 3s. 6d.
 WATSON'S Plane and Solid Geometry, 3s. 6d.

. Other Text-Books in extension of this Series are in active preparation.

ELEMENTARY TREATISE on PHYSICS, Experimental and Applied.

Translated and edited from GANOT'S *Éléments de Physique* by E. ATKINSON, Ph.D. F.C.S. Seventh Edition, revised and enlarged; with 4 Coloured Plates and 758 Woodcuts. Post 8vo. 15s.

NATURAL PHILOSOPHY for GENERAL READERS and YOUNG

PERSONS; being a Course of Physics divested of Mathematical Formulæ expressed in the language of daily life. Translated from GANOT'S *Cours de Physique* and by E. ATKINSON, Ph.D. F.C.S. Second Edition, with 2 Plates and 429 Woodcuts. Crown 8vo. price 7s. 6d.

HELMHOLTZ'S POPULAR LECTURES on SCIENTIFIC SUBJECTS.

Translated by E. ATKINSON, Ph.D. F.C.S. Professor of Experimental Science, Staff College. With an Introduction by Professor TYNDALL. 8vo. with numerous Woodcuts, price 12s. 6d.

On the SENSATIONS of TONE as a Physiological Basis for the

Theory of Music. By HERMANN L. F. HELMHOLTZ, M.D. Professor of Physics in the University of Berlin. Translated, with the Author's sanction, from the Third German Edition, with Additional Notes and an Additional Appendix, by ALEXANDER J. ELLIS, F.R.S. &c. 8vo. price 36s.

The HISTORY of MODERN MUSIC, a Course of Lectures delivered

at the Royal Institution of Great Britain. By JOHN HULLAH, Professor of Vocal Music in Queen's College and Bedford College, and Organist of Charterhouse. New Edition. 8vo. 8s. 6d.

The TRANSITION PERIOD of MUSICAL HISTORY; a Second

Course of Lectures on the History of Music from the Beginning of the Seventeenth to the Middle of the Eighteenth Century, delivered at the Royal Institution. By JOHN HULLAH. New Edition. 8vo. 10s. 6d.

SOUND. By JOHN TYNDALL, LL.D. D.C.L. F.R.S. Third Edition, including Recent Researches on Fog-Signalling; Portrait and Woodcuts. Crown 8vo. 10s. 6d.

HEAT and MODE of MOTION. By JOHN TYNDALL, LL.D. D.C.L. F.R.S. Fifth Edition. Plate and Woodcuts. Crown 8vo. 10s. 6d.

CONTRIBUTIONS to MOLECULAR PHYSICS in the DOMAIN of RADIANT HEAT. By J. TYNDALL, LL.D. D.C.L. F.R.S. With 2 Plates and 31 Woodcuts. 8vo. 16s.

RESEARCHES on DIAMAGNETISM and MAGNE-CRYSTALLIC ACTION; including the Question of Diamagnetic Polarity. By J. TYNDALL, M.D. D.C.L. F.R.S. With 6 plates and many Woodcuts. 8vo. 14s.

NOTES of a COURSE of SEVEN LECTURES on ELECTRICAL PHENOMENA and THEORIES, delivered at the Royal Institution, A.D. 1870. By JOHN TYNDALL, J.L.D., D.C.L., F.R.S. Crown 8vo. 1s. sewed; 1s. 6d. cloth.

SIX LECTURES on LIGHT delivered in America in 1872 and 1873. By JOHN TYNDALL, LL.D. D.C.L. F.R.S. Second Edition, with Portrait, Plate, and 59 Diagrams. Crown 8vo. 7s. 6d.

NOTES of a COURSE of NINE LECTURES on LIGHT delivered at the Royal Institution, A.D. 1869. By JOHN TYNDALL, LL.D. D.C.L. F.R.S. Crown 8vo. price 1s. sewed, or 1s. 6d. cloth.

FRAGMENTS of SCIENCE. By JOHN TYNDALL, LL.D. D.C.L. F.R.S. Third Edition, with a New Introduction. Crown 8vo. 10s. 6d.

LIGHT SCIENCE for LEISURE HOURS; a Series of Familiar Essays on Scientific Subjects, Natural Phenomena, &c. By R. A. PROCTOR, B.A. First and Second Series. Crown 8vo. 7s. 6d. each.

A TREATISE on MAGNETISM, General and Terrestrial. By HUMPHRY LLOYD, D.D. D.C.L., Provost of Trinity College, Dublin. 8vo. 10s. 6d.

ELEMENTARY TREATISE on the WAVE-THEORY of LIGHT. By HUMPHRY LLOYD, D.D. D.C.L., Provost of Trinity College, Dublin. Third Edition, revised and enlarged. 8vo. price 10s. 6d.

The CORRELATION of PHYSICAL FORCES. By the Hon. Sir W. R. GROVE, M.A. F.R.S. one of the Judges of the Court of Common Pleas. Sixth Edition, with other Contributions to Science. 8vo. price 15s.

The COMPARATIVE ANATOMY and PHYSIOLOGY of the VERTEBRATE ANIMALS. By RICHARD OWEN, F.R.S. D.C.L. With 1,472 Woodcuts. 3 vols. 8vo. £3. 13s. 6d.

PRINCIPLES of ANIMAL MECHANICS. By the Rev. S. HAUGHTON, F.R.S. Fellow of Trin. Coll. Dubl. M.D. Dubl. and D.C.L. Oxon. Second Edition, with 111 Figures on Wood. 8vo. 21s.

ROCKS CLASSIFIED and DESCRIBED. By BERNHARD VON COTTA. English Edition, by P. H. LAWRENCE; with English, German, and French Synonymes. Post 8vo. 14s.

The ANCIENT STONE IMPLEMENTS, WEAPONS, and ORNAMENTS of GREAT BRITAIN. By JOHN EVANS, F.R.S. F.S.A. With 2 Plates and 476 Woodcuts. 8vo. price 28s.

The NATIVE RACES of the PACIFIC STATES of NORTH AMERICA. By HUBERT HOWE BANCROFT. 5 vols. 8vo. with Maps, £6. 5s.

The ORIGIN of CIVILISATION and the PRIMITIVE CONDITION of MAN; Mental and Social Condition of Savages. By Sir JOHN LUBBOCK, Bart. &c. F.R.S. Third Edition, with 25 Woodcuts. 8vo. 18s.

BIBLE ANIMALS; being a Description of every Living Creature mentioned in the Scriptures, from the Ape to the Coral. By the Rev. J. G. WOOD, M.A. F.L.S. With about 112 Vignettes on Wood. 8vo. 14s.

HOMES WITHOUT HANDS; a Description of the Habitations of Animals, classed according to their Principle of Construction. By the Rev. J. G. Wood, M.A. F.L.S. With about 140 Vignettes on Wood. 8vo. 14s.

INSECTS AT HOME; a Popular Account of British Insects, their Structure, Habits, and Transformations. By the Rev. J. G. Wood, M.A. F.L.S. With upwards of 700 Illustrations. 8vo. price 14s.

INSECTS ABROAD; a Popular Account of Foreign Insects, their Structure, Habits, and Transformations. By J. G. Wood, M.A. F.L.S. Printed and illustrated uniformly with 'Insects at Home.' 8vo. price 21s.

STRANGE DWELLINGS; a description of the Habitations of Animals, abridged from 'Homes without Hands.' By the Rev. J. G. Wood, M.A. F.L.S. With about 60 Woodcut Illustrations. Crown 8vo. price 7s. 6d.

OUT of DOORS; a Selection of original Articles on Practical Natural History. By the Rev. J. G. Wood, M.A. F.L.S. With Eleven Illustrations from Original Designs engraved on Wood by G. Pearson. Crown 8vo. price 7s. 6d.

A FAMILIAR HISTORY of BIRDS. By E. STANLEY, D.D. F.R.S. late Lord Bishop of Norwich. Seventh Edition, with Woodcuts. Fcp. 3s. 6d.

The SEA and its LIVING WONDERS. By Dr. GEORGE HARTWIG. Latest revised Edition. 8vo. with many Illustrations, 10s. 6d.

The TROPICAL WORLD. By Dr. GEORGE HARTWIG. With above 160 Illustrations. Latest revised Edition. 8vo. price 10s. 6d.

The SUBTERRANEAN WORLD. By Dr. GEORGE HARTWIG. With 3 Maps and about 80 Woodcuts, including 8 full size of page. 8vo. price 10s. 6d.

The POLAR WORLD, a Popular Description of Man and Nature in the Arctic and Antarctic Regions of the Globe. By Dr. GEORGE HARTWIG. With 8 Chromoxylographs, 3 Maps, and 85 Woodcuts. 8vo. 10s. 6d.

THE AERIAL WORLD. By Dr. G. HARTWIG. New Edition, with 8 Chromoxylographs and 60 Woodcut Illustrations. 8vo. price 21s.

KIRBY and SPENCE'S INTRODUCTION to ENTOMOLOGY, or Elements of the Natural History of Insects. 7th Edition. Crown 8vo. 5s.

MAUNDER'S TREASURY of NATURAL HISTORY, or Popular Dictionary of Birds, Beasts, Fishes, Reptiles, Insects, and Creeping Things. With above 900 Woodcuts. Fcp. 8vo. price 6s. cloth, or 10s. 6d. bound in calf.

MAUNDER'S SCIENTIFIC and LITERARY TREASURY. New Edition, thoroughly revised and in great part rewritten, with above 1,000 new Articles, by J. Y. JOHNSON. Fcp. 8vo. 6s. cloth, or 10s. 6d. calf.

BRANDE'S DICTIONARY of SCIENCE, LITERATURE, and ART. Re-edited by the Rev. GEORGE W. COX, M.A. late Scholar of Trinity College, Oxford; assisted by Contributors of eminent Scientific and Literary Acquirements. New Edition, revised. 3 vols. medium 8vo. 63s.

HANDBOOK of HARDY TREES, SHRUBS, and HERBACEOUS PLANTS, containing Descriptions, Native Countries, &c. of a Selection of the Best Species in Cultivation; together with Cultural Details, Comparative Hardiness, Suitability for Particular Positions, &c. By W. B. HEMSLEY. Based on DECAISNE and NAUDIN'S *Manuel de l'Amateur des Jardins*, and including the 264 Original Woodcuts. Medium 8vo. 21s.

A GENERAL SYSTEM of BOTANY DESCRIPTIVE and ANALYTICAL.

By E. LE MAOUT, and J. DECAISNE, Members of the Institute of France. Translated by Mrs. HOOKER. The Orders arranged after the Method followed in the Universities and Schools of Great Britain, its Colonies, America, and India; with an Appendix on the Natural Method, and other Additions, by J. D. HOOKER, F.R.S. &c. Second Thousand, with 5,500 Woodcuts. Imperial 8vo. 31s. 6d.

The TREASURY of BOTANY, or Popular Dictionary of the Vegetable Kingdom; including a Glossary of Botanical Terms. Edited by J. LINDLEY, F.R.S. and T. MOORE, F.L.S. assisted by eminent Contributors. With 274 Woodcuts and 29 Steel Plates. Two Parts, fcp. 8vo. 12s. cloth, or 21s. calf.

The ELEMENTS of BOTANY for FAMILIES and SCHOOLS. Tenth Edition, revised by THOMAS MOORE, F.L.S. Fcp. 8vo. with 154 Woodcuts, 2s. 6d.

The ROSE AMATEUR'S GUIDE. By THOMAS RIVERS. Fourteenth Edition. Fcp. 8vo. 4s.

LOUDON'S ENCYCLOPÆDIA of PLANTS; comprising the Specific Character, Description, Culture, History, &c. of all the Plants found in Great Britain. With upwards of 12,000 Woodcuts. 8vo. 42s.

FOREST TREES and WOODLAND SCENERY, as described in Ancient and Modern Poets. By WILLIAM MENZIES, Deputy Surveyor of Windsor Forest and Parks, &c. With Twenty Chromo-lithographic Plates. Folio, price £5 5s.

Chemistry and Physiology.

A DICTIONARY of CHEMISTRY and the Allied Branches of other Sciences. By HENRY WATTS, F.R.S. assisted by eminent Contributors. Seven Volumes, medium 8vo. price £10. 16s. 6d.

ELEMENTS of CHEMISTRY, Theoretical and Practical. By W. ALLEN MILLER, M.D. late Prof. of Chemistry, King's Coll. London. New Edition. 3 vols. 8vo. PART I. CHEMICAL PHYSICS, 15s. PART II. INORGANIC CHEMISTRY, 21s. PART III. ORGANIC CHEMISTRY, New Edition in the press.

SELECT METHODS in CHEMICAL ANALYSIS, chiefly INORGANIC. By WILLIAM CROOKES, F.R.S. With 22 Woodcuts. Crown 8vo. price 12s. 6d.

A PRACTICAL HANDBOOK of DYEING and CALICO PRINTING. By WILLIAM CROOKES, F.R.S. With 11 Page Plates, 49 Specimens of Dyed and Printed Fabrics, and 36 Woodcuts. 8vo. 42s.

OUTLINES of PHYSIOLOGY, Human and Comparative. By JOHN MARSHALL, F.R.C.S. Surgeon to the University College Hospital. 2 vols. crown 8vo. with 122 Woodcuts, 32s.

HEALTH in the HOUSE; a Series of Lectures on Elementary Physiology in its application to the Daily Wants of Man and Animals, delivered to the Wives and Children of Working Men in Leeds and Saltaire. By CATHERINE M. BUCKTON. New Edition, revised. Small 8vo. Woodcuts, 2s.

The Fine Arts, and Illustrated Editions.

A DICTIONARY of ARTISTS of the ENGLISH SCHOOL: Painters, Sculptors, Architects, Engravers, and Ornamentists; with Notices of their Lives and Works. By S. REDGRAVE. 8vo. 16s.

MOORE'S IRISH MELODIES, with 161 Steel Plates from Original Drawings by D. MACLISE, R.A. Super-royal 8vo. 21s.

LORD MACAULAY'S LAYS of ANCIENT ROME. With 90 Illustrations on Wood, from the Antique, from Drawings by G. SCHAEFER. Fcp. 4to. 21s.

Miniature Edition of Lord Macaulay's Lays of Ancient Rome, with the Illustrations (as above) reduced in Lithography. Imp. 16mo. 10s. 6d.

POEMS. By WILLIAM B. SCOTT. I. Ballads and Tales. II. Studies from Nature. III. Sonnets &c. Illustrated by W. B. SCOTT (the Author) and L. ALMA TADEMA. Crown 8vo. price 15s.

HALF-HOUR LECTURES on the HISTORY and PRACTICE of the FINE and ORNAMENTAL ARTS. By WILLIAM B. SCOTT. Third Edition, with 50 Woodcuts. Crown 8vo. 8s. 6d.

The THREE CATHEDRALS DEDICATED to ST. PAUL, in LONDON; their History from the Foundation of the First Building in the Sixth Century to the Proposals for the Adornment of the Present Cathedral. By WILLIAM LONGMAN, F.A.S. With numerous Illustrations. Square crown 8vo. 21s.

IN FAIRYLAND; Pictures from the Elf-World. By RICHARD DOYLE. With a Poem by W. ALLINGHAM. With Sixteen Plates, containing Thirty-six Designs printed in Colours. Second Edition. Folio, price 15s.

The NEW TESTAMENT, illustrated with Wood Engravings after the Early Masters, chiefly of the Italian School. Crown 4to. 63s. cloth, gilt top; or £5 5s. elegantly bound in morocco.

SACRED and LEGENDARY ART. By MRS. JAMESON.

Legends of the Saints and Martyrs. New Edition, with 19 Etchings and 187 Woodcuts. 2 vols. square crown 8vo. 31s. 6d.

Legends of the Monastic Orders. New Edition, with 11 Etchings and 88 Woodcuts. 1 vol. square crown 8vo. 21s.

Legends of the Madonna. New Edition, with 27 Etchings and 165 Woodcuts. 1 vol. square crown 8vo. 21s.

The History of Our Lord, with that of his Types and Precursors. Completed by Lady EASTLAKE. Revised Edition, with 31 Etchings and 281 Woodcuts. 2 vols. square crown 8vo. 42s.

The Useful Arts, Manufactures, &c.

GWILT'S ENCYCLOPÆDIA of ARCHITECTURE, with above 1,600 Engravings on Wood. New Edition, revised and enlarged by WYATT PAPWORTH. 8vo. 52s. 6d.

HINTS on HOUSEHOLD TASTE in FURNITURE, UPHOLSTERY, and other Details. By CHARLES L. EASTLAKE, Architect. New Edition, with about 90 Illustrations. Square crown 8vo. 14s.

INDUSTRIAL CHEMISTRY; a Manual for Manufacturers and for use in Colleges or Technical Schools. Being a Translation of Professors Stohmann and Engler's German Edition of *PAYEN'S Précis de Chimie Industrielle*, by Dr. J. D. BARRY. Edited and supplemented by B. H. PAUL, Ph.D. 8vo. with Plates and Woodcuts. [In the press.]

URE'S DICTIONARY of ARTS, MANUFACTURES, and MINES. Seventh Edition, rewritten and enlarged by ROBERT HUNT, F.R.S. assisted by numerous Contributors eminent in Science and the Arts, and familiar with Manufactures. With above 2,100 Woodcuts. 3 vols. medium 8vo. £5 5s.

HANDBOOK of PRACTICAL TELEGRAPHY. By R. S. CULLEY Memb. Inst. C.E., Engineer-in-Chief of Telegraphs to the Post Office. Sixth Edition, with 14th Woodcuts and 5 Plates. 8vo. price 16s.

TELEGRAPHY. By W. H. PREECE, C.E. Divisional Engineer, P.O. Telegraphs; and J. SIVEWRIGHT, M.A. Superintendent (Engineering Department) P.O. Telegraphs. Small 8vo. with 160 Woodcuts, 3s. 6d.

RAILWAY APPLIANCES; a Description of Details of Railway Construction subsequent to the completion of the Earthworks and Masonry, including a short Notice of Railway Rolling Stock. By J. W. BARRY, Member of the Institution of Civil Engineers. Small 8vo. with 207 Woodcuts, 3s. 6d.

ENCYCLOPÆDIA of CIVIL ENGINEERING, Historical, Theoretical, and Practical. By E. CHESY, C.E. With above 3,000 Woodcuts. 8vo. 42s.

OCCASIONAL PAPERS on SUBJECTS connected with CIVIL ENGINEERING, GUNNERY, and Naval Architecture. By MICHAEL SCOTT, Memb. Inst. C.E. & of Inst. N.A. 2 vols. 8vo. with Plates, 42s.

NAVAL POWERS and their POLICY, with Tabular Statements of British and Foreign Ironclad Navies, giving Dimensions, Armour, Details of Armament, Engines, Speed, &c. By JOHN C. PAGET. 8vo. 10s. 6d.

TREATISE on MILLS and MILLWORK. By Sir W. FAIRBAIRN, Bart. F.R.S. New Edition, with 18 Plates and 322 Woodcuts, 2 vols. 8vo. 32s.

USEFUL INFORMATION for ENGINEERS. By Sir W. FAIRBAIRN, Bart. F.R.S. Revised Edition, with Illustrations. 3 vols. crown 8vo. price 31s. 6d.

The APPLICATION of CAST and WROUGHT IRON to Building Purposes. By Sir W. FAIRBAIRN, Bart. F.R.S. Fourth Edition, enlarged; with 6 Plates and 118 Woodcuts. 8vo. price 16s.

The THEORY of STRAINS in GIRDERS and similar Structures, with Observations on the application of Theory to Practice, and Tables of the Strength and other Properties of Materials. By BINDON B. STONEY, M.A. M. Inst. C.E. New Edition, royal 8vo. with 5 Plates and 123 Woodcuts, 36s.

A TREATISE on the STEAM ENGINE, in its various Applications to Mines, Mills, Steam Navigation, Railways, and Agriculture. By J. BOURNE, C.E. Eighth Edition; with Portrait, 37 Plates, and 546 Woodcuts. 4to. 42s.

CATECHISM of the STEAM ENGINE, in its various Applications to Mines, Mills, Steam Navigation, Railways, and Agriculture. By the same Author. With 89 Woodcuts. Fcp. 8vo. 6s.

HANDBOOK of the STEAM ENGINE. By the same Author, forming a KEY to the Catechism of the Steam Engine, with 67 Woodcuts. Fcp. 9s.

BOURNE'S RECENT IMPROVEMENTS in the STEAM ENGINE in its various applications to Mines, Mills, Steam Navigation, Railways, and Agriculture. By JOHN BOURNE, C.E. New Edition, with 124 Woodcuts. Fcp. 8vo. 6s.

PRACTICAL TREATISE on METALLURGY, adapted from the last German Edition of Professor KERL's *Metallurgy* by W. CROOKES, F.R.S. &c. and E. BÖHRIG, Ph.D. M.E. With 625 Woodcuts. 3 vols. 8vo. price £4 19s.

MITCHELL'S MANUAL of PRACTICAL ASSAYING. Fourth Edition, for the most part rewritten, with all the recent Discoveries incorporated, by W. CROOKES, F.R.S. With 199 Woodcuts. 8vo. 31s. 6d.

LOUDON'S ENCYCLOPÆDIA of AGRICULTURE: comprising the Laying-out, Improvement, and Management of Landed Property, and the Cultivation and Economy of Agricultural Produce. With 1,100 Woodcuts. 8vo. 21s.

LONDON'S ENCYCLOPÆDIA of Gardening: comprising the Theory and Practice of Horticulture, Floriculture, Arboriculture, and Landscape Gardening. With 1,000 Woodcuts. 8vo. 21s.

REMINISCENCES of FEN and MERE. By J. M. HEATHCOTE. With 27 Illustrations and 3 Maps. Square crown 8vo. price 28s.

Religious and Moral Works.

CHRISTIAN LIFE, its COURSE, its HINDRANCES, and its HELPS; Sermons preached mostly in the Chapel of Rugby School. By the late Rev. THOMAS ARNOLD, D.D. 8vo. 7s. 6d.

CHRISTIAN LIFE, its HOPES, its FEARS, and its CLOSE; Sermons preached mostly in the Chapel of Rugby School. By the late Rev. THOMAS ARNOLD, D.D. 8vo. 7s. 6d.

SERMONS chiefly on the INTERPRETATION of SCRIPTURE. By the late Rev. THOMAS ARNOLD, D.D. 8vo. price 7s. 6d.

SERMONS preached in the Chapel of Rugby School; with an Address before Confirmation. By the late Rev. THOMAS ARNOLD, D.D. Fcp. 8vo. 3s. 6d.

THREE ESSAYS on RELIGION: Nature; the Utility of Religion; Theism. By JOHN STUART MILL. 8vo. price 10s. 6d.

INTRODUCTION to the SCIENCE of RELIGION. Four Lectures delivered at the Royal Institution; with Two Essays on False Analogies and the Philosophy of Mythology. By F. MAX MÜLLER, M.A. Crown 8vo. 10s. 6d.

SUPERNATURAL RELIGION; an Inquiry into the Reality of Divine Revelation. Sixth Edition, carefully revised, with Eighty Pages of New Preface. 2 vols. 8vo. 24s.

NOTES on the EARLIER HEBREW SCRIPTURES. By Sir G. B. AIRY, K.C.B. 8vo. price 6s.

ISLAM under the ARABS. By ROBERT DRURIE OSBORN, Major in the Bengal Staff Corps. 8vo. 12s.

RELIGION and SCIENCE, their Relations to each other at the Present Day; Three Essays on the Grounds of Religious Beliefs. By STANLEY T. GIBSON, B.D., late Fellow of Queen's College, Cambridge. 8vo. 10s. 6d.

The PRIMITIVE and CATHOLIC FAITH in Relation to the Church of England. By the Rev. B. W. SAVILE, M.A. Rector of Shillingford, Exeter, Author of 'Truth of the Bible' &c. 8vo. price 7s.

SYNONYMS of the OLD TESTAMENT, their BEARING on CHRISTIAN FAITH and PRACTICE. By the Rev. R. B. GIRDLESTONE, M.A. 8vo. 15s.

An INTRODUCTION to the THEOLOGY of the CHURCH of ENGLAND, in an Exposition of the Thirty-nine Articles. By the Rev. T. P. BOULTBEE, LL.D. New Edition, Fcp. 8vo. price 6s.

An EXPOSITION of the 39 ARTICLES, Historical and Doctrinal. By E. HAROLD BROWNE, D.D. Lord Bishop of Winchester. New Edit. 8vo. 16s.

The LIFE and EPISTLES of ST. PAUL. By the Rev. W. J. CONYBEARE, M.A., and the Very Rev. J. S. HOWSON, D.D. Dean of Chester:—

LIBRARY EDITION, with all the Original Illustrations, Maps, Landscapes on Steel, Woodcuts, &c. 2 vols. 4to. 42s.

INTERMEDIATE EDITION, with a Selection of Maps, Plates, and Woodcuts. 2 vols. square crown 8vo. 21s.

STUDENT'S EDITION, revised and condensed, with 46 Illustrations and Maps. 1 vol. crown 8vo. price 9s.

HISTORY of the REFORMATION in EUROPE in the TIME of CALVIN. By the Rev. J. H. MEULE D'AUBIGNÉ, D.D. Translated by W. L. R. CATES. 7 vols. 8vo. price £5. 11s.

* * Vol. VIII. completing the Work, is preparing for publication.

NEW TESTAMENT COMMENTARIES. By the Rev. W. A. O'CONOR, B.A., Rector of St. Simon and St. Jude, Manchester. Crown 8vo.

Epistle to the Romans, price 3s. 6d.

Epistle to the Hebrews, 4s. 6d.

St. John's Gospel, 10s. 6d.

A CRITICAL and GRAMMATICAL COMMENTARY on ST. PAUL'S Epistles. By C. J. ELLICOTT, D.D. Lord Bishop of Gloucester and Bristol. 8vo.

Galatians, Fourth Edition, 8s. 6d.

Ephesians, Fourth Edition, 8s. 6d.

Pastoral Epistles, Fourth Edition, 10s. 6d.

Philippians, Colossians, and Philemon, Third Edition, 10s. 6d.

Thessalonians, Third Edition, 7s. 6d.

HISTORICAL LECTURES on the LIFE of OUR LORD. By C. J. ELLICOTT, D.D. Bishop of Gloucester and Bristol. Sixth Edition. 8vo. 12s.

EVIDENCE of the TRUTH of the CHRISTIAN RELIGION derived from the Literal Fulfilment of Prophecy. By ALEXANDER KEITH, D.D. 37th Edition, with Plates, in square 8vo. 12s. 6d.; 39th Edition, in post 8vo. 6s.

HISTORY of ISRAEL. By H. EWALD, late Professor of the Univ. of Göttingen. Translated by J. E. CARPENTER, M.A., with a Preface by RUSSELL MARTINEAU, M.A. 5 vols. 8vo. 63s.

The ANTIQUITIES of ISRAEL. By HEINRICH EWALD, late Professor of the University of Göttingen. Translated from the German by HENRY SHAEN SOLLY, M.A. 8vo. price 12s. 6d.

The TREASURY of BIBLE KNOWLEDGE; being a Dictionary of the Books, Persons, Places, Events, and other matters of which mention is made in Holy Scripture. By Rev. J. AYRE, M.A. With Maps, 16 Plates, and numerous Woodcuts. Fcp. 8vo. price 6s. cloth, or 10s. 6d. neatly bound in calf.

LECTURES on the PENTATEUCH and the MOABITE STONE.
By the Right Rev. J. W. COLENSO, D.D. Bishop of Natal. 8vo. 12s.

THE PENTATEUCH and BOOK of JOSHUA CRITICALLY EXAMINED.
By the Right Rev. J. W. COLENSO, D.D. Bishop of Natal. Crown 8vo. 6s.

AN INTRODUCTION to the STUDY of the NEW TESTAMENT,
Critical, Exegetical, and Theological. By the Rev. S. DAVIDSON, D.D. LL.D.
2 vols. 8vo. price 30s.

SOME QUESTIONS of the DAY. By the Author of 'Amy Herbert.'
Crown 8vo. price 2s. 6d.

THOUGHTS for the AGE. By the Author of 'Amy Herbert,' &c.
New Edition, revised. Fcp. 8vo. price 3s. 6d.

THE DOCTRINE and PRACTICE of CONFESSION in the CHURCH of ENGLAND. By the Rev. W. E. JELF, B.D. 8vo. price 7s. 6d.

PREPARATION for the HOLY COMMUNION ; the Devotions chiefly
' from the Works of JEREMY TAYLOR. By Miss SEWELL. 32mo. 3s.

LYRA GERMANICA, Hymns translated from the German by Miss C. WINKWORTH. Fcp. 8vo. price 5s.

SPIRITUAL SONGS for the SUNDAYS and HOLIDAYS through-
out the Year. By J. S. B. MONSELL, LL.D. Ninth Thousand. Fcp. 8vo. 5s.
18mo. 2s.

ENDEAVOURS after the CHRISTIAN LIFE: Discourses. By the
Rev. J. MARTINEAU, LL.D. Fifth Edition, carefully revised. Crown 8vo. 7s. 6d.

HYMNS of PRAISE and PRAYER, collected and edited by the Rev.
J. MARTINEAU, LL.D. Crown 8vo. 4s. 6d. 32mo. 1s. 6d.

THE TYPES of GENESIS. briefly considered as revealing the Develop-
ment of Human Nature. By ANDREW JUKES. Third Edition. Crown 8vo. 7s. 6d.

THE SECOND DEATH and the RESTITUTION of ALL THINGS ;
with some Preliminary Remarks on the Nature and Inspiration of Holy Scrip-
ture. By ANDREW JUKES. Fourth Edition. Crown 8vo. 3s. 6d.

WHATELY'S INTRODUCTORY LESSONS on the CHRISTIAN
Evidences. 18mo. 6d.

BISHOP JEREMY TAYLOR'S ENTIRE WORKS. With Life by
BISHOP HEBER. Revised and corrected by the Rev. C. P. EDEN. Complete in
Ten Volumes, 8vo. cloth, price £5. 5s.

Travels, Voyages, &c.

THE INDIAN ALPS, and How we Crossed them: being a Narrative
of Two Years' Residence in the Eastern Himalayas, and Two Months' Tour
into the Interior, towards Kinchinjunga and Mount Everest. By a Lady
PIONEER. With Illustrations from Original Drawings made on the spot by the
Authoress. Imperial 8vo. 42s.

TYROL and the TYROLESE; being an Account of the People and the Land, in their Social, Sporting, and Mountaineering Aspects. By W. A. BAILLIE GROHMAN. With numerous Illustrations from Sketches by the Author. Crown 8vo. 14s.

'The FROSTY CAUCASUS'; An Account of a Walk through Part of the Range, and of an Ascent of Elbruz in the Summer of 1874. By F. C. GROVE. With Eight Illustrations engraved on Wood by E. Whymper, from Photographs taken during the Journey, and a Map. Crown 8vo. price 15s.

A JOURNEY of 1,000 MILES through EGYPT and NUBIA to the SECOND CATARACT of the NILE. By AMELIA B. EDWARDS. With numerous Illustrations from Drawings by the Authoress, Map, Plans, Facsimiles, &c. Imperial 8vo. [*In the Autumn.*]

OVER the SEA and FAR AWAY; being a Narrative of a Ramble round the World. By THOMAS WOODBINE HINCHLIFF, M.A. F.R.G.S. President of the Alpine Club, Author of 'Summer Months among the Alps.' With 14 full-page Illustrations, engraved on Wood from Photographs and Sketches. Medium 8vo. 21s.

THROUGH BOSNIA and the HERZEGOVINA on FOOT during the INSURRECTION, August and September 1875; with an Historical Review of Bosnia, and a Glimpse at the Croats, Slavonians, and the Ancient Republic of Ragusa. By A. J. EVANS, B.A. F.S.A. With Map and 58 Wood Engravings from Photographs and Sketches by the Author. 8vo. 18s.

DISCOVERIES at EPHEBUS, including the Site and Remains of the Great Temple of Diana. By J. T. WOOD, F.S.A. 1 vol. Imperial 8vo. copiously illustrated. [*In the press.*]

MEMORIALS of the DISCOVERY and EARLY SETTLEMENT of the BERMUDAS or SOMERS ISLANDS, from 1615 to 1685. Compiled from the Colonial Records and other original sources. By Major-General J. H. LEFROY, R.A. C.B. F.R.S. &c. Governor of the Bermudas. 8vo. with Map. [*In the press.*]

ITALIAN ALPS; Sketches in the Mountains of Ticino, Lombardy, the Trentino, and Venetia. By DOUGLAS W. FRESHFIELD, Editor of 'The Alpine Journal.' Square crown 8vo. with Maps and Illustrations, price 15s.

The RIFLE and the HOUND in CEYLON. By Sir SAMUEL W. BAKER, M.A. F.R.G.S. New Edition, with Illustrations engraved on Wood by G. Pearson. Crown 8vo. 7s. 6d.

EIGHT YEARS in CEYLON. By Sir SAMUEL W. BAKER, M.A. F.R.G.S. New Edition, with Illustrations engraved on Wood, by G. Pearson. Crown 8vo. 7s. 6d.

TWO YEARS in FIJI, a Descriptive Narrative of a Residence in the Fijian Group of Islands; with some Account of the Fortunes of Foreign Settlers and Colonists up to the Time of the British Annexation. By LITTON FORBES, M.D. F.R.G.S. Crown 8vo. 8s. 6d.

MEETING the SUN; a Journey all round the World through Egypt, China, Japan, and California. By WILLIAM SIMPSON, F.R.G.S. With 48 Heliotypes and Wood Engravings from Drawings by the Author. Medium 8vo. 24s.

UNTRODDEN PEAKS and UNFREQUENTED VALLEYS; a Mid-summer Ramble among the Dolomites. By AMELIA B. EDWARDS. With a Map and 27 Wood Engravings. Medium 8vo. 21s.

The DOLOMITE MOUNTAINS; Excursions through Tyrol, Carinthia, Carniola, and Friuli, 1861-1863. By J. GILBERT and G. C. CHURCHILL, F.R.G.S. With numerous Illustrations. Square crown 8vo. 21s.

The ALPINE CLUB MAP of SWITZERLAND, with parts of the Neighbouring Countries, on the Scale of Four Miles to an Inch. Edited by R. C. NICHOLS, F.S.A. F.R.G.S. In Four Sheets, price 42s. or mounted in a case, 52s. 6d. Each Sheet may be had separately, price 12s. or mounted in a case, 15s.

MAP of the CHAIN of MONT BLANC, from an Actual Survey in 1863-1864. By ADAMS-REILLY, F.R.G.S. M.A.C. Published under the Authority of the Alpine Club. In Chromolithography on extra stout drawing-paper 28in. x 17in. price 10s. or mounted on canvas in a folding case, 12s. 6d.

HOW to SEE NORWAY. By Captain J. R. CAMPBELL. With Map and 5 Woodcuts. Fep. 8vo. price 5s.

GUIDE to the PYRENEES, for the use of Mountaineers. By CHARLES PACKE. With Map and Illustrations. Crown 8vo. 7s. 6d.

The ALPINE GUIDE. By JOHN BALL, M.R.I.A. late President of the Alpine Club. 3 vols. post. 8vo. Thoroughly Revised Editions, with Maps and Illustrations:—I. *Western Alps*, 6s. 6d. II. *Central Alps*, 7s. 6d. III. *Eastern Alps*, 10s. 6d. Or in Ten Parts, price 2s. 6d. each.

Introduction on Alpine Travelling in General, and on the Geology of the Alps, price 1s. Each of the Three Volumes or Parts of the *Alpine Guide* may be had with this INTRODUCTION prefixed, price 1s. extra.

Works of Fiction.

HIGGLEDY-PIGGLEDY; or, Stories for Everybody and Everybody's Children. By the Right Hon. E. M. KNATCHBULL-HUGHESSEN, M.P. With Nine Illustrations from Original Designs by R. Doyle, engraved on Wood by G. Pearson. Crown 8vo. price 6s.

WHISPERS from FAIRYLAND. By the Right Hon. E. H. KNATCHBULL-HUGHESSEN, M.P. With Nine Illustrations from Original Designs engraved on Wood by G. Pearson. Crown 8vo. price 6s.

NOVELS and TALES. By the Right Hon. B. DISRAELI, M.P. Cabinet Edition, complete in Ten Volumes, crown 8vo. price £3.

LOTHAIR, 6s.
CONINGSBY, 6s.
SYBIL, 6s.
TANCRED, 6s.
VENETIA, 6s.

HENRIETTA TEMPLE, 6s.
CONTARINI FLEMING, &c. 6s.
ALHOY, IXION, &c. 6s.
The YOUNG DUKE, &c. 6s.
VIVIAN GREY 6s.

CABINET EDITION of STORIES and TALES by Miss SEWELL:—

AMY HERBERT, 2s. 6d.
GERTRUDE, 2s. 6d.
The EARL'S DAUGHTER, 2s. 6d.
EXPERIENCE of LIFE, 2s. 6d.
CLEVE HALL, 2s. 6d.

IVORS, 2s. 6d.
KATHARINE ASHTON, 2s. 6d.
MARGARET PERCIVAL, 3s. 6d.
LANKTON PARSONAGE, 3s. 6d.
URSULA, 3s. 6d.

BECKER'S GALLUS; or, Roman Scenes of the Time of Augustus: with Notes and Excursions. New Edition. Post 8vo. 7s. 6d.

BECKER'S CHARICLES; a Tale illustrative of Private Life among the Ancient Greeks: with Notes and Excursions. New Edition. Post 8vo. 7s. 6d.

The MODERN NOVELIST'S LIBRARY. Each Work, in crown 8vo. complete in a Single Volume :—

- ATHERSTONE PRIORY, 2s. boards; 2s. 6d. cloth.
 MADEMOISELLE MOHI, 2s. boards; 2s. 6d. cloth.
 MELVILLE'S GLADIATORS, 2s. boards; 2s. 6d. cloth.
 ——— GOOD FOR NOTHING, 2s. boards; 2s. 6d. cloth.
 ——— HOLMBY HOUSE, 2s. boards; 2s. 6d. cloth.
 ——— INTERPRETER, 2s. boards; 2s. 6d. cloth.
 ——— KATE COVENTRY, 2s. boards; 2s. 6d. cloth.
 ——— QUEEN'S MAJESTIES, 2s. boards; 2s. 6d. cloth.
 ——— DIGBY GRAND, 2s. boards; 2s. 6d. cloth.
 ——— GENERAL BOUNCE, 2s. boards; 2s. 6d. cloth.
 TROLLOPE'S WARDEN, 1s. 6d. boards; 2s. cloth.
 ——— BARCHESTER TOWERS, 2s. boards; 2s. 6d. cloth.
 BRAMLEY-MOORE'S SIX SISTERS of the VALLEYS, 2s. boards; 2s. 6d. cloth.
 The BURGOMASTER'S FAMILY, 2s. boards; 2s. 6d. cloth.
 ELSA, a Tale of the Tyrolean Alps. Translated from the German of WILHELMINE VON HILBERN by Lady WALLACE. 2s. boards; 2s. 6d. cloth.

Poetry and The Drama.

POEMS. By WILLIAM B. SCOTT. I. Ballads and Tales. II. Studies from Nature. III. Sonnets &c. Illustrated by 17 Etchings by L. ALMA TADEMA and WILLIAM B. SCOTT. Crown 8vo. price 15s.

MOORE'S IRISH MELODIES, with 161 Steel Plates from Original Drawings by D. MACLISE, R.A. New Edition. Super-royal 8vo. 21s.

The LONDON SERIES of FRENCH CLASSICS. Edited by CH. CASSAL, LL.D. T. NANCYER, LL.B. and LÉONCE STÉVENARD. In course of publication, in fcp. 8vo. volumes. The following Plays, in the Division of the Drama in this Series, are now ready :—

- | | |
|--------------------------------|---|
| CORNÉILLE'S LE CID, 1s. 6d. | VOLTAIRE'S AIZIK, 1s. 6d. |
| CORNÉILLE'S POLYEUCTE, 1s. 6d. | LAMARTINE'S TOUSSAINT LOUVENTURE ^r |
| RACINE'S IPHIGÉNIE, 1s. 6d. | 2s. 6d. |
| VOLTAIRE'S ZAÏRE, 1s. 6d. | DE VIGNY'S CHATTERTON, 1s. 6d. |

BALLADS and LYRICS of OLD FRANCE; with other Poems. By A. LANG, M.A. Late fellow of Merton College, Oxford. Square fcp. 8vo. 5s.

SOUTHEY'S POETICAL WORKS, with the Author's last Corrections and copyright Additions. Medium 8vo. with Portrait and Vignette, 14s.

LAYS of ANCIENT ROME; with IVRY and the ARMADA. By the Right Hon. Lord MACAULAY. 16mo. 3s. 6d.

LORD MACAULAY'S LAYS of ANCIENT ROME. With 90 Illustrations on Wood, from the Antique, from Drawings by G. SCHARF. Fcp. 4to. 21s.

Miniature Edition of Lord Macaulay's Lays of Ancient Rome, with the Illustrations (as above) reduced in Lithography. Imp. 16mo. 10s. 6d.

The ÆNEID of VIRGIL Translated into English Verse. By JOHN CONINGTON, M.A. New Edition. Crown 8vo. 9s.

HORATII OPERA. Library Edition, with Marginal References and English Notes. Edited by the Rev. J. E. YONGE, M.A. 8vo. 21s.

The LYCIDAS and EPITAPHIUM DAMONIS of MILTON. Edited, with Notes and Introduction (including a Reprint of the rare Latin Version of the Lycidas, by W. Hogg, 1694), by C. S. JERRAM, M.A. Crown 8vo. 2s. 6d.

BOWDLER'S FAMILY SHAKSPEARE, cheaper Genuine Editions. Medium 8vo. large type, with 36 Woodcuts, price 14s. Cabinet Edition, with the same ILLUSTRATIONS, 6 vols. fcp. 8vo. price 21s.

POEMS. By JEAN INGELOW. 2 vols. fcp. 8vo. price 10s.

FIRST SERIES, containing 'DIVIDED,' 'The STAR'S MONUMENT,' &c. Sixteenth Thousand. Fcp. 8vo. price 5s.

SECOND SERIES, 'A STORY OF DOOM,' 'GLADYS and her ISLAND,' &c. Fifth Thousand. Fcp. 8vo. price 5s.

POEMS by Jean Ingelow. FIRST SERIES, with nearly 100 Illustrations, engraved on Wood by Dalziel Brothers. Fcp. 4to. 21s.

Rural Sports, &c.

DOWN the ROAD; Or, Reminiscences of a Gentleman Coachman. By C. T. S. BIRCH REYNARDSON. Second Edition, with Twelve Coloured Illustrations from Paintings by H. Alken. Medium 8vo. 21s.

ANNALS of the ROAD; Or, Notes on Mail and Stage Coaching in Great Britain. By CAPTAIN MALET, 18th Hussars. To which are added, Essays on the Road, by NIMROD. With 3 Woodcuts and 10 Illustrations in Chromolithography. Medium 8vo. 21s.

ENCYCLOPÆDIA of RURAL SPORTS; a complete Account, Historical, Practical, and Descriptive, of Hunting, Shooting, Fishing, Racing, and all other Rural and Athletic Sports and Pastimes. By D. P. BLAINE. With above 600 Woodcuts (20 from Designs by JOHN LEECH). 8vo. 21s.

The FLY-FISHER'S ENTOMOLOGY. By ALFRED RONALDS. With coloured Representations of the Natural and Artificial Insect. Sixth Edition, with 20 coloured Plates. 8vo. 14s.

A BOOK on ANGLING; a complete Treatise on the Art of Angling in every branch. By FRANCIS FRANCIS. New Edition, with Portrait and 16 other Plates, plain and coloured. Post 8vo. 15s.

WILCOCKS'S SEA-FISHERMAN; comprising the Chief Methods of Hook and Line Fishing, a Glance at Nets, and Remarks on Boats and Boating. New Edition, with 80 Woodcuts. Post 8vo. 12s. 6d.

HORSES and STABLES. By Colonel F. FITZWYGRAM, XV. the King's Hussars. With Twenty-four Plates of Illustrations, containing very numerous Figures engraved on Wood. 8vo. 10s. 6d.

The HORSE'S FOOT, and HOW to KEEP it SOUND. By W. MILES, Esq. Ninth Edition, with Illustrations. Imperial 8vo. 12s. 6d.

A PLAIN TREATISE on HORSE-SHOEING. By W. MILES, Esq. Sixth Edition. Post 8vo. with Illustrations, 2s. 6d.

STABLES and STABLE-FITTINGS. By W. MILES, Esq. Imp. 8vo. with 13 Plates, 15s.

REMARKS on HORSES' TEETH, addressed to Purchasers. By W. MILES, Esq. Post 8vo. 1s. 6d.

The HORSE: with a Treatise on Draught. By WILLIAM YOUATT. New Edition, revised and enlarged. 8vo. with numerous Woodcuts, 12s. 6d.

The DOG. By WILLIAM YOUATT. 8vo. with numerous Woodcuts, 6s.

The DOG in HEALTH and DISEASE. By STONEHENGE. With 70 Wood Engravings. Square crown 8vo. 7s. 6d.

The GREYHOUND. By STONEHENGE. Revised Edition, with 25 Portraits of Greyhounds. Square crown 8vo. 15s.

The OX; his Diseases and their Treatment: with an Essay on Parturition in the Cow. By J. R. DOBSON. Crown 8vo. with Illustrations, 7s. 6d.

Works of Utility and General Information.

The THEORY and PRACTICE of BANKING. By H. D. MACLEOD, M.A. Barrister-at-Law. Third Edition, thoroughly revised. 2 vols. 8vo. price 26s.

The ELEMENTS of BANKING. By HENRY DUNNING MACLEOD, Esq. M.A. of Trinity College, Cambridge, and the Inner Temple, Barrister-at-Law. Crown 8vo. price 7s. 6d.

MC'ULLOCH'S DICTIONARY, Practical, Theoretical, and Historical, of Commerce and Commercial Navigation. New and revised Edition. 8vo. 63s. Supplement, price 5s.

The CABINET LAWYER; a Popular Digest of the Laws of England, Civil, Criminal, and Constitutional: intended for Practical Use and General Information. Twenty-fifth Edition. Fcp. 8vo. price 9s.

BLACKSTONE ECONOMISED, a Compendium of the Laws of England to the Present time, in Four Books, each embracing the Legal Principles and Practical Information contained in their respective volumes of Blackstone, supplemented by Subsequent Statutory Enactments, Important Legal Decisions, &c. By D. M. AIRD, Barrister-at-Law. Revised Edition. Post 8vo. 7s. 6d.

PEWTNER'S COMPREHENSIVE SPECIFIER; a Guide to the Practical Specification of every kind of Building-Artificers' Work, with Forms of Conditions and Agreements. Edited by W. YOUNG. Crown 8vo. 6s.

WILLICH'S POPULAR TABLES for ascertaining according to the Carlisle Table of Mortality the Value of Lifehold, Leasehold, and Church Property, Renewal Fines, Reversions, &c.; also Interest, Legacy, Succession Duty, and various other useful Tables. Eighth Edition. Post 8vo. 10s.

HINTS to MOTHERS on the MANAGEMENT of their HEALTH during the Period of Pregnancy and in the Lying-in Room. By the late THOMAS BULL, M.D. Fcp. 8vo. 5s.

The MATERNAL MANAGEMENT of CHILDREN in HEALTH and Disease. By the late THOMAS BULL, M.D. Fcp. 8vo. 5s.

The THEORY of the MODERN SCIENTIFIC GAME of WHIST. By WILLIAM POLE, F.R.S. Seventh Edition, enlarged. Fcp. 8vo. 2s. 6d.

The CORRECT CARD; or, How to Play at Whist: a Whist Catechism. By Captain A. CAMPBELL-WALKER, F.R.G.S. late 79th Highlanders; Author of 'The Rifle, its Theory and Practice.' 32mo. 2s. 6d.

CHESS OPENINGS. By F. W. LONGMAN, Balliol College, Oxford. Second Edition revised. Fcp. 8vo. 2s. 6d.

THREE HUNDRED ORIGINAL CHESS PROBLEMS and STUDIES. By JAMES PIERCE, M.A. and W. T. PIERCE. With numerous Diagrams. Square fcp. 8vo. 7s. 6d. SUPPLEMENT, price 2s. 6d.

A SKETCH of the HISTORY of TAXES in ENGLAND from the Earliest Times to the Present Day By STEPHEN DOWELL. Vol. 1. to the Civil War 1642. 8vo. 10s. 6d.

The NEW CODE of the Education Department, with Notes, Analysis, Appendix, and Index, and a Sketch of the Administration of the Grants for Public Elementary Education (1839-1876). By H. J. GIBBS, and J. W. EDWARDS, Barrister-at-Law. Second Edition, revised and adapted to the New Code, 1876. Crown 8vo. 3s. 6d.

A PRACTICAL TREATISE on BREWING; with Formulæ for Public Brewers, and Instructions for Private Families. By W. BLACK. 8vo. 10s. 6d.

MODERN COOKERY for PRIVATE FAMILIES, reduced to a System of Easy Practice in a Series of carefully-tested Receipts. By ELIZA ACTON. Newly revised and enlarged; with 8 Plates and 150 Woodcuts. Fcp. 8vo. 6s.

MANNING'S TREASURY of KNOWLEDGE and LIBRARY of Reference; comprising an English Dictionary and Grammar, Universal Gazetteer, Classical Dictionary, Chronology, Law Dictionary, a synopsis of the Peerage, useful Tables, &c. Revised Edition. Fcp. 8vo. 6s. cloth, or 10s. 6d. calf.

Knowledge for the Young.

The STEPPING-STONE to KNOWLEDGE; or upwards of 700 Questions and Answers on Miscellaneous Subjects, adapted to the capacity of Infant minds. New Edition, revised. 18mo. 1s.

SECOND SERIES of the STEPPING-STONE to KNOWLEDGE: Containing upwards of 800 Questions and Answers on Miscellaneous Subjects not contained in the FIRST SERIES. 18mo. 1s.

The STEPPING-STONE to GEOGRAPHY: Containing several Hundred Questions and Answers on Geographical Subjects. 18mo. 1s.

The STEPPING-STONE to ENGLISH HISTORY; Questions and Answers on the History of England. 18mo. 1s.

The STEPPING-STONE to BIBLE KNOWLEDGE; Questions and Answers on the Old and New Testaments. 18mo. 1s.

The STEPPING-STONE to BIOGRAPHY; Questions and Answers on the Lives of Eminent Men and Women. 18mo. 1s.

The STEPPING-STONE to IRISH HISTORY: Containing several Hundred Questions and Answers on the History of Ireland. 18mo. 1s.

The STEPPING-STONE to FRENCH HISTORY: Containing several Hundred Questions and Answers on the History of France. 18mo. 1s.

The STEPPING-STONE to ROMAN HISTORY: Containing several Hundred Questions and Answers on the History of Rome. 18mo. 1s.

The STEPPING-STONE to GRECIAN HISTORY: Containing several Hundred Questions and Answers on the History of Greece. 18mo. 1s.

The STEPPING-STONE to ENGLISH GRAMMAR: Containing several Hundred Questions and Answers on English Grammar. 18mo. 1s.

The STEPPING-STONE to FRENCH PRONUNCIATION and CONVERSATION: Containing several Hundred Questions and Answers. 18mo. 1s.

The STEPPING-STONE to ASTRONOMY: Containing several Hundred familiar Questions and Answers on the Earth and the Solar and Stellar Systems. 18mo. 1s.

The STEPPING-STONE to MUSIC: Containing several Hundred Questions on the Science; also a short History of Music. 18mo. 1s.

The STEPPING-STONE to NATURAL HISTORY: VERTEBRATE OR BACK-BONED ANIMALS. PART I. *Mammalia*; PART II. *Birds, Reptiles, and Fishes*. 18mo. 1s. each Part.

THE STEPPING-STONE to ARCHITECTURE; Questions and Answers explaining the Principles and Progress of Architecture from the Earliest Times. With 100 Woodcuts. 18mo. 1s.

INDEX.

ACTON'S Modern Cookery	27
AIRD'S Blackstone Economised	26
AIRY'S Notes on the Hebrew Scriptures.....	19
Alpine Club Map of Switzerland	23
Alpine Guide (The)	23
AMOS'S Jurisprudence	5
Principles of the Constitution	6
ANDERSON'S Strength of Materials.....	13
ARMSTRONG'S Organic Chemistry.....	13
ARNOLD'S (Dr.) Christian Life	19
Lectures on Modern History	2
Miscellaneous Works	9
Sermons	19
School Sermons	19
(T.) Manual of English Literature	8
Atherstone Priory	24
Autumn Holidays of a Country Parson	9
AYLE'S Treasury of Bible Knowledge	20
BACON'S Essays, by WHATELY	7
Life and Letters, by SPEDDING	5
Works, edited by SPEDDING	7
BAIN'S Emotions and Will	10
Logic, Deductive and Inductive	11
Mental and Moral Science	10
on the Senses and Intellect	10
BAKER'S 2 works on Ceylon	22
BALL'S Alpine Guide	23
BANCROFT'S Native Races of the Pacific ..	14
BARRY on Railway Appliances	18
BECKER'S Charicles and Gallus	23
BLACK'S Treatise on Brewing	27
BLACKLEY'S German-English Dictionary ..	9
BLAINE'S Rural Sports.....	25
BLOXAM'S Metals	13
BOULTREE on 39 Articles	20
BOURNE'S Catechism of the Steam Engine ..	18
Handbook of Steam Engine	18
Improvements in the Steam	18
Engine	18
Treatise on the Steam Engine	18
BOWDLER'S Family SHAKESPEARE	25
BRAMLEY-MOORE'S Six Sisters of the	24
Valleys.....	24
BRANDE'S Dictionary of Science, Litera-	15
ture, and Art	15
BRAY'S Philosophy of Necessity	11
BRINKLEY'S ASTRONOMY	11
BROWNE'S Exposition of the 39 Articles.....	20
BUCKLE'S History of Civilization	3

BUCKLE'S Miscellaneous Works.....	9
BUCKTON'S Health in the House (Physio-	6
logical Lectures)	26
BULL'S Hints to Mothers	27
Maternal Management of Children	21
Burgomaster's Family (The)	5
BURKE'S Rise of Great Families.....	5
Vicissitudes of Families.....	5
Cabinet Lawyer	26
CAMPBELL'S Norway	24
CATES'S Biographical Dictionary	5
and WOODWARD'S Encyclopædia	3
Changed Aspects of Unchanged Truths.....	10
CHESNEY'S Indian Polity	3
Modern Military Biography	4
Waterloo Campaign.....	2
COLESSEO (Bishop) on Pentateuch	21
on Moulshite Stone, &c.	21
Commonplace Philosopher, by A.K.H.B.	9
COMTE'S Positive Philosophy	6
CONGREVE'S Politics of Aristotle	6
CONINGTON'S Translation of the <i>Aeneid</i>	21
Miscellaneous Writings	9
CONTANSEAU'S French Dictionaries	8
CONYBEARE and HOWSON'S St. Paul	20
COTTON'S (Bishop) Memoir	4
Counsel and Comfort from a City Pulpit.....	10
COX'S Aryan Mythology	3
Crusades.....	4
History of Greece	2
General ditto	2
Greeks and Persians	2
Tale of the Great Persian War	2
Tales of Ancient Greece.....	3
CRAWLEY'S Thucydides.....	3
CRAIGTON'S Age of Elizabeth	4
CRESY'S Civil Engineering	18
Critical Essays of a Country Parson	9
CROOKER'S Chemical Analysis	16
Dyeing and Calico Printing	16
CULLEY'S Handbook of Telegraphy.....	19
D'AUBIGNÉ'S Reformation	20
DAVIDSON'S Introduction to the New Testa-	21
ment	21
DECAHNE and LE MAOUT'S Botany	16
DE MORGAN'S Budget of Paradoxes.....	11

DEMOSTHENES' Oration on the Crown, translated by COLLIER	7	GREVILLE's Journal	1
DE TOCQUEVILLE's Democracy in America	7	GRIFFIN's Algebra and Trigonometry	13
DISRAELI's Lord George Bentinck	5	GROHMANN's Tyrol and the Tyrolese	22
———— Novels and Tales	23	GROVE on Correlation of Physical Forces	14
DOBSON on the Ox	20	————'s (F. C.) Frosty Caucasus	22
DOVE on Storms	12	GWILT's Encyclopædia of Architecture	17
DOWELL's History of Taxes	27		
DOYLE's Fairyland	17		
		HALE's Fall of the Stuarts	4
EASTLAKE's Hints on Household Taste	17	HARRISON's Order and Progress	7
EDWARDS's Journey of 1400 Miles through ' Egypt and Nubia	22	HARTLEY on the Air	12
———— Untrodden Peaks	22	HARTWIG's Aerial World	15
Elements of Botany	16	———— Polar World	15
ELLICOTT's Commentary on Ephesians	20	———— Sea and its Living Wonders	15
———— Galatians	20	———— Subterranean World	15
———— Pastoral Epist.	20	———— Tropical World	15
———— Philippians, &c	20	HAUGHTON's Animal Mechanics	14
———— Thessalonians	20	HAYWARD's Essays	5
———— Lectures on the Life of Christ	20	HEATHCOTE's Reminiscences of Fen and Mere	19
EVANS' (A. J.) Bonnia	22	HEINE's Life, Works, and Opinions, by STIGAND	5
———— (J.) Ancient Stone Implements	14	HELMHOLTZ on Tone	13
Elsa; a Tale of the Tyrolean Alps	21	———— Popular Lectures	13
EWALD's Antiquities of Israel	20	HEMSLEY's Handbook of Trees and Plants	15
———— History of Israel	20	HERSCHEL's Outlines of Astronomy	11
		HINGLIFF's Over the Sea and Far Away	22
FAIRBAIN's Applications of Iron	18	HOLLAND's Fragmentary Papers	11
———— Information for Engineers	18	HOLMS on the Army	3
———— Life	4	HULLAN's History of Modern Music	13
———— Mills and Millwork	18	———— Transition Period	13
FARRAR's Chapters on Language	7	HUME's Essays	11
———— Families of Speech	7	———— Treatise on Human Nature	11
FITZWYGRAM on Horses and Stables	25		
FORBES's Two Years in Fiji	22	INNE's Roman History	2
FRANCIS's Fishing Book	25	Indian Alps (The), by a Lady Pioneer	21
FRESHFIELD's Italian Alps	22	INGELOW's Poems	25
FROUDE's English in Ireland	1		
———— History of England	1	JAMESON's Saints and Martyrs	17
———— Short Studies on Great Subjects	10	———— Legends of the Madonna	17
		———— Monastic Orders	17
GAIRDNER's Houses of Lancaster and York	4	JAMESON and EASTLAKE's Saviour	17
———— Puritan Revolution	4	JELF on Confession in the English Church	21
GANOT's Elementary Physics	13	JENKIN's Electricity and Magnetism	13
———— Natural Philosophy	13	JERRAM's Lycidas of Milton	25
GARDINER's Buckingham and Charles	2	JERROLD's Life of Napoleon	4
———— Thirty Years' War	4	JOHNSTON's Geographical Dictionary	12
GEFFCKEN on Church and State	5	JUKES's Types of Genesis	21
German Home Life	9	———— on Second Death	21
GIBBS & EDWARDS's New Code	27		
GIBSON's Religion and Science	19	KALISON's Commentary on the Bible	6
GILBERT and CHUBBOKILL's Dolomites	23	KEITH on Fulfilment of Prophecy	20
GIRDLESTONE's Bible Synonyms	20	KERL's Metallurgy	19
GOODEVE's Mechanism	13	KINGSLEY's Lectures delivered in America	9
———— Mechanics	13	KIRBY and SPENCE's Entomology	15
GRANT's Ethics of Aristotle	6	KIRKMAN's Philosophy	10
Graver Thoughts of a Country Parson	9	KNATCHBULL-HUGHESSEN's Higgledy-Pig- gledy	22
		KNATCHBULL-HUGHESSEN's Whispers from Fairyland	23

Landscapes, Churches, and Moralities, by A. K. H. B.	10	MAY's Constitutional History of England... ..	1
LANG's Ballads and Lyrics	24	— History of Democracy	1
LATHAM's New English Dictionary	7	MELVILLE's Novels and Tales	24
— Johnson's Dictionary	8	MENZIES' Forest Trees	16
— Handbook of the English Lan- guage	7	MERIVALE's Fall of the Roman Republic... ..	2
LAUGHTON's Nautical Surveying	12	— General History of Rome	2
LAWRENCE on Rocks	14	— Romans under the Empire	2
LECKY's History of European Morals	3	MERRIFIELD's Arithmetic & Mensuration ..	13
— Rationalism	3	MILES on Horse's Feet and Horseshoeing ...	25
— Leaders of Public Opinion	5	— Horse's Teeth and Stables	26
LEFROY's Bermudas	22	MILL (J.) on the Mind	10
Leisure Hours in Town, by A. K. H. B.	9	MILL (J. S.) on Liberty	7
Lessons of Middle Age, by A. K. H. B.	10	— on Representative Government	7
LEWIS' History of Philosophy	3	— on Utilitarianism	7
LEWIS on the Influence of Authority in Matters of Opinion	6	— (J. S.) Autobiography	4
LIDDELL and SCOTT's Two Lessons	8	— Dissertations and Discussions	7
LINDSEY and MOORE's Treasury of Botany ..	16	— Essays on Religion &c.	19
LLOYD's Magnetism	14	— Political Economy	7
— Wave-Theory of Light	14	— System of Logic	7
London Series of French Classics	21	— Hamilton's Philosophy	7
LONGMAN's (W.) Edward the Third	2	— Unsettled Questions	7
— Lectures on History of England	2	MILLER's Elements of Chemistry	16
— Old and New St. Paul's	17	— Inorganic Chemistry	13
— Chess Openings	27	MINTO's (Lord) Life and Letters	4
— (F. W.) German Dictionary	9	MITCHELL's Manual of Assaying	19
LOUDON's Agriculture	19	MONSIELL's Spiritual Songs	21
— Gardening	19	MOORE's Irish Melodies	24
— Plants	16	MOORE's Mental Philosophy	10
LUDLOW's War of American Independence ..	4	MULLER's (MAX) Chieftains from a German Workshop	10
LUTBROCK on Origin of Civilisation	11	— Lectures on Language	8
Lyra Germanica	21	— Science of Religion	19
MACAULAY's (Lord) Essays	3	NEISON on the Moon	12
— History of England	1	New Reformation, by THEODORUS	1
— Lays of Ancient Rome	24	New Testament, Illustrated Edition	17
— Life and Letters	4	O'CONOR's Commentary on Hebrews	20
— Miscellaneous Writings	10	— Romans	20
— Speeches	7	— St. John's Gospel	20
— Complete Works	1	ODLING's Course of Practical Chemistry ...	16
MACLEOD's Economical Philosophy	7	OSBORN's Islam	19
— Theory and Practice of Banking	26	OWEN's Comparative Anatomy and Physio- logy of Vertebrate Animals	11
— Elements of Banking	26	PACKER's Guide to the Pyrenees	23
MACCULLOCH's Dictionary of Commerce ..	26	PACKT's Naval Powers	18
Mademoiselle Mori	21	PATTISON's Casaubon	5
MALET's Annals of the Road	25	PAYEN's Industrial Chemistry	18
MALLESON's Genoese Studies	3	PEWTERER's Comprehensive Specifier	26
— Native States of India	3	PIERCE's Chess Problems	27
MARSHALL's Physiology	16	POLK on Whist	27
MARSHMAN's Life of Havelock	5	PRECKE and SIVEWRIGHT's Telegraphy ...	18
— History of India	2	PRENDERGAST's Mastery of Languages	9
MARTINEAU's Christian Life	21	Present-Day Thoughts, by A. K. H. B.	10
— Hymns	21	PROCTOR's Astronomical Essays	11
MAUNDER's Biographical Treasury	5	— Moon	11
— Geographical Treasury	12	— New Star Atlas	12
— Historical Treasury	3	— Orbs Around Us	12
— Scientific and Literary Treas- ury	15	— Plurality of Worlds	12
— Treasury of Knowledge	27		
— Treasury of Natural History	15		
MAXWELL's Theory of Heat	13		

PROCTOR'S Saturn and its System.....	12	TAYLOR'S History of India.....	2
Scientific Essays.....	14	(Jeremy) Works, edited by EDEN.....	21
Sun.....	11	Text-Books of Science.....	7
Transits of Venus.....	11	THOMSON'S Laws of Thought.....	7
Universe.....	11	THORPE'S Quantitative Analysis.....	13
Public Schools Atlases (The).....	12	THORPE and MUIR'S Qualitative Analysis.....	13
Modern Geography.....	12	TILNEY'S Chemical Philosophy.....	21
RAWLINSON'S Parthia.....	2	TODD (A.) on Parliamentary Government.....	1
Sassanian Monarchy.....	2	TRENCH'S Realities of Irish Life.....	4
Recreations of a Country Parson.....	9	TREVELYAN'S Selections from MACAU-LAY'S Writings.....	10
REDGRAVE'S Dictionary of Artists.....	17	TROLLOPE'S Barchester Towers.....	24
REILLY'S Map of Mont Blanc.....	23	Warden.....	24
REIFF'S Memoirs.....	4	Twiss's Law of Nations during the Time of War.....	5
REYNARDSON'S Down the Road.....	25	TYNDALL on Diamagnetism.....	14
RICH'S Dictionary of Antiquities.....	8	Electricity.....	14
RIVERS' Free Amateur's Guide.....	16	Heat.....	13
ROBERTS' Eclipse of Faith.....	10	Sound.....	13
Defence of ditto.....	10	American Lectures on Light.....	14
ESSAYS.....	9	Fragments of Science.....	14
ROBERT'S English Thesaurus of Classified Words and Phrases.....	8	Lectures on Light.....	14
RONALDSON'S Fly-Fisher's Entomology.....	25	Molecular Physics.....	14
ROSCOE'S Outlines of Civil Procedure.....	6	URBERWEG'S System of Logic.....	11
RUSSELL'S (Lord) Recollections and Suggestions.....	1	URR'S Arts, Manufactures, and Mines.....	18
SANDARS'S Justinian Institutes.....	6	WALKER on Whist.....	27
SAVILLE on Apparitions.....	10	WARBURTON'S Edward the Third.....	4
on Primitive Faith.....	19	WATSON'S Geometry.....	13
SCHLEIER'S Spectrum Analysis.....	12	WATTS'S Dictionary of Chemistry.....	16
SCOTT'S Lectures on the Fine Arts.....	17	WEBB'S Objects for Common Telescopes.....	12
Poems, illustrated.....	17, 24	WELLINGTON'S Life, by GLEIG.....	5
Papers on Engineering.....	18	WHATELY'S English Synonyms.....	6
Seaside Musings by A. K. H. B.....	9	Christian Evidences.....	21
SEEBORN'S Oxford Reformers of 1498.....	2	Logic.....	6
Protestant Revolution.....	3	Rhetoric.....	6
SEWELL'S Preparation for Communion.....	21	WHITE'S Latin-English and English-Latin Dictionaries.....	8
Questions of the Day.....	21	WILCOCKS'S Sea Fisherman.....	25
History of France.....	3	WILLIAMS'S Aristotle's Ethics.....	6
Tales and Stories.....	21	WILLICH'S Popular Tables.....	25
Thoughts for the Age.....	21	WOOD'S (J. G.) Bible Animals.....	14
SHELLEY'S Workshop Appliances.....	13	Homes without Hands.....	16
SHORT'S Church History.....	3	Insects at Home.....	15
SIMPSON'S Meeting the Sun.....	22	Abroad.....	15
SMITH'S (SYDNEY) ESSAYS.....	10	Out of Doors.....	15
Wit and Wisdom.....	10	Strange Dwellings.....	15
(Dr. R. A.) Air and Rain.....	12	(J. T.) Ephesus.....	22
FOOTHY'S Doctor.....	8	WYATT'S History of Prussia.....	3
Poetical Works.....	21	YONGE'S English-Greek Lexicons.....	8
STANLEY'S History of British Birds.....	15	Horace.....	25
STEPHEN'S Ecclesiastical Biography.....	5	YOUATT on the Dog.....	26
Stepping Stones (the Serfs).....	27, 28	on the Horse.....	26
STOCKMAN'S Memoirs.....	4	ZELLER'S Socrates.....	6
STONEHENGE on the Dog.....	26	Stoics, Epicureans, and Sceptics.....	6
on the Greyhound.....	26	Plato.....	6
STONEY on Strains.....	18	ZIMMERN'S Schopenhauer.....	4
Sunday Afternoons, by A. K. H. B.....	9		
Supernatural Religion.....	19		
SWINBOURNE'S Picture Logic.....	6		

